

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15HH1N0B02	1	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N0C02	1	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N0S02	1	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N1B02	1.1	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N1C02	1.1	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N1S02	1.1	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N2B02	1.2	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N2C02	1.2	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N2S02	1.2	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N3B02	1.3	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N3C02	1.3	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N3S02	1.3	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N5B02	1.5	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N5C02	1.5	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N5S02	1.5	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N6B02	1.6	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N6C02	1.6	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N6S02	1.6	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N8B02	1.8	±0.1nH	950mA	0.08	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N8C02	1.8	±0.2nH	950mA	0.08	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH1N8S02	1.8	±0.3nH	950mA	0.08	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N0B02	2	±0.1nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N0C02	2	±0.2nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N0S02	2	±0.3nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N2B02	2.2	±0.1nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N2C02	2.2	±0.2nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N2S02	2.2	±0.3nH	900mA	0.09	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N4B02	2.4	±0.1nH	850mA	0.11	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N4C02	2.4	±0.2nH	850mA	0.11	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N4S02	2.4	±0.3nH	850mA	0.11	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N7B02	2.7	±0.1nH	800mA	0.12	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N7C02	2.7	±0.2nH	800mA	0.12	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH2N7S02	2.7	±0.3nH	800mA	0.12	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N0B02	3	±0.1nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N0C02	3	±0.2nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N0S02	3	±0.3nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N3B02	3.3	±0.1nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N3C02	3.3	±0.2nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N3S02	3.3	±0.3nH	800mA	0.125	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N6B02	3.6	±0.1nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N6C02	3.6	±0.2nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N6S02	3.6	±0.3nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N9B02	3.9	±0.1nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N9C02	3.9	±0.2nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH3N9S02	3.9	±0.3nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N3B02	4.3	±0.1nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N3C02	4.3	±0.2nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N3S02	4.3	±0.3nH	750mA	0.14	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N7B02	4.7	±0.1nH	700mA	0.16	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N7C02	4.7	±0.2nH	700mA	0.16	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH4N7S02	4.7	±0.3nH	700mA	0.16	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N1B02	5.1	±0.1nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N1C02	5.1	±0.2nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N1S02	5.1	±0.3nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N6B02	5.6	±0.1nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N6C02	5.6	±0.2nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH5N6S02	5.6	±0.3nH	650mA	0.18	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N2B02	6.2	±0.1nH	600mA	0.2	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N2C02	6.2	±0.2nH	600mA	0.2	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N2S02	6.2	±0.3nH	600mA	0.2	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N8G02	6.8	±2%	600mA	0.22	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N8H02	6.8	±3%	600mA	0.22	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH6N8J02	6.8	±5%	600mA	0.22	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH7N5G02	7.5	±2%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH7N5H02	7.5	±3%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH7N5J02	7.5	±5%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH8N2G02	8.2	±2%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH8N2H02	8.2	±3%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH8N2J02	8.2	±5%	550mA	0.24	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH9N1G02	9.1	±2%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH9N1H02	9.1	±3%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH9N1J02	9.1	±5%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH10NG02	10	±2%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH10NH02	10	±3%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH10NJ02	10	±5%	500mA	0.26	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH12NG02	12	±2%	500mA	0.28	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH12NH02	12	±3%	500mA	0.28	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH12NJ02	12	±5%	500mA	0.28	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH15NG02	15	±2%	450mA	0.32	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH15NH02	15	±3%	450mA	0.32	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH15NJ02	15	±5%	450mA	0.32	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH18NG02	18	±2%	400mA	0.36	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH18NH02	18	±3%	400mA	0.36	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH18NJ02	18	±5%	400mA	0.36	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH22NG02	22	±2%	350mA	0.42	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH22NH02	22	±3%	350mA	0.42	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH22NJ02	22	±5%	350mA	0.42	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH27NG02	27	±2%	350mA	0.46	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH27NH02	27	±3%	350mA	0.46	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH27NJ02	27	±5%	350mA	0.46	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH33NG02	33	±2%	350mA	0.58	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH33NH02	33	±3%	350mA	0.58	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH33NJ02	33	±5%	350mA	0.58	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH39NG02	39	±2%	300mA	0.65	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH39NH02	39	±3%	300mA	0.65	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH39NJ02	39	±5%	300mA	0.65	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH47NG02	47	±2%	300mA	0.72	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH47NH02	47	±3%	300mA	0.72	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH47NJ02	47	±5%	300mA	0.72	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH56NG02	56	±2%	250mA	0.82	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH56NH02	56	±3%	250mA	0.82	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH56NJ02	56	±5%	250mA	0.82	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH68NG02	68	±2%	250mA	0.92	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH68NH02	68	±3%	250mA	0.92	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH68NJ02	68	±5%	250mA	0.92	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH82NG02	82	±2%	200mA	1.2	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HH82NH02	82	±3%	200mA	1.2	1005	Powertrain/Safety	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15HH82NJ02	82	±5%	200mA	1.2	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR10G02	100	±2%	200mA	1.25	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR10H02	100	±3%	200mA	1.25	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR10J02	100	±5%	200mA	1.25	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR12G02	120	±2%	200mA	1.3	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR12H02	120	±3%	200mA	1.3	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR12J02	120	±5%	200mA	1.3	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR15G02	150	±2%	150mA	2.99	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR15H02	150	±3%	150mA	2.99	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR15J02	150	±5%	150mA	2.99	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR18G02	180	±2%	150mA	3.38	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR18H02	180	±3%	150mA	3.38	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR18J02	180	±5%	150mA	3.38	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR22G02	220	±2%	120mA	3.77	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR22H02	220	±3%	120mA	3.77	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR22J02	220	±5%	120mA	3.77	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR27G02	270	±2%	110mA	4.94	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR27H02	270	±3%	110mA	4.94	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HHR27J02	270	±5%	110mA	4.94	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15HN1N0B02	1	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HN1N0C02	1	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HN1N0S02	1	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HN1N1B02	1.1	±0.1nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N1C02	1.1	±0.2nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N1S02	1.1	±0.3nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N2B02	1.2	±0.1nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N2C02	1.2	±0.2nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N2S02	1.2	±0.3nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N3B02	1.3	±0.1nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N3C02	1.3	±0.2nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N3S02	1.3	±0.3nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N5B02	1.5	±0.1nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N5C02	1.5	±0.2nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N5S02	1.5	±0.3nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N6B02	1.6	±0.1nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N6C02	1.6	±0.2nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N6S02	1.6	±0.3nH	1000mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N8B02	1.8	±0.1nH	900mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N8C02	1.8	±0.2nH	900mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN1N8S02	1.8	±0.3nH	900mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HN2N0B02	2	±0.1nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N0C02	2	±0.2nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N0S02	2	±0.3nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N2B02	2.2	±0.1nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N2C02	2.2	±0.2nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N2S02	2.2	±0.3nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HN2N4B02	2.4	±0.1nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN2N4C02	2.4	±0.2nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN2N4S02	2.4	±0.3nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN2N7B02	2.7	±0.1nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN2N7C02	2.7	±0.2nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN2N7S02	2.7	±0.3nH	800mA	0.1	1005	General	50 MHz - 20 GHz
LQG15HN3N0B02	3	±0.1nH	800mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HN3N0C02	3	±0.2nH	800mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HN3N0S02	3	±0.3nH	800mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HN3N3B02	3.3	±0.1nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HN3N3C02	3.3	±0.2nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HN3N3S02	3.3	±0.3nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HN3N6B02	3.6	±0.1nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN3N6C02	3.6	±0.2nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN3N6S02	3.6	±0.3nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN3N9B02	3.9	±0.1nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN3N9C02	3.9	±0.2nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN3N9S02	3.9	±0.3nH	700mA	0.13	1005	General	50 MHz - 20 GHz
LQG15HN4N3B02	4.3	±0.1nH	700mA	0.15	1005	General	50 MHz - 20 GHz
LQG15HN4N3C02	4.3	±0.2nH	700mA	0.15	1005	General	50 MHz - 20 GHz
LQG15HN4N3S02	4.3	±0.3nH	700mA	0.15	1005	General	50 MHz - 20 GHz
LQG15HN4N7B02	4.7	±0.1nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN4N7C02	4.7	±0.2nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN4N7S02	4.7	±0.3nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN5N1B02	5.1	±0.1nH	600mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN5N1C02	5.1	±0.2nH	600mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN5N1S02	5.1	±0.3nH	600mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HN5N6B02	5.6	±0.1nH	600mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HN5N6C02	5.6	±0.2nH	600mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HN5N6S02	5.6	±0.3nH	600mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HN6N2B02	6.2	±0.1nH	600mA	0.19	1005	General	50 MHz - 20 GHz
LQG15HN6N2C02	6.2	±0.2nH	600mA	0.19	1005	General	50 MHz - 20 GHz
LQG15HN6N2S02	6.2	±0.3nH	600mA	0.19	1005	General	50 MHz - 20 GHz
LQG15HN6N8G02	6.8	±2%	600mA	0.21	1005	General	50 MHz - 20 GHz
LQG15HN6N8H02	6.8	±3%	600mA	0.21	1005	General	50 MHz - 20 GHz
LQG15HN6N8J02	6.8	±5%	600mA	0.21	1005	General	50 MHz - 20 GHz
LQG15HN7N5G02	7.5	±2%	500mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HN7N5H02	7.5	±3%	500mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HN7N5J02	7.5	±5%	500mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HN8N2G02	8.2	±2%	500mA	0.25	1005	General	50 MHz - 20 GHz
LQG15HN8N2H02	8.2	±3%	500mA	0.25	1005	General	50 MHz - 20 GHz
LQG15HN8N2J02	8.2	±5%	500mA	0.25	1005	General	50 MHz - 20 GHz
LQG15HN9N1G02	9.1	±2%	500mA	0.27	1005	General	50 MHz - 20 GHz
LQG15HN9N1H02	9.1	±3%	500mA	0.27	1005	General	50 MHz - 20 GHz
LQG15HN9N1J02	9.1	±5%	500mA	0.27	1005	General	50 MHz - 20 GHz
LQG15HN10NG02	10	±2%	500mA	0.29	1005	General	50 MHz - 20 GHz
LQG15HN10NH02	10	±3%	500mA	0.29	1005	General	50 MHz - 20 GHz
LQG15HN10NJ02	10	±5%	500mA	0.29	1005	General	50 MHz - 20 GHz
LQG15HN12NG02	12	±2%	400mA	0.4	1005	General	50 MHz - 20 GHz
LQG15HN12NH02	12	±3%	400mA	0.4	1005	General	50 MHz - 20 GHz
LQG15HN12NJ02	12	±5%	400mA	0.4	1005	General	50 MHz - 20 GHz
LQG15HN15NG02	15	±2%	400mA	0.45	1005	General	50 MHz - 20 GHz
LQG15HN15NH02	15	±3%	400mA	0.45	1005	General	50 MHz - 20 GHz
LQG15HN15NJ02	15	±5%	400mA	0.45	1005	General	50 MHz - 20 GHz
LQG15HN18NG02	18	±2%	350mA	0.51	1005	General	50 MHz - 20 GHz
LQG15HN18NH02	18	±3%	350mA	0.51	1005	General	50 MHz - 20 GHz
LQG15HN18NJ02	18	±5%	350mA	0.51	1005	General	50 MHz - 20 GHz
LQG15HN22NG02	22	±2%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HN22NH02	22	±3%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HN22NJ02	22	±5%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HN27NG02	27	±2%	300mA	0.67	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15HN27NH02	27	±3%	300mA	0.67	1005	General	50 MHz - 20 GHz
LQG15HN27NJ02	27	±5%	300mA	0.67	1005	General	50 MHz - 20 GHz
LQG15HN33NG02	33	±2%	300mA	0.67	1005	General	50 MHz - 20 GHz
LQG15HN33NH02	33	±3%	300mA	0.67	1005	General	50 MHz - 20 GHz
LQG15HN33NJ02	33	±5%	300mA	0.67	1005	General	50 MHz - 20 GHz
LQG15HN39NG02	39	±2%	250mA	1.06	1005	General	50 MHz - 20 GHz
LQG15HN39NH02	39	±3%	250mA	1.06	1005	General	50 MHz - 20 GHz
LQG15HN39NJ02	39	±5%	250mA	1.06	1005	General	50 MHz - 20 GHz
LQG15HN47NG02	47	±2%	250mA	1.15	1005	General	50 MHz - 20 GHz
LQG15HN47NH02	47	±3%	250mA	1.15	1005	General	50 MHz - 20 GHz
LQG15HN47NJ02	47	±5%	250mA	1.15	1005	General	50 MHz - 20 GHz
LGG15HN56NG02	56	±2%	200mA	1.2	1005	General	50 MHz - 20 GHz
LGG15HN56NH02	56	±3%	200mA	1.2	1005	General	50 MHz - 20 GHz
LGG15HN56NJ02	56	±5%	200mA	1.2	1005	General	50 MHz - 20 GHz
LQG15HN68NG02	68	±2%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HN68NH02	68	±3%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HN68NJ02	68	±5%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HN82NG02	82	±2%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HN82NH02	82	±3%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HN82NJ02	82	±5%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR10G02	100	±2%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR10H02	100	±3%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR10J02	100	±5%	200mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR12G02	120	±2%	150mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR12H02	120	±3%	150mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HNR12J02	120	±5%	150mA	1.6	1005	General	50 MHz - 20 GHz
LQG15HS1N0B02	1	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N0C02	1	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N0S02	1	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N1B02	1.1	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N1C02	1.1	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N1S02	1.1	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N2B02	1.2	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N2C02	1.2	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N2S02	1.2	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N3B02	1.3	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N3C02	1.3	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N3S02	1.3	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N5B02	1.5	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N5C02	1.5	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N5S02	1.5	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N6B02	1.6	±0.1nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N6C02	1.6	±0.2nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N6S02	1.6	±0.3nH	1000mA	0.07	1005	General	50 MHz - 20 GHz
LQG15HS1N8B02	1.8	±0.1nH	950mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HS1N8C02	1.8	±0.2nH	950mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HS1N8S02	1.8	±0.3nH	950mA	0.08	1005	General	50 MHz - 20 GHz
LQG15HS2N0B02	2	±0.1nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N0C02	2	±0.2nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N0S02	2	±0.3nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N2B02	2.2	±0.1nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N2C02	2.2	±0.2nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N2S02	2.2	±0.3nH	900mA	0.09	1005	General	50 MHz - 20 GHz
LQG15HS2N4B02	2.4	±0.1nH	850mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HS2N4C02	2.4	±0.2nH	850mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HS2N4S02	2.4	±0.3nH	850mA	0.11	1005	General	50 MHz - 20 GHz
LQG15HS2N7B02	2.7	±0.1nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HS2N7C02	2.7	±0.2nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HS2N7S02	2.7	±0.3nH	800mA	0.12	1005	General	50 MHz - 20 GHz
LQG15HS3N0B02	3	±0.1nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N0C02	3	±0.2nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N0S02	3	±0.3nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N3B02	3.3	±0.1nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N3C02	3.3	±0.2nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N3S02	3.3	±0.3nH	800mA	0.125	1005	General	50 MHz - 20 GHz
LQG15HS3N6B02	3.6	±0.1nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS3N6C02	3.6	±0.2nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS3N6S02	3.6	±0.3nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS3N9B02	3.9	±0.1nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS3N9C02	3.9	±0.2nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS3N9S02	3.9	±0.3nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS4N3B02	4.3	±0.1nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS4N3C02	4.3	±0.2nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS4N3S02	4.3	±0.3nH	750mA	0.14	1005	General	50 MHz - 20 GHz
LQG15HS4N7B02	4.7	±0.1nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HS4N7C02	4.7	±0.2nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HS4N7S02	4.7	±0.3nH	700mA	0.16	1005	General	50 MHz - 20 GHz
LQG15HS5N1B02	5.1	±0.1nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS5N1C02	5.1	±0.2nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS5N1S02	5.1	±0.3nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS5N6B02	5.6	±0.1nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS5N6C02	5.6	±0.2nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS5N6S02	5.6	±0.3nH	650mA	0.18	1005	General	50 MHz - 20 GHz
LQG15HS6N2B02	6.2	±0.1nH	600mA	0.2	1005	General	50 MHz - 20 GHz
LQG15HS6N2C02	6.2	±0.2nH	600mA	0.2	1005	General	50 MHz - 20 GHz
LQG15HS6N2S02	6.2	±0.3nH	600mA	0.2	1005	General	50 MHz - 20 GHz
LQG15HS6N8G02	6.8	±2%	600mA	0.22	1005	General	50 MHz - 20 GHz
LQG15HS6N8H02	6.8	±3%	600mA	0.22	1005	General	50 MHz - 20 GHz
LQG15HS6N8J02	6.8	±5%	600mA	0.22	1005	General	50 MHz - 20 GHz
LQG15HS7N5G02	7.5	±2%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS7N5H02	7.5	±3%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS7N5J02	7.5	±5%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS8N2G02	8.2	±2%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS8N2H02	8.2	±3%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS8N2J02	8.2	±5%	550mA	0.24	1005	General	50 MHz - 20 GHz
LQG15HS9N1G02	9.1	±2%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS9N1H02	9.1	±3%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS9N1J02	9.1	±5%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS10NG02	10	±2%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS10NH02	10	±3%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS10NJ02	10	±5%	500mA	0.26	1005	General	50 MHz - 20 GHz
LQG15HS12NG02	12	±2%	500mA	0.28	1005	General	50 MHz - 20 GHz
LQG15HS12NH02	12	±3%	500mA	0.28	1005	General	50 MHz - 20 GHz
LQG15HS12NJ02	12	±5%	500mA	0.28	1005	General	50 MHz - 20 GHz
LQG15HS15NG02	15	±2%	450mA	0.32	1005	General	50 MHz - 20 GHz
LQG15HS15NH02	15	±3%	450mA	0.32	1005	General	50 MHz - 20 GHz
LQG15HS15NJ02	15	±5%	450mA	0.32	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15HS18NG02	18	±2%	400mA	0.36	1005	General	50 MHz - 20 GHz
LQG15HS18NH02	18	±3%	400mA	0.36	1005	General	50 MHz - 20 GHz
LQG15HS18NJ02	18	±5%	400mA	0.36	1005	General	50 MHz - 20 GHz
LQG15HS22NG02	22	±2%	350mA	0.42	1005	General	50 MHz - 20 GHz
LQG15HS22NH02	22	±3%	350mA	0.42	1005	General	50 MHz - 20 GHz
LQG15HS22NJ02	22	±5%	350mA	0.42	1005	General	50 MHz - 20 GHz
LQG15HS27NG02	27	±2%	350mA	0.46	1005	General	50 MHz - 20 GHz
LQG15HS27NH02	27	±3%	350mA	0.46	1005	General	50 MHz - 20 GHz
LQG15HS27NJ02	27	±5%	350mA	0.46	1005	General	50 MHz - 20 GHz
LQG15HS33NG02	33	±2%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HS33NH02	33	±3%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HS33NJ02	33	±5%	350mA	0.58	1005	General	50 MHz - 20 GHz
LQG15HS39NG02	39	±2%	300mA	0.65	1005	General	50 MHz - 20 GHz
LQG15HS39NH02	39	±3%	300mA	0.65	1005	General	50 MHz - 20 GHz
LQG15HS39NJ02	39	±5%	300mA	0.65	1005	General	50 MHz - 20 GHz
LQG15HS47NG02	47	±2%	300mA	0.72	1005	General	50 MHz - 20 GHz
LQG15HS47NH02	47	±3%	300mA	0.72	1005	General	50 MHz - 20 GHz
LQG15HS47NJ02	47	±5%	300mA	0.72	1005	General	50 MHz - 20 GHz
LQG15HS56NG02	56	±2%	250mA	0.82	1005	General	50 MHz - 20 GHz
LQG15HS56NH02	56	±3%	250mA	0.82	1005	General	50 MHz - 20 GHz
LQG15HS56NJ02	56	±5%	250mA	0.82	1005	General	50 MHz - 20 GHz
LQG15HS68NG02	68	±2%	250mA	0.92	1005	General	50 MHz - 20 GHz
LQG15HS68NH02	68	±3%	250mA	0.92	1005	General	50 MHz - 20 GHz
LQG15HS68NJ02	68	±5%	250mA	0.92	1005	General	50 MHz - 20 GHz
LQG15HS82NG02	82	±2%	200mA	1.2	1005	General	50 MHz - 20 GHz
LQG15HS82NH02	82	±3%	200mA	1.2	1005	General	50 MHz - 20 GHz
LQG15HS82NJ02	82	±5%	200mA	1.2	1005	General	50 MHz - 20 GHz
LQG15HSR10G02	100	±2%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HSR10H02	100	±3%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HSR10J02	100	±5%	200mA	1.25	1005	General	50 MHz - 20 GHz
LQG15HSR12G02	120	±2%	200mA	1.3	1005	General	50 MHz - 20 GHz
LQG15HSR12H02	120	±3%	200mA	1.3	1005	General	50 MHz - 20 GHz
LQG15HSR12J02	120	±5%	200mA	1.3	1005	General	50 MHz - 20 GHz
LQG15HSR15G02	150	±2%	150mA	2.99	1005	General	50 MHz - 20 GHz
LQG15HSR15H02	150	±3%	150mA	2.99	1005	General	50 MHz - 20 GHz
LQG15HSR15J02	150	±5%	150mA	2.99	1005	General	50 MHz - 20 GHz
LQG15HSR18G02	180	±2%	150mA	3.38	1005	General	50 MHz - 20 GHz
LQG15HSR18H02	180	±3%	150mA	3.38	1005	General	50 MHz - 20 GHz
LQG15HSR18J02	180	±5%	150mA	3.38	1005	General	50 MHz - 20 GHz
LQG15HSR22G02	220	±2%	120mA	3.77	1005	General	50 MHz - 20 GHz
LQG15HSR22H02	220	±3%	120mA	3.77	1005	General	50 MHz - 20 GHz
LQG15HSR22J02	220	±5%	120mA	3.77	1005	General	50 MHz - 20 GHz
LQG15HSR27G02	270	±2%	110mA	4.94	1005	General	50 MHz - 20 GHz
LQG15HSR27H02	270	±3%	110mA	4.94	1005	General	50 MHz - 20 GHz
LQG15HSR27J02	270	±5%	110mA	4.94	1005	General	50 MHz - 20 GHz
LQG15HZ1N0B02	1	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N0C02	1	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N0S02	1	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N1B02	1.1	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N1C02	1.1	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N1S02	1.1	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N2B02	1.2	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N2C02	1.2	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N2S02	1.2	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N3B02	1.3	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N3C02	1.3	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N3S02	1.3	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N5B02	1.5	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N5C02	1.5	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N5S02	1.5	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N6B02	1.6	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N6C02	1.6	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N6S02	1.6	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N8B02	1.8	±0.1nH	950mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N8C02	1.8	±0.2nH	950mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ1N8S02	1.8	±0.3nH	950mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N0B02	2	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N0C02	2	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N0S02	2	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N2B02	2.2	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N2C02	2.2	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N2S02	2.2	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N4B02	2.4	±0.1nH	850mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N4C02	2.4	±0.2nH	850mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N4S02	2.4	±0.3nH	850mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N7B02	2.7	±0.1nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N7C02	2.7	±0.2nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ2N7S02	2.7	±0.3nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N0B02	3	±0.1nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N0C02	3	±0.2nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N0S02	3	±0.3nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N3B02	3.3	±0.1nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N3C02	3.3	±0.2nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N3S02	3.3	±0.3nH	800mA	0.125	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N6B02	3.6	±0.1nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N6C02	3.6	±0.2nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N6S02	3.6	±0.3nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N9B02	3.9	±0.1nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N9C02	3.9	±0.2nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ3N9S02	3.9	±0.3nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N3B02	4.3	±0.1nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N3C02	4.3	±0.2nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N3S02	4.3	±0.3nH	750mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N7B02	4.7	±0.1nH	700mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N7C02	4.7	±0.2nH	700mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ4N7S02	4.7	±0.3nH	700mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N1B02	5.1	±0.1nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N1C02	5.1	±0.2nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N1S02	5.1	±0.3nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N6B02	5.6	±0.1nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N6C02	5.6	±0.2nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ5N6S02	5.6	±0.3nH	650mA	0.18	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ6N2B02	6.2	±0.1nH	600mA	0.2	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ6N2C02	6.2	±0.2nH	600mA	0.2	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ6N2S02	6.2	±0.3nH	600mA	0.2	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ6N8G02	6.8	±2%	600mA	0.22	1005	Infotainment	50 MHz - 20 GHz
LQG15HZ6N8H02	6.8	±3%	600mA	0.22	1005	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15H26N8J02	6.8	±5%	600mA	0.22	1005	Infotainment	50 MHz - 20 GHz
LQG15H27N5G02	7.5	±2%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H27N5H02	7.5	±3%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H27N5J02	7.5	±5%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H28N2G02	8.2	±2%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H28N2H02	8.2	±3%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H28N2J02	8.2	±5%	550mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15H29N1G02	9.1	±2%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H29N1H02	9.1	±3%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H29N1J02	9.1	±5%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H210NG02	10	±2%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H210NH02	10	±3%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H210NJ02	10	±5%	500mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15H212NG02	12	±2%	500mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15H212NH02	12	±3%	500mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15H212NJ02	12	±5%	500mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15H215NG02	15	±2%	450mA	0.32	1005	Infotainment	50 MHz - 20 GHz
LQG15H215NH02	15	±3%	450mA	0.32	1005	Infotainment	50 MHz - 20 GHz
LQG15H215NJ02	15	±5%	450mA	0.32	1005	Infotainment	50 MHz - 20 GHz
LQG15H218NG02	18	±2%	400mA	0.36	1005	Infotainment	50 MHz - 20 GHz
LQG15H218NH02	18	±3%	400mA	0.36	1005	Infotainment	50 MHz - 20 GHz
LQG15H218NJ02	18	±5%	400mA	0.36	1005	Infotainment	50 MHz - 20 GHz
LQG15H222NG02	22	±2%	350mA	0.42	1005	Infotainment	50 MHz - 20 GHz
LQG15H222NH02	22	±3%	350mA	0.42	1005	Infotainment	50 MHz - 20 GHz
LQG15H222NJ02	22	±5%	350mA	0.42	1005	Infotainment	50 MHz - 20 GHz
LQG15H227NG02	27	±2%	350mA	0.46	1005	Infotainment	50 MHz - 20 GHz
LQG15H227NH02	27	±3%	350mA	0.46	1005	Infotainment	50 MHz - 20 GHz
LQG15H227NJ02	27	±5%	350mA	0.46	1005	Infotainment	50 MHz - 20 GHz
LQG15H233NG02	33	±2%	350mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQG15H233NH02	33	±3%	350mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQG15H233NJ02	33	±5%	350mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQG15H239NG02	39	±2%	300mA	0.65	1005	Infotainment	50 MHz - 20 GHz
LQG15H239NH02	39	±3%	300mA	0.65	1005	Infotainment	50 MHz - 20 GHz
LQG15H239NJ02	39	±5%	300mA	0.65	1005	Infotainment	50 MHz - 20 GHz
LQG15H247NG02	47	±2%	300mA	0.72	1005	Infotainment	50 MHz - 20 GHz
LQG15H247NH02	47	±3%	300mA	0.72	1005	Infotainment	50 MHz - 20 GHz
LQG15H247NJ02	47	±5%	300mA	0.72	1005	Infotainment	50 MHz - 20 GHz
LQG15H256NG02	56	±2%	250mA	0.82	1005	Infotainment	50 MHz - 20 GHz
LQG15H256NH02	56	±3%	250mA	0.82	1005	Infotainment	50 MHz - 20 GHz
LQG15H256NJ02	56	±5%	250mA	0.82	1005	Infotainment	50 MHz - 20 GHz
LQG15H268NG02	68	±2%	250mA	0.92	1005	Infotainment	50 MHz - 20 GHz
LQG15H268NH02	68	±3%	250mA	0.92	1005	Infotainment	50 MHz - 20 GHz
LQG15H268NJ02	68	±5%	250mA	0.92	1005	Infotainment	50 MHz - 20 GHz
LQG15H282NG02	82	±2%	200mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15H282NH02	82	±3%	200mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15H282NJ02	82	±5%	200mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R10G02	100	±2%	200mA	1.25	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R10H02	100	±3%	200mA	1.25	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R10J02	100	±5%	200mA	1.25	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R12G02	120	±2%	200mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R12H02	120	±3%	200mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R12J02	120	±5%	200mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R15G02	150	±2%	150mA	2.99	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R15H02	150	±3%	150mA	2.99	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R15J02	150	±5%	150mA	2.99	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R18G02	180	±2%	150mA	3.38	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R18H02	180	±3%	150mA	3.38	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R18J02	180	±5%	150mA	3.38	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R22G02	220	±2%	120mA	3.77	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R22H02	220	±3%	120mA	3.77	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R22J02	220	±5%	120mA	3.77	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R27G02	270	±2%	110mA	4.94	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R27H02	270	±3%	110mA	4.94	1005	Infotainment	50 MHz - 20 GHz
LQG15H2R27J02	270	±5%	110mA	4.94	1005	Infotainment	50 MHz - 20 GHz
LQG15WH1N0B02	1	±0.1nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N0C02	1	±0.2nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N0S02	1	±0.3nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N1B02	1.1	±0.1nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N1C02	1.1	±0.2nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N1S02	1.1	±0.3nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N2B02	1.2	±0.1nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N2C02	1.2	±0.2nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N2S02	1.2	±0.3nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N3B02	1.3	±0.1nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N3C02	1.3	±0.2nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N3S02	1.3	±0.3nH	1200mA	0.03	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N4B02	1.4	±0.1nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N4C02	1.4	±0.2nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N4S02	1.4	±0.3nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N5B02	1.5	±0.1nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N5C02	1.5	±0.2nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N5S02	1.5	±0.3nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N6B02	1.6	±0.1nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N6C02	1.6	±0.2nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N6S02	1.6	±0.3nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N7B02	1.7	±0.1nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N7C02	1.7	±0.2nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N7S02	1.7	±0.3nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N8B02	1.8	±0.1nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N8C02	1.8	±0.2nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N8S02	1.8	±0.3nH	1000mA	0.04	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N9B02	1.9	±0.1nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N9C02	1.9	±0.2nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH1N9S02	1.9	±0.3nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N0B02	2	±0.1nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N0C02	2	±0.2nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N0S02	2	±0.3nH	1000mA	0.05	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N1B02	2.1	±0.1nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N1C02	2.1	±0.2nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N1S02	2.1	±0.3nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N2B02	2.2	±0.1nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N2C02	2.2	±0.2nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N2S02	2.2	±0.3nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N3B02	2.3	±0.1nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N3C02	2.3	±0.2nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N3S02	2.3	±0.3nH	1000mA	0.07	1005	Powertrain/Safety	50 MHz - 20 GHz
LQG15WH2N4B02	2.4	±0.1nH	1000mA	0.06	1005	Powertrain/Safety	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15WZ1N8S02	1.8	±0.3nH	1000mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ1N9B02	1.9	±0.1nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ1N9C02	1.9	±0.2nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ1N9S02	1.9	±0.3nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N0B02	2	±0.1nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N0C02	2	±0.2nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N0S02	2	±0.3nH	1000mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N1B02	2.1	±0.1nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N1C02	2.1	±0.2nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N1S02	2.1	±0.3nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N2B02	2.2	±0.1nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N2C02	2.2	±0.2nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N2S02	2.2	±0.3nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N3B02	2.3	±0.1nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N3C02	2.3	±0.2nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N3S02	2.3	±0.3nH	1000mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N4B02	2.4	±0.1nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N4C02	2.4	±0.2nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N4S02	2.4	±0.3nH	1000mA	0.06	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N5B02	2.5	±0.1nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N5C02	2.5	±0.2nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N5S02	2.5	±0.3nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N6B02	2.6	±0.1nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N6C02	2.6	±0.2nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N6S02	2.6	±0.3nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N7B02	2.7	±0.1nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N7C02	2.7	±0.2nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N7S02	2.7	±0.3nH	900mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N8B02	2.8	±0.1nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N8C02	2.8	±0.2nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N8S02	2.8	±0.3nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N9B02	2.9	±0.1nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N9C02	2.9	±0.2nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ2N9S02	2.9	±0.3nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N0B02	3	±0.1nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N0C02	3	±0.2nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N0S02	3	±0.3nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N1B02	3.1	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N1C02	3.1	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N1S02	3.1	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N2B02	3.2	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N2C02	3.2	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N2S02	3.2	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N3B02	3.3	±0.1nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N3C02	3.3	±0.2nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N3S02	3.3	±0.3nH	900mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N4B02	3.4	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N4C02	3.4	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N4S02	3.4	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N5B02	3.5	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N5C02	3.5	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N5S02	3.5	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N6B02	3.6	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N6C02	3.6	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N6S02	3.6	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N7B02	3.7	±0.1nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N7C02	3.7	±0.2nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N7S02	3.7	±0.3nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N8B02	3.8	±0.1nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N8C02	3.8	±0.2nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N8S02	3.8	±0.3nH	900mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N9B02	3.9	±0.1nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N9C02	3.9	±0.2nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ3N9S02	3.9	±0.3nH	900mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N1B02	4.1	±0.1nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N1C02	4.1	±0.2nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N1S02	4.1	±0.3nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N3B02	4.3	±0.1nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N3C02	4.3	±0.2nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N3S02	4.3	±0.3nH	800mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N7B02	4.7	±0.1nH	800mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N7C02	4.7	±0.2nH	800mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ4N7S02	4.7	±0.3nH	800mA	0.11	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N1B02	5.1	±0.1nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N1C02	5.1	±0.2nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N1S02	5.1	±0.3nH	800mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N6B02	5.6	±0.1nH	800mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N6C02	5.6	±0.2nH	800mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N6S02	5.6	±0.3nH	800mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N8B02	5.8	±0.1nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N8C02	5.8	±0.2nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ5N8S02	5.8	±0.3nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N2B02	6.2	±0.1nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N2C02	6.2	±0.2nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N2S02	6.2	±0.3nH	700mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N8G02	6.8	±2%	700mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N8H02	6.8	±3%	700mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ6N8J02	6.8	±5%	700mA	0.14	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N3G02	7.3	±2%	600mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N3H02	7.3	±3%	600mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N3J02	7.3	±5%	600mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N5G02	7.5	±2%	600mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N5H02	7.5	±3%	600mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ7N5J02	7.5	±5%	600mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N2G02	8.2	±2%	550mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N2H02	8.2	±3%	550mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N2J02	8.2	±5%	550mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N7G02	8.7	±2%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N7H02	8.7	±3%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ8N7J02	8.7	±5%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N1G02	9.1	±2%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N1H02	9.1	±3%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N1J02	9.1	±5%	550mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N5G02	9.5	±2%	500mA	0.21	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N5H02	9.5	±3%	500mA	0.21	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ9N5J02	9.5	±5%	500mA	0.21	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ10NG02	10	±2%	500mA	0.19	1005	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG15WZ10NH02	10	±3%	500mA	0.19	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ10NJ02	10	±5%	500mA	0.19	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ11NG02	11	±2%	450mA	0.22	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ11NH02	11	±3%	450mA	0.22	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ11NJ02	11	±5%	450mA	0.22	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ12NG02	12	±2%	450mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ12NH02	12	±3%	450mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ12NJ02	12	±5%	450mA	0.24	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ13NG02	13	±2%	400mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ13NH02	13	±3%	400mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ13NJ02	13	±5%	400mA	0.26	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ15NG02	15	±2%	400mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ15NH02	15	±3%	400mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ15NJ02	15	±5%	400mA	0.28	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ16NG02	16	±2%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ16NH02	16	±3%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ16NJ02	16	±5%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ18NG02	18	±2%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ18NH02	18	±3%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ18NJ02	18	±5%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ19NG02	19	±2%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ19NH02	19	±3%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ19NJ02	19	±5%	260mA	0.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ20NG02	20	±2%	260mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ20NH02	20	±3%	260mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ20NJ02	20	±5%	260mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ22NG02	22	±2%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ22NH02	22	±3%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ22NJ02	22	±5%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ23NG02	23	±2%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ23NH02	23	±3%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ23NJ02	23	±5%	230mA	1.1	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ24NG02	24	±2%	230mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ24NH02	24	±3%	230mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ24NJ02	24	±5%	230mA	1.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ27NG02	27	±2%	230mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ27NH02	27	±3%	230mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ27NJ02	27	±5%	230mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ30NG02	30	±2%	220mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ30NH02	30	±3%	220mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ30NJ02	30	±5%	220mA	1.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ33NG02	33	±2%	220mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ33NH02	33	±3%	220mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ33NJ02	33	±5%	220mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ36NG02	36	±2%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ36NH02	36	±3%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ36NJ02	36	±5%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ39NG02	39	±2%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ39NH02	39	±3%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ39NJ02	39	±5%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ40NG02	40	±2%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ40NH02	40	±3%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ40NJ02	40	±5%	190mA	1.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ43NG02	43	±2%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ43NH02	43	±3%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ43NJ02	43	±5%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ47NG02	47	±2%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ47NH02	47	±3%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ47NJ02	47	±5%	190mA	1.6	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ51NG02	51	±2%	190mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ51NH02	51	±3%	190mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ51NJ02	51	±5%	190mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ56NG02	56	±2%	180mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ56NH02	56	±3%	180mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ56NJ02	56	±5%	180mA	1.8	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ62NG02	62	±2%	180mA	1.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ62NH02	62	±3%	180mA	1.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ62NJ02	62	±5%	180mA	1.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ68NG02	68	±2%	160mA	2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ68NH02	68	±3%	160mA	2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ68NJ02	68	±5%	160mA	2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ72NG02	72	±2%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ72NH02	72	±3%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ72NJ02	72	±5%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ75NG02	75	±2%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ75NH02	75	±3%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ75NJ02	75	±5%	160mA	2.2	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ82NG02	82	±2%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ82NH02	82	±3%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ82NJ02	82	±5%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ91NG02	91	±2%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ91NH02	91	±3%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZ91NJ02	91	±5%	160mA	2.3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR10G02	100	±2%	150mA	2.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR10H02	100	±3%	150mA	2.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR10J02	100	±5%	150mA	2.5	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR11G02	110	±2%	150mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR11H02	110	±3%	150mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR11J02	110	±5%	150mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR12G02	120	±2%	140mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR12H02	120	±3%	140mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR12J02	120	±5%	140mA	2.7	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR13G02	130	±2%	110mA	2.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR13H02	130	±3%	110mA	2.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR13J02	130	±5%	110mA	2.9	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR15G02	150	±2%	110mA	3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR15H02	150	±3%	110mA	3	1005	Infotainment	50 MHz - 20 GHz
LQG15WZR15J02	150	±5%	110mA	3	1005	Infotainment	50 MHz - 20 GHz
LQG18HH1N2S00	1.2	±0.3nH	1100mA	0.1	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH1N5S00	1.5	±0.3nH	1100mA	0.1	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH1N8S00	1.8	±0.3nH	1100mA	0.1	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH2N2S00	2.2	±0.3nH	1100mA	0.1	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH2N7S00	2.7	±0.3nH	1000mA	0.13	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH3N3S00	3.3	±0.3nH	900mA	0.14	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH3N9S00	3.9	±0.3nH	900mA	0.15	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH4N7S00	4.7	±0.3nH	800mA	0.16	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH5N6S00	5.6	±0.3nH	800mA	0.17	1608	Powertrain/Safety	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQG18HH6N2S00	6.2	±0.3nH	800mA	0.18	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH6N8J00	6.8	±5%	800mA	0.18	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH8N2J00	8.2	±5%	800mA	0.2	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH10NJ00	10	±5%	700mA	0.25	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH12NJ00	12	±5%	600mA	0.3	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH15NJ00	15	±5%	600mA	0.35	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH18NJ00	18	±5%	600mA	0.35	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH22NJ00	22	±5%	500mA	0.5	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH27NJ00	27	±5%	500mA	0.54	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH33NJ00	33	±5%	500mA	0.54	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH39NJ00	39	±5%	400mA	0.6	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH47NJ00	47	±5%	400mA	0.7	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH56NJ00	56	±5%	400mA	0.7	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH68NJ00	68	±5%	400mA	0.8	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HH82NJ00	82	±5%	300mA	0.85	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR10J00	100	±5%	300mA	0.9	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR12J00	120	±5%	300mA	1.1	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR15J00	150	±5%	300mA	1.2	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR18J00	180	±5%	300mA	1.3	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR22J00	220	±5%	300mA	1.5	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HHR27J00	270	±5%	200mA	1.9	1608	Powertrain/Safety	50 MHz - 20 GHz
LQG18HN1N2S00	1.2	±0.3nH	1100mA	0.1	1608	General	50 MHz - 20 GHz
LQG18HN1N5S00	1.5	±0.3nH	1100mA	0.1	1608	General	50 MHz - 20 GHz
LQG18HN1N8S00	1.8	±0.3nH	1100mA	0.1	1608	General	50 MHz - 20 GHz
LQG18HN2N2S00	2.2	±0.3nH	1100mA	0.1	1608	General	50 MHz - 20 GHz
LQG18HN2N7S00	2.7	±0.3nH	1000mA	0.12	1608	General	50 MHz - 20 GHz
LQG18HN3N3S00	3.3	±0.3nH	1000mA	0.12	1608	General	50 MHz - 20 GHz
LQG18HN3N9S00	3.9	±0.3nH	900mA	0.15	1608	General	50 MHz - 20 GHz
LQG18HN4N7S00	4.7	±0.3nH	900mA	0.15	1608	General	50 MHz - 20 GHz
LQG18HN5N6S00	5.6	±0.3nH	800mA	0.2	1608	General	50 MHz - 20 GHz
LQG18HN6N8J00	6.8	±5%	800mA	0.2	1608	General	50 MHz - 20 GHz
LQG18HN8N2J00	8.2	±5%	800mA	0.2	1608	General	50 MHz - 20 GHz
LQG18HN10NJ00	10	±5%	650mA	0.3	1608	General	50 MHz - 20 GHz
LQG18HN12NJ00	12	±5%	600mA	0.35	1608	General	50 MHz - 20 GHz
LQG18HN15NJ00	15	±5%	600mA	0.35	1608	General	50 MHz - 20 GHz
LQG18HN18NJ00	18	±5%	600mA	0.37	1608	General	50 MHz - 20 GHz
LQG18HN22NJ00	22	±5%	500mA	0.5	1608	General	50 MHz - 20 GHz
LQG18HN27NJ00	27	±5%	500mA	0.54	1608	General	50 MHz - 20 GHz
LQG18HN33NJ00	33	±5%	500mA	0.54	1608	General	50 MHz - 20 GHz
LQG18HN39NJ00	39	±5%	450mA	0.6	1608	General	50 MHz - 20 GHz
LQG18HN47NJ00	47	±5%	400mA	0.7	1608	General	50 MHz - 20 GHz
LQG18HN56NJ00	56	±5%	400mA	0.75	1608	General	50 MHz - 20 GHz
LQG18HN68NJ00	68	±5%	400mA	0.8	1608	General	50 MHz - 20 GHz
LQG18HN82NJ00	82	±5%	350mA	0.85	1608	General	50 MHz - 20 GHz
LQG18HNR10J00	100	±5%	350mA	0.9	1608	General	50 MHz - 20 GHz
LQP01HV0N3B02	0.3	±0.1nH	500mA	0.04	201	General	50 MHz - 20 GHz
LQP01HV0N4B02	0.4	±0.1nH	500mA	0.07	201	General	50 MHz - 20 GHz
LQP01HV0N5B02	0.5	±0.1nH	500mA	0.07	201	General	50 MHz - 20 GHz
LQP01HV0N6B02	0.6	±0.1nH	500mA	0.07	201	General	50 MHz - 20 GHz
LQP01HV0N7B02	0.7	±0.1nH	500mA	0.08	201	General	50 MHz - 20 GHz
LQP01HV0N8B02	0.8	±0.1nH	500mA	0.11	201	General	50 MHz - 20 GHz
LQP01HV0N9B02	0.9	±0.1nH	500mA	0.11	201	General	50 MHz - 20 GHz
LQP01HV1N0B02	1	±0.1nH	400mA	0.11	201	General	50 MHz - 20 GHz
LQP01HV1N1B02	1.1	±0.1nH	400mA	0.12	201	General	50 MHz - 20 GHz
LQP01HV1N2B02	1.2	±0.1nH	400mA	0.14	201	General	50 MHz - 20 GHz
LQP01HV1N3B02	1.3	±0.1nH	400mA	0.18	201	General	50 MHz - 20 GHz
LQP01HV1N4B02	1.4	±0.1nH	400mA	0.2	201	General	50 MHz - 20 GHz
LQP01HV1N5B02	1.5	±0.1nH	400mA	0.2	201	General	50 MHz - 20 GHz
LQP01HV1N6B02	1.6	±0.1nH	400mA	0.2	201	General	50 MHz - 20 GHz
LQP01HV1N7B02	1.7	±0.1nH	250mA	0.21	201	General	50 MHz - 20 GHz
LQP01HV1N8B02	1.8	±0.1nH	250mA	0.23	201	General	50 MHz - 20 GHz
LQP01HV1N9B02	1.9	±0.1nH	250mA	0.26	201	General	50 MHz - 20 GHz
LQP01HV2N0B02	2	±0.1nH	250mA	0.31	201	General	50 MHz - 20 GHz
LQP01HV2N1B02	2.1	±0.1nH	250mA	0.31	201	General	50 MHz - 20 GHz
LQP01HV2N2B02	2.2	±0.1nH	250mA	0.37	201	General	50 MHz - 20 GHz
LQP01HV2N3B02	2.3	±0.1nH	250mA	0.37	201	General	50 MHz - 20 GHz
LQP01HV2N4B02	2.4	±0.1nH	250mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV2N5B02	2.5	±0.1nH	250mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV2N6B02	2.6	±0.1nH	250mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV2N7B02	2.7	±0.1nH	200mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV2N8B02	2.8	±0.1nH	200mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV2N9B02	2.9	±0.1nH	180mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV3N0B02	3	±0.1nH	180mA	0.42	201	General	50 MHz - 20 GHz
LQP01HV3N1B02	3.1	±0.1nH	180mA	0.46	201	General	50 MHz - 20 GHz
LQP01HV3N2B02	3.2	±0.1nH	130mA	0.5	201	General	50 MHz - 20 GHz
LQP01HV3N3B02	3.3	±0.1nH	130mA	0.53	201	General	50 MHz - 20 GHz
LQP01HV3N4B02	3.4	±0.1nH	130mA	0.53	201	General	50 MHz - 20 GHz
LQP01HV3N5B02	3.5	±0.1nH	130mA	0.54	201	General	50 MHz - 20 GHz
LQP01HV3N6B02	3.6	±0.1nH	130mA	0.58	201	General	50 MHz - 20 GHz
LQP01HV3N7B02	3.7	±0.1nH	130mA	0.62	201	General	50 MHz - 20 GHz
LQP01HV3N8B02	3.8	±0.1nH	130mA	0.69	201	General	50 MHz - 20 GHz
LQP01HV3N9B02	3.9	±0.1nH	130mA	0.79	201	General	50 MHz - 20 GHz
LQP01HV4N0B02	4	±0.1nH	130mA	0.81	201	General	50 MHz - 20 GHz
LQP01HV4N1B02	4.1	±0.1nH	130mA	0.88	201	General	50 MHz - 20 GHz
LQP01HV4N2B02	4.2	±0.1nH	130mA	0.88	201	General	50 MHz - 20 GHz
LQP01HV4N3H02	4.3	±3%	130mA	0.88	201	General	50 MHz - 20 GHz
LQP01HV4N7H02	4.7	±3%	100mA	1.3	201	General	50 MHz - 20 GHz
LQP01HV5N1H02	5.1	±3%	100mA	1.3	201	General	50 MHz - 20 GHz
LQP01HV5N6H02	5.6	±3%	100mA	1.3	201	General	50 MHz - 20 GHz
LQP01HV6N2H02	6.2	±3%	100mA	1.5	201	General	50 MHz - 20 GHz
LQP01HV6N8H02	6.8	±3%	100mA	1.6	201	General	50 MHz - 20 GHz
LQP01HV7N5H02	7.5	±3%	70mA	1.65	201	General	50 MHz - 20 GHz
LQP01HV8N2H02	8.2	±3%	70mA	2	201	General	50 MHz - 20 GHz
LQP01HV9N1H02	9.1	±3%	70mA	2	201	General	50 MHz - 20 GHz
LQP01HV10NH02	10	±3%	70mA	2.3	201	General	50 MHz - 20 GHz
LQP01HV11NH02	11	±3%	70mA	2.8	201	General	50 MHz - 20 GHz
LQP01HV12NH02	12	±3%	70mA	2.8	201	General	50 MHz - 20 GHz
LQP01HV13NH02	13	±3%	70mA	3.3	201	General	50 MHz - 20 GHz
LQP01HV15NH02	15	±3%	70mA	3.7	201	General	50 MHz - 20 GHz
LQP01HV16NH02	16	±3%	70mA	3.7	201	General	50 MHz - 20 GHz
LQP02HQ0N4B02	0.4	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HQ0N4C02	0.4	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HQ0N4W02	0.4	±0.05nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HQ0N5B02	0.5	±0.1nH	1000mA	0.04	402	General	50 MHz - 20 GHz
LQP02HQ0N5C02	0.5	±0.2nH	1000mA	0.04	402	General	50 MHz - 20 GHz
LQP02HQ0N5W02	0.5	±0.05nH	1000mA	0.04	402	General	50 MHz - 20 GHz
LQP02HQ0N6B02	0.6	±0.1nH	950mA	0.05	402	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02HQ0N6C02	0.6	±0.2nH	950mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N6W02	0.6	±0.05nH	950mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N7B02	0.7	±0.1nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N7C02	0.7	±0.2nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N7W02	0.7	±0.05nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N8B02	0.8	±0.1nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N8C02	0.8	±0.2nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N8W02	0.8	±0.05nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N9B02	0.9	±0.1nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N9C02	0.9	±0.2nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ0N9W02	0.9	±0.05nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ1N0B02	1	±0.1nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ1N0C02	1	±0.2nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ1N0W02	1	±0.05nH	900mA	0.05	402	General	50 MHz - 20 GHz
LQP02HQ1N1B02	1.1	±0.1nH	850mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N1C02	1.1	±0.2nH	850mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N1W02	1.1	±0.05nH	850mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N2B02	1.2	±0.1nH	800mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N2C02	1.2	±0.2nH	800mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N2W02	1.2	±0.05nH	800mA	0.06	402	General	50 MHz - 20 GHz
LQP02HQ1N3B02	1.3	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N3C02	1.3	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N3W02	1.3	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N4B02	1.4	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N4C02	1.4	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N4W02	1.4	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N5B02	1.5	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N5C02	1.5	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N5W02	1.5	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N6B02	1.6	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N6C02	1.6	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N6W02	1.6	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N7B02	1.7	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N7C02	1.7	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N7W02	1.7	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N8B02	1.8	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N8C02	1.8	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N8W02	1.8	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N9B02	1.9	±0.1nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N9C02	1.9	±0.2nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ1N9W02	1.9	±0.05nH	700mA	0.08	402	General	50 MHz - 20 GHz
LQP02HQ2N0B02	2	±0.1nH	700mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N0C02	2	±0.2nH	700mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N0W02	2	±0.05nH	700mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N1B02	2.1	±0.1nH	650mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N1C02	2.1	±0.2nH	650mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N1W02	2.1	±0.05nH	650mA	0.1	402	General	50 MHz - 20 GHz
LQP02HQ2N2B02	2.2	±0.1nH	500mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N2C02	2.2	±0.2nH	500mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N2W02	2.2	±0.05nH	500mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N3B02	2.3	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N3C02	2.3	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N3W02	2.3	±0.05nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N4B02	2.4	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N4C02	2.4	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N4W02	2.4	±0.05nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N5B02	2.5	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N5C02	2.5	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N5W02	2.5	±0.05nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N6B02	2.6	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N6C02	2.6	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N7B02	2.7	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N7C02	2.7	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N8B02	2.8	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N8C02	2.8	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N9B02	2.9	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ2N9C02	2.9	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ3N0B02	3	±0.1nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ3N0C02	3	±0.2nH	450mA	0.2	402	General	50 MHz - 20 GHz
LQP02HQ3N1B02	3.1	±0.1nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N1C02	3.1	±0.2nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N2B02	3.2	±0.1nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N2C02	3.2	±0.2nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N3B02	3.3	±0.1nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N3C02	3.3	±0.2nH	400mA	0.25	402	General	50 MHz - 20 GHz
LQP02HQ3N4B02	3.4	±0.1nH	400mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N4C02	3.4	±0.2nH	400mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N5B02	3.5	±0.1nH	350mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N5C02	3.5	±0.2nH	350mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N6B02	3.6	±0.1nH	350mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N6C02	3.6	±0.2nH	350mA	0.3	402	General	50 MHz - 20 GHz
LQP02HQ3N7B02	3.7	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ3N7C02	3.7	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ3N8B02	3.8	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ3N8C02	3.8	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ3N9B02	3.9	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ3N9C02	3.9	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N0B02	4	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N0C02	4	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N1B02	4.1	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N1C02	4.1	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N2B02	4.2	±0.1nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N2C02	4.2	±0.2nH	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N3H02	4.3	±3%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N3J02	4.3	±5%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N7H02	4.7	±3%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ4N7J02	4.7	±5%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ5N1H02	5.1	±3%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ5N1J02	5.1	±5%	350mA	0.35	402	General	50 MHz - 20 GHz
LQP02HQ5N6H02	5.6	±3%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ5N6J02	5.6	±5%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ6N2H02	6.2	±3%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ6N2J02	6.2	±5%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ6N8H02	6.8	±3%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ6N8J02	6.8	±5%	300mA	0.4	402	General	50 MHz - 20 GHz
LQP02HQ7N5H02	7.5	±3%	300mA	0.5	402	General	50 MHz - 20 GHz
LQP02HQ7N5J02	7.5	±5%	300mA	0.5	402	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02HQ8N2H02	8.2	±3%	300mA	0.5	402	General	50 MHz - 20 GHz
LQP02HQ8N2J02	8.2	±5%	300mA	0.5	402	General	50 MHz - 20 GHz
LQP02HQ9N1H02	9.1	±3%	300mA	0.5	402	General	50 MHz - 20 GHz
LQP02HQ9N1J02	9.1	±5%	300mA	0.5	402	General	50 MHz - 20 GHz
LQP02HQ10NH02	10	±3%	250mA	0.6	402	General	50 MHz - 20 GHz
LQP02HQ10NJ02	10	±5%	250mA	0.6	402	General	50 MHz - 20 GHz
LQP02HQ11NH02	11	±3%	250mA	0.8	402	General	50 MHz - 20 GHz
LQP02HQ11NJ02	11	±5%	250mA	0.8	402	General	50 MHz - 20 GHz
LQP02HQ12NH02	12	±3%	230mA	0.82	402	General	50 MHz - 20 GHz
LQP02HQ12NJ02	12	±5%	230mA	0.82	402	General	50 MHz - 20 GHz
LQP02HQ13NH02	13	±3%	210mA	0.99	402	General	50 MHz - 20 GHz
LQP02HQ13NJ02	13	±5%	210mA	0.99	402	General	50 MHz - 20 GHz
LQP02HQ15NH02	15	±3%	170mA	1.53	402	General	50 MHz - 20 GHz
LQP02HQ15NJ02	15	±5%	170mA	1.53	402	General	50 MHz - 20 GHz
LQP02HQ16NH02	16	±3%	170mA	1.53	402	General	50 MHz - 20 GHz
LQP02HQ16NJ02	16	±5%	170mA	1.53	402	General	50 MHz - 20 GHz
LQP02HQ18NH02	18	±3%	160mA	1.63	402	General	50 MHz - 20 GHz
LQP02HQ18NJ02	18	±5%	160mA	1.63	402	General	50 MHz - 20 GHz
LQP02HQ20NH02	20	±3%	140mA	2.26	402	General	50 MHz - 20 GHz
LQP02HQ20NJ02	20	±5%	140mA	2.26	402	General	50 MHz - 20 GHz
LQP02HQ22NH02	22	±3%	140mA	2.26	402	General	50 MHz - 20 GHz
LQP02HQ22NJ02	22	±5%	140mA	2.26	402	General	50 MHz - 20 GHz
LQP02HQ24NH02	24	±3%	120mA	2.6	402	General	50 MHz - 20 GHz
LQP02HQ24NJ02	24	±5%	120mA	2.6	402	General	50 MHz - 20 GHz
LQP02HQ27NH02	27	±3%	120mA	2.6	402	General	50 MHz - 20 GHz
LQP02HQ27NJ02	27	±5%	120mA	2.6	402	General	50 MHz - 20 GHz
LQP02HQ30NH02	30	±3%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02HQ30NJ02	30	±5%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02HQ33NH02	33	±3%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02HQ33NJ02	33	±5%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02HQ36NH02	36	±3%	110mA	3.6	402	General	50 MHz - 20 GHz
LQP02HQ36NJ02	36	±5%	110mA	3.6	402	General	50 MHz - 20 GHz
LQP02HQ39NH02	39	±3%	110mA	3.6	402	General	50 MHz - 20 GHz
LQP02HQ39NJ02	39	±5%	110mA	3.6	402	General	50 MHz - 20 GHz
LQP02HQ43NH02	43	±3%	100mA	4	402	General	50 MHz - 20 GHz
LQP02HQ43NJ02	43	±5%	100mA	4	402	General	50 MHz - 20 GHz
LQP02HQ47NH02	47	±3%	100mA	4	402	General	50 MHz - 20 GHz
LQP02HQ47NJ02	47	±5%	100mA	4	402	General	50 MHz - 20 GHz
LQP02HQ51NH02	51	±3%	100mA	4.2	402	General	50 MHz - 20 GHz
LQP02HQ51NJ02	51	±5%	100mA	4.2	402	General	50 MHz - 20 GHz
LQP02HQ56NH02	56	±3%	100mA	4.2	402	General	50 MHz - 20 GHz
LQP02HQ56NJ02	56	±5%	100mA	4.2	402	General	50 MHz - 20 GHz
LQP02HQ0N4BZ2	0.4	±0.1nH	1000mA	0.03	402	Infotainment	50 MHz - 20 GHz
LQP02HQ0N5BZ2	0.5	±0.1nH	1000mA	0.04	402	Infotainment	50 MHz - 20 GHz
LQP02HQ0N6BZ2	0.6	±0.1nH	950mA	0.05	402	Infotainment	50 MHz - 20 GHz
LQP02HQ0N7BZ2	0.7	±0.1nH	900mA	0.05	402	Infotainment	50 MHz - 20 GHz
LQP02HQ0N8BZ2	0.8	±0.1nH	900mA	0.05	402	Infotainment	50 MHz - 20 GHz
LQP02HQ0N9BZ2	0.9	±0.1nH	900mA	0.05	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N0BZ2	1	±0.1nH	900mA	0.05	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N1BZ2	1.1	±0.1nH	850mA	0.06	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N2BZ2	1.2	±0.1nH	800mA	0.06	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N3BZ2	1.3	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N4BZ2	1.4	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N5BZ2	1.5	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N6BZ2	1.6	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N7BZ2	1.7	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N8BZ2	1.8	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ1N9BZ2	1.9	±0.1nH	700mA	0.08	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N0BZ2	2	±0.1nH	700mA	0.1	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N1BZ2	2.1	±0.1nH	650mA	0.1	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N2BZ2	2.2	±0.1nH	500mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N3BZ2	2.3	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N4BZ2	2.4	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N5BZ2	2.5	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N6BZ2	2.6	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N7BZ2	2.7	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N8BZ2	2.8	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ2N9BZ2	2.9	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N0BZ2	3	±0.1nH	450mA	0.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N1BZ2	3.1	±0.1nH	400mA	0.25	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N2BZ2	3.2	±0.1nH	400mA	0.25	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N3BZ2	3.3	±0.1nH	400mA	0.25	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N4BZ2	3.4	±0.1nH	400mA	0.3	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N5BZ2	3.5	±0.1nH	350mA	0.3	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N6BZ2	3.6	±0.1nH	350mA	0.3	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N7BZ2	3.7	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N8BZ2	3.8	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ3N9BZ2	3.9	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ4N0BZ2	4	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ4N1BZ2	4.1	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ4N2BZ2	4.2	±0.1nH	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ4N3HZ2	4.3	±3%	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ4N7HZ2	4.7	±3%	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ5N1HZ2	5.1	±3%	350mA	0.35	402	Infotainment	50 MHz - 20 GHz
LQP02HQ5N6HZ2	5.6	±3%	300mA	0.4	402	Infotainment	50 MHz - 20 GHz
LQP02HQ6N2HZ2	6.2	±3%	300mA	0.4	402	Infotainment	50 MHz - 20 GHz
LQP02HQ6N8HZ2	6.8	±3%	300mA	0.4	402	Infotainment	50 MHz - 20 GHz
LQP02HQ7N5HZ2	7.5	±3%	300mA	0.5	402	Infotainment	50 MHz - 20 GHz
LQP02HQ8N2HZ2	8.2	±3%	300mA	0.5	402	Infotainment	50 MHz - 20 GHz
LQP02HQ9N1HZ2	9.1	±3%	300mA	0.5	402	Infotainment	50 MHz - 20 GHz
LQP02HQ10NHZ2	10	±3%	250mA	0.6	402	Infotainment	50 MHz - 20 GHz
LQP02HQ11NHZ2	11	±3%	250mA	0.8	402	Infotainment	50 MHz - 20 GHz
LQP02HQ12NHZ2	12	±3%	230mA	0.82	402	Infotainment	50 MHz - 20 GHz
LQP02HQ13NHZ2	13	±3%	210mA	0.99	402	Infotainment	50 MHz - 20 GHz
LQP02HQ15NHZ2	15	±3%	170mA	1.53	402	Infotainment	50 MHz - 20 GHz
LQP02HQ16NHZ2	16	±3%	170mA	1.53	402	Infotainment	50 MHz - 20 GHz
LQP02HQ18NHZ2	18	±3%	160mA	1.63	402	Infotainment	50 MHz - 20 GHz
LQP02HQ20NHZ2	20	±3%	140mA	2.26	402	Infotainment	50 MHz - 20 GHz
LQP02HQ22NHZ2	22	±3%	140mA	2.26	402	Infotainment	50 MHz - 20 GHz
LQP02HQ24NHZ2	24	±3%	120mA	2.6	402	Infotainment	50 MHz - 20 GHz
LQP02HQ27NHZ2	27	±3%	120mA	2.6	402	Infotainment	50 MHz - 20 GHz
LQP02HQ30NHZ2	30	±3%	120mA	3.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ33NHZ2	33	±3%	120mA	3.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ36NHZ2	36	±3%	110mA	3.6	402	Infotainment	50 MHz - 20 GHz
LQP02HQ39NHZ2	39	±3%	110mA	3.6	402	Infotainment	50 MHz - 20 GHz
LQP02HQ43NHZ2	43	±3%	100mA	4	402	Infotainment	50 MHz - 20 GHz
LQP02HQ47NHZ2	47	±3%	100mA	4	402	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02HQ51NHZ2	51	±3%	100mA	4.2	402	Infotainment	50 MHz - 20 GHz
LQP02HQ56NHZ2	56	±3%	100mA	4.2	402	Infotainment	50 MHz - 20 GHz
LQP02HV0N4B02	0.4	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N4C02	0.4	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N5B02	0.5	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N5C02	0.5	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N6B02	0.6	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N6C02	0.6	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N7B02	0.7	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N7C02	0.7	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N8B02	0.8	±0.1nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N8C02	0.8	±0.2nH	1000mA	0.03	402	General	50 MHz - 20 GHz
LQP02HV0N9B02	0.9	±0.1nH	900mA	0.04	402	General	50 MHz - 20 GHz
LQP02HV0N9C02	0.9	±0.2nH	900mA	0.04	402	General	50 MHz - 20 GHz
LQP02HV1N0B02	1	±0.1nH	900mA	0.04	402	General	50 MHz - 20 GHz
LQP02HV1N0C02	1	±0.2nH	900mA	0.04	402	General	50 MHz - 20 GHz
LQP02HV1N1B02	1.1	±0.1nH	800mA	0.05	402	General	50 MHz - 20 GHz
LQP02HV1N1C02	1.1	±0.2nH	800mA	0.05	402	General	50 MHz - 20 GHz
LQP02HV1N2B02	1.2	±0.1nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N2C02	1.2	±0.2nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N3B02	1.3	±0.1nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N3C02	1.3	±0.2nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N4B02	1.4	±0.1nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N4C02	1.4	±0.2nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N5B02	1.5	±0.1nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N5C02	1.5	±0.2nH	730mA	0.06	402	General	50 MHz - 20 GHz
LQP02HV1N6B02	1.6	±0.1nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N6C02	1.6	±0.2nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N7B02	1.7	±0.1nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N7C02	1.7	±0.2nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N8B02	1.8	±0.1nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N8C02	1.8	±0.2nH	680mA	0.07	402	General	50 MHz - 20 GHz
LQP02HV1N9B02	1.9	±0.1nH	640mA	0.08	402	General	50 MHz - 20 GHz
LQP02HV1N9C02	1.9	±0.2nH	640mA	0.08	402	General	50 MHz - 20 GHz
LQP02HV2N0B02	2	±0.1nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N0C02	2	±0.2nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N1B02	2.1	±0.1nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N1C02	2.1	±0.2nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N2B02	2.2	±0.1nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N2C02	2.2	±0.2nH	600mA	0.09	402	General	50 MHz - 20 GHz
LQP02HV2N3B02	2.3	±0.1nH	540mA	0.11	402	General	50 MHz - 20 GHz
LQP02HV2N3C02	2.3	±0.2nH	540mA	0.11	402	General	50 MHz - 20 GHz
LQP02HV2N4B02	2.4	±0.1nH	420mA	0.18	402	General	50 MHz - 20 GHz
LQP02HV2N4C02	2.4	±0.2nH	420mA	0.18	402	General	50 MHz - 20 GHz
LQP02HV2N5B02	2.5	±0.1nH	410mA	0.19	402	General	50 MHz - 20 GHz
LQP02HV2N5C02	2.5	±0.2nH	410mA	0.19	402	General	50 MHz - 20 GHz
LQP02HV2N6B02	2.6	±0.1nH	410mA	0.19	402	General	50 MHz - 20 GHz
LQP02HV2N6C02	2.6	±0.2nH	410mA	0.19	402	General	50 MHz - 20 GHz
LQP02HV2N7B02	2.7	±0.1nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV2N7C02	2.7	±0.2nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV2N8B02	2.8	±0.1nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV2N8C02	2.8	±0.2nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV2N9B02	2.9	±0.1nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV2N9C02	2.9	±0.2nH	390mA	0.21	402	General	50 MHz - 20 GHz
LQP02HV3N0B02	3	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N0C02	3	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N1B02	3.1	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N1C02	3.1	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N2B02	3.2	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N2C02	3.2	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N3B02	3.3	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N3C02	3.3	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N4B02	3.4	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N4C02	3.4	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N5B02	3.5	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N5C02	3.5	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N6B02	3.6	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N6C02	3.6	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N7B02	3.7	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N7C02	3.7	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N8B02	3.8	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N8C02	3.8	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N9B02	3.9	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV3N9C02	3.9	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N0B02	4	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N0C02	4	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N1B02	4.1	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N1C02	4.1	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N2B02	4.2	±0.1nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N2C02	4.2	±0.2nH	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N3H02	4.3	±3%	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N3J02	4.3	±5%	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N7H02	4.7	±3%	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV4N7J02	4.7	±5%	360mA	0.24	402	General	50 MHz - 20 GHz
LQP02HV5N1H02	5.1	±3%	360mA	0.25	402	General	50 MHz - 20 GHz
LQP02HV5N1J02	5.1	±5%	360mA	0.25	402	General	50 MHz - 20 GHz
LQP02HV5N6H02	5.6	±3%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV5N6J02	5.6	±5%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV6N2H02	6.2	±3%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV6N2J02	6.2	±5%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV6N8H02	6.8	±3%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV6N8J02	6.8	±5%	260mA	0.46	402	General	50 MHz - 20 GHz
LQP02HV7N5H02	7.5	±3%	240mA	0.53	402	General	50 MHz - 20 GHz
LQP02HV7N5J02	7.5	±5%	240mA	0.53	402	General	50 MHz - 20 GHz
LQP02HV8N2H02	8.2	±3%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV8N2J02	8.2	±5%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV9N1H02	9.1	±3%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV9N1J02	9.1	±5%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV10NH02	10	±3%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV10NJ02	10	±5%	230mA	0.57	402	General	50 MHz - 20 GHz
LQP02HV11NH02	11	±3%	220mA	0.65	402	General	50 MHz - 20 GHz
LQP02HV11NJ02	11	±5%	220mA	0.65	402	General	50 MHz - 20 GHz
LQP02HV12NH02	12	±3%	220mA	0.65	402	General	50 MHz - 20 GHz
LQP02HV12NJ02	12	±5%	220mA	0.65	402	General	50 MHz - 20 GHz
LQP02HV13NH02	13	±3%	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02HV13NJ02	13	±5%	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02HV15NH02	15	±3%	180mA	0.97	402	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02HV15NJ02	15	±5%	180mA	0.97	402	General	50 MHz - 20 GHz
LQP02HV16NH02	16	±3%	170mA	1.08	402	General	50 MHz - 20 GHz
LQP02HV16NJ02	16	±5%	170mA	1.08	402	General	50 MHz - 20 GHz
LQP02HV18NH02	18	±3%	170mA	1.08	402	General	50 MHz - 20 GHz
LQP02HV18NJ02	18	±5%	170mA	1.08	402	General	50 MHz - 20 GHz
LQP02HV20NH02	20	±3%	140mA	1.48	402	General	50 MHz - 20 GHz
LQP02HV20NJ02	20	±5%	140mA	1.48	402	General	50 MHz - 20 GHz
LQP02HV22NH02	22	±3%	140mA	1.48	402	General	50 MHz - 20 GHz
LQP02HV22NJ02	22	±5%	140mA	1.48	402	General	50 MHz - 20 GHz
LQP02HV24NH02	24	±3%	120mA	2	402	General	50 MHz - 20 GHz
LQP02HV24NJ02	24	±5%	120mA	2	402	General	50 MHz - 20 GHz
LQP02HV27NH02	27	±3%	120mA	2	402	General	50 MHz - 20 GHz
LQP02HV27NJ02	27	±5%	120mA	2	402	General	50 MHz - 20 GHz
LQP02TN0N2B02	0.2	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N2C02	0.2	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N3B02	0.3	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N3C02	0.3	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N4B02	0.4	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N4C02	0.4	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N5B02	0.5	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N5C02	0.5	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N6B02	0.6	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N6C02	0.6	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N7B02	0.7	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N7C02	0.7	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N8B02	0.8	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N8C02	0.8	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N9B02	0.9	±0.1nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN0N9C02	0.9	±0.2nH	320mA	0.5	402	General	50 MHz - 20 GHz
LQP02TN1N0B02	1	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N0C02	1	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N1B02	1.1	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N1C02	1.1	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N2B02	1.2	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N2C02	1.2	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N3B02	1.3	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N3C02	1.3	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N4B02	1.4	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N4C02	1.4	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N5B02	1.5	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N5C02	1.5	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N6B02	1.6	±0.1nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N6C02	1.6	±0.2nH	220mA	0.6	402	General	50 MHz - 20 GHz
LQP02TN1N7B02	1.7	±0.1nH	200mA	0.7	402	General	50 MHz - 20 GHz
LQP02TN1N7C02	1.7	±0.2nH	200mA	0.7	402	General	50 MHz - 20 GHz
LQP02TN1N8B02	1.8	±0.1nH	200mA	0.7	402	General	50 MHz - 20 GHz
LQP02TN1N8C02	1.8	±0.2nH	200mA	0.7	402	General	50 MHz - 20 GHz
LQP02TN1N9B02	1.9	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN1N9C02	1.9	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N0B02	2	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N0C02	2	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N1B02	2.1	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N1C02	2.1	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N2B02	2.2	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N2C02	2.2	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N3B02	2.3	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N3C02	2.3	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N4B02	2.4	±0.1nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N4C02	2.4	±0.2nH	200mA	0.75	402	General	50 MHz - 20 GHz
LQP02TN2N5B02	2.5	±0.1nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N5C02	2.5	±0.2nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N6B02	2.6	±0.1nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N6C02	2.6	±0.2nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N7B02	2.7	±0.1nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N7C02	2.7	±0.2nH	200mA	0.8	402	General	50 MHz - 20 GHz
LQP02TN2N8B02	2.8	±0.1nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN2N8C02	2.8	±0.2nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN2N9B02	2.9	±0.1nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN2N9C02	2.9	±0.2nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN3N0B02	3	±0.1nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN3N0C02	3	±0.2nH	200mA	1.1	402	General	50 MHz - 20 GHz
LQP02TN3N1B02	3.1	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N1C02	3.1	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N2B02	3.2	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N2C02	3.2	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N3B02	3.3	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N3C02	3.3	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N4B02	3.4	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N4C02	3.4	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N5B02	3.5	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N5C02	3.5	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N6B02	3.6	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N6C02	3.6	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N7B02	3.7	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N7C02	3.7	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N8B02	3.8	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N8C02	3.8	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N9B02	3.9	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN3N9C02	3.9	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N0B02	4	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N0C02	4	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N1B02	4.1	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N1C02	4.1	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N2B02	4.2	±0.1nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N2C02	4.2	±0.2nH	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N3H02	4.3	±3%	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N3J02	4.3	±5%	180mA	1.3	402	General	50 MHz - 20 GHz
LQP02TN4N7H02	4.7	±3%	160mA	1.5	402	General	50 MHz - 20 GHz
LQP02TN4N7J02	4.7	±5%	160mA	1.5	402	General	50 MHz - 20 GHz
LQP02TN5N1H02	5.1	±3%	160mA	1.5	402	General	50 MHz - 20 GHz
LQP02TN5N1J02	5.1	±5%	160mA	1.5	402	General	50 MHz - 20 GHz
LQP02TN5N6H02	5.6	±3%	140mA	1.8	402	General	50 MHz - 20 GHz
LQP02TN5N6J02	5.6	±5%	140mA	1.8	402	General	50 MHz - 20 GHz
LQP02TN6N2H02	6.2	±3%	140mA	1.8	402	General	50 MHz - 20 GHz
LQP02TN6N2J02	6.2	±5%	140mA	1.8	402	General	50 MHz - 20 GHz
LQP02TN6N8H02	6.8	±3%	140mA	2	402	General	50 MHz - 20 GHz
LQP02TN6N8J02	6.8	±5%	140mA	2	402	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02TN7N5H02	7.5	±3%	140mA	2	402	General	50 MHz - 20 GHz
LQP02TN7N5J02	7.5	±5%	140mA	2	402	General	50 MHz - 20 GHz
LQP02TN8N2H02	8.2	±3%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TN8N2J02	8.2	±5%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TN9N1H02	9.1	±3%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TN9N1J02	9.1	±5%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TN10NH02	10	±3%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TN10NJ02	10	±5%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TN11NH02	11	±3%	140mA	2.8	402	General	50 MHz - 20 GHz
LQP02TN11NJ02	11	±5%	140mA	2.8	402	General	50 MHz - 20 GHz
LQP02TN12NH02	12	±3%	140mA	2.8	402	General	50 MHz - 20 GHz
LQP02TN12NJ02	12	±5%	140mA	2.8	402	General	50 MHz - 20 GHz
LQP02TN13NH02	13	±3%	140mA	3.2	402	General	50 MHz - 20 GHz
LQP02TN13NJ02	13	±5%	140mA	3.2	402	General	50 MHz - 20 GHz
LQP02TN15NH02	15	±3%	140mA	3.2	402	General	50 MHz - 20 GHz
LQP02TN15NJ02	15	±5%	140mA	3.2	402	General	50 MHz - 20 GHz
LQP02TN16NH02	16	±3%	140mA	3.5	402	General	50 MHz - 20 GHz
LQP02TN16NJ02	16	±5%	140mA	3.5	402	General	50 MHz - 20 GHz
LQP02TN18NH02	18	±3%	140mA	3.5	402	General	50 MHz - 20 GHz
LQP02TN18NJ02	18	±5%	140mA	3.5	402	General	50 MHz - 20 GHz
LQP02TN20NH02	20	±3%	120mA	5	402	General	50 MHz - 20 GHz
LQP02TN20NJ02	20	±5%	120mA	5	402	General	50 MHz - 20 GHz
LQP02TN22NH02	22	±3%	120mA	5	402	General	50 MHz - 20 GHz
LQP02TN22NJ02	22	±5%	120mA	5	402	General	50 MHz - 20 GHz
LQP02TN24NH02	24	±3%	120mA	5.5	402	General	50 MHz - 20 GHz
LQP02TN24NJ02	24	±5%	120mA	5.5	402	General	50 MHz - 20 GHz
LQP02TN27NH02	27	±3%	120mA	5.5	402	General	50 MHz - 20 GHz
LQP02TN27NJ02	27	±5%	120mA	5.5	402	General	50 MHz - 20 GHz
LQP02TN30NH02	30	±3%	90mA	6.5	402	General	50 MHz - 20 GHz
LQP02TN30NJ02	30	±5%	90mA	6.5	402	General	50 MHz - 20 GHz
LQP02TN33NH02	33	±3%	90mA	6.5	402	General	50 MHz - 20 GHz
LQP02TN33NJ02	33	±5%	90mA	6.5	402	General	50 MHz - 20 GHz
LQP02TN36NH02	36	±3%	90mA	7	402	General	50 MHz - 20 GHz
LQP02TN36NJ02	36	±5%	90mA	7	402	General	50 MHz - 20 GHz
LQP02TN39NH02	39	±3%	90mA	7	402	General	50 MHz - 20 GHz
LQP02TN39NJ02	39	±5%	90mA	7	402	General	50 MHz - 20 GHz
LQP02TQ0N2B02	0.2	±0.1nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N2C02	0.2	±0.2nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N3B02	0.3	±0.1nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N3C02	0.3	±0.2nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N4B02	0.4	±0.1nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N4C02	0.4	±0.2nH	990mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N5B02	0.5	±0.1nH	730mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N5C02	0.5	±0.2nH	730mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N6B02	0.6	±0.1nH	730mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N6C02	0.6	±0.2nH	730mA	0.1	402	General	50 MHz - 20 GHz
LQP02TQ0N7B02	0.7	±0.1nH	630mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ0N7C02	0.7	±0.2nH	630mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ0N8B02	0.8	±0.1nH	630mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ0N8C02	0.8	±0.2nH	630mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ0N9B02	0.9	±0.1nH	580mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ0N9C02	0.9	±0.2nH	580mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ1N0B02	1	±0.1nH	580mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ1N0C02	1	±0.2nH	580mA	0.15	402	General	50 MHz - 20 GHz
LQP02TQ1N1B02	1.1	±0.1nH	570mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N1C02	1.1	±0.2nH	570mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N2B02	1.2	±0.1nH	550mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N2C02	1.2	±0.2nH	550mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N3B02	1.3	±0.1nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N3C02	1.3	±0.2nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N4B02	1.4	±0.1nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N4C02	1.4	±0.2nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N5B02	1.5	±0.1nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N5C02	1.5	±0.2nH	400mA	0.2	402	General	50 MHz - 20 GHz
LQP02TQ1N6B02	1.6	±0.1nH	390mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N6C02	1.6	±0.2nH	390mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N7B02	1.7	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N7C02	1.7	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N8B02	1.8	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N8C02	1.8	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N9B02	1.9	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ1N9C02	1.9	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N0B02	2	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N0C02	2	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N1B02	2.1	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N1C02	2.1	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N2B02	2.2	±0.1nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N2C02	2.2	±0.2nH	380mA	0.3	402	General	50 MHz - 20 GHz
LQP02TQ2N3B02	2.3	±0.1nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N3C02	2.3	±0.2nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N4B02	2.4	±0.1nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N4C02	2.4	±0.2nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N5B02	2.5	±0.1nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N5C02	2.5	±0.2nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N6B02	2.6	±0.1nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N6C02	2.6	±0.2nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N7B02	2.7	±0.1nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N7C02	2.7	±0.2nH	370mA	0.4	402	General	50 MHz - 20 GHz
LQP02TQ2N8B02	2.8	±0.1nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ2N8C02	2.8	±0.2nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ2N9B02	2.9	±0.1nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ2N9C02	2.9	±0.2nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ3N0B02	3	±0.1nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ3N0C02	3	±0.2nH	360mA	0.45	402	General	50 MHz - 20 GHz
LQP02TQ3N1B02	3.1	±0.1nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N1C02	3.1	±0.2nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N2B02	3.2	±0.1nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N2C02	3.2	±0.2nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N3B02	3.3	±0.1nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N3C02	3.3	±0.2nH	290mA	0.9	402	General	50 MHz - 20 GHz
LQP02TQ3N4B02	3.4	±0.1nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N4C02	3.4	±0.2nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N5B02	3.5	±0.1nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N5C02	3.5	±0.2nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N6B02	3.6	±0.1nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N6C02	3.6	±0.2nH	280mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N7B02	3.7	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP02TQ3N7C02	3.7	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N8B02	3.8	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N8C02	3.8	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N9B02	3.9	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ3N9C02	3.9	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N0B02	4	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N0C02	4	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N1B02	4.1	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N1C02	4.1	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N2B02	4.2	±0.1nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N2C02	4.2	±0.2nH	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N3H02	4.3	±3%	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N3J02	4.3	±5%	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N7H02	4.7	±3%	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ4N7J02	4.7	±5%	270mA	1	402	General	50 MHz - 20 GHz
LQP02TQ5N1H02	5.1	±3%	250mA	1.2	402	General	50 MHz - 20 GHz
LQP02TQ5N1J02	5.1	±5%	250mA	1.2	402	General	50 MHz - 20 GHz
LQP02TQ5N6H02	5.6	±3%	230mA	1.3	402	General	50 MHz - 20 GHz
LQP02TQ5N6J02	5.6	±5%	230mA	1.3	402	General	50 MHz - 20 GHz
LQP02TQ6N2H02	6.2	±3%	220mA	1.3	402	General	50 MHz - 20 GHz
LQP02TQ6N2J02	6.2	±5%	220mA	1.3	402	General	50 MHz - 20 GHz
LQP02TQ6N8H02	6.8	±3%	210mA	1.4	402	General	50 MHz - 20 GHz
LQP02TQ6N8J02	6.8	±5%	210mA	1.4	402	General	50 MHz - 20 GHz
LQP02TQ7N5H02	7.5	±3%	200mA	1.5	402	General	50 MHz - 20 GHz
LQP02TQ7N5J02	7.5	±5%	200mA	1.5	402	General	50 MHz - 20 GHz
LQP02TQ8N2H02	8.2	±3%	190mA	1.6	402	General	50 MHz - 20 GHz
LQP02TQ8N2J02	8.2	±5%	190mA	1.6	402	General	50 MHz - 20 GHz
LQP02TQ9N1H02	9.1	±3%	170mA	1.7	402	General	50 MHz - 20 GHz
LQP02TQ9N1J02	9.1	±5%	170mA	1.7	402	General	50 MHz - 20 GHz
LQP02TQ10NH02	10	±3%	170mA	1.7	402	General	50 MHz - 20 GHz
LQP02TQ10NJ02	10	±5%	170mA	1.7	402	General	50 MHz - 20 GHz
LQP02TQ11NH02	11	±3%	140mA	1.9	402	General	50 MHz - 20 GHz
LQP02TQ11NJ02	11	±5%	140mA	1.9	402	General	50 MHz - 20 GHz
LQP02TQ12NH02	12	±3%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TQ12NJ02	12	±5%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TQ13NH02	13	±3%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TQ13NJ02	13	±5%	140mA	2.1	402	General	50 MHz - 20 GHz
LQP02TQ14NH02	14	±3%	140mA	2.3	402	General	50 MHz - 20 GHz
LQP02TQ14NJ02	14	±5%	140mA	2.3	402	General	50 MHz - 20 GHz
LQP02TQ15NH02	15	±3%	140mA	2.3	402	General	50 MHz - 20 GHz
LQP02TQ15NJ02	15	±5%	140mA	2.3	402	General	50 MHz - 20 GHz
LQP02TQ16NH02	16	±3%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ16NJ02	16	±5%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ17NH02	17	±3%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ17NJ02	17	±5%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ18NH02	18	±3%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ18NJ02	18	±5%	140mA	2.5	402	General	50 MHz - 20 GHz
LQP02TQ19NH02	19	±3%	140mA	2.9	402	General	50 MHz - 20 GHz
LQP02TQ19NJ02	19	±5%	140mA	2.9	402	General	50 MHz - 20 GHz
LQP02TQ20NH02	20	±3%	140mA	2.9	402	General	50 MHz - 20 GHz
LQP02TQ20NJ02	20	±5%	140mA	2.9	402	General	50 MHz - 20 GHz
LQP02TQ21NH02	21	±3%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02TQ21NJ02	21	±5%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02TQ22NH02	22	±3%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP02TQ22NJ02	22	±5%	120mA	3.2	402	General	50 MHz - 20 GHz
LQP03HQ0N6B02	0.6	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N6C02	0.6	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N6W02	0.6	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N7B02	0.7	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N7C02	0.7	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N7W02	0.7	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N8B02	0.8	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N8C02	0.8	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N8W02	0.8	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N9B02	0.9	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N9C02	0.9	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ0N9W02	0.9	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N0B02	1	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N0C02	1	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N0W02	1	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N1B02	1.1	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N1C02	1.1	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N1W02	1.1	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N2B02	1.2	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N2C02	1.2	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N2W02	1.2	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N3B02	1.3	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N3C02	1.3	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N3W02	1.3	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N4B02	1.4	±0.1nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N4C02	1.4	±0.2nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N4W02	1.4	±0.05nH	1100mA	0.04	603	General	50 MHz - 20 GHz
LQP03HQ1N5B02	1.5	±0.1nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N5C02	1.5	±0.2nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N5W02	1.5	±0.05nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N6B02	1.6	±0.1nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N6C02	1.6	±0.2nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N6W02	1.6	±0.05nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03HQ1N7B02	1.7	±0.1nH	800mA	0.07	603	General	50 MHz - 20 GHz
LQP03HQ1N7C02	1.7	±0.2nH	800mA	0.07	603	General	50 MHz - 20 GHz
LQP03HQ1N7W02	1.7	±0.05nH	800mA	0.07	603	General	50 MHz - 20 GHz
LQP03HQ1N8B02	1.8	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03HQ1N8C02	1.8	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03HQ1N8W02	1.8	±0.05nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03HQ1N9B02	1.9	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ1N9C02	1.9	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ1N9W02	1.9	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N0B02	2	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N0C02	2	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N0W02	2	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N1B02	2.1	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N1C02	2.1	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N1W02	2.1	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N2B02	2.2	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N2C02	2.2	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N2W02	2.2	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N3B02	2.3	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03HQ2N3C02	2.3	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N3W02	2.3	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N4B02	2.4	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N4C02	2.4	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N4W02	2.4	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N5B02	2.5	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N5C02	2.5	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N5W02	2.5	±0.05nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N6B02	2.6	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N6C02	2.6	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N7B02	2.7	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N7C02	2.7	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N8B02	2.8	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N8C02	2.8	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N9B02	2.9	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ2N9C02	2.9	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ3N0B02	3	±0.1nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ3N0C02	3	±0.2nH	600mA	0.12	603	General	50 MHz - 20 GHz
LQP03HQ3N1B02	3.1	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N1C02	3.1	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N2B02	3.2	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N2C02	3.2	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N3B02	3.3	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N3C02	3.3	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N4B02	3.4	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N4C02	3.4	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N5B02	3.5	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N5C02	3.5	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N6B02	3.6	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N6C02	3.6	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N7B02	3.7	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N7C02	3.7	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N8B02	3.8	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N8C02	3.8	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N9B02	3.9	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ3N9C02	3.9	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N0B02	4	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N0C02	4	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N1B02	4.1	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N1C02	4.1	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N2B02	4.2	±0.1nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N2C02	4.2	±0.2nH	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N3H02	4.3	±3%	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N3J02	4.3	±5%	500mA	0.17	603	General	50 MHz - 20 GHz
LQP03HQ4N4H02	4.4	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N4J02	4.4	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N5H02	4.5	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N5J02	4.5	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N6H02	4.6	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N6J02	4.6	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N7H02	4.7	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N7J02	4.7	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N8H02	4.8	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N8J02	4.8	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N9H02	4.9	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ4N9J02	4.9	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N0H02	5	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N0J02	5	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N1H02	5.1	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N1J02	5.1	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N6H02	5.6	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ5N6J02	5.6	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ6N2H02	6.2	±3%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ6N2J02	6.2	±5%	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03HQ6N8H02	6.8	±3%	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03HQ6N8J02	6.8	±5%	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03HQ7N5H02	7.5	±3%	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03HQ7N5J02	7.5	±5%	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03HQ8N2H02	8.2	±3%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ8N2J02	8.2	±5%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ9N1H02	9.1	±3%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ9N1J02	9.1	±5%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ10N0H02	10	±3%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ10N0J02	10	±5%	300mA	0.4	603	General	50 MHz - 20 GHz
LQP03HQ11N0H02	11	±3%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ11N0J02	11	±5%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ12N0H02	12	±3%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ12N0J02	12	±5%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ13N0H02	13	±3%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ13N0J02	13	±5%	300mA	0.5	603	General	50 MHz - 20 GHz
LQP03HQ15N0H02	15	±3%	300mA	0.7	603	General	50 MHz - 20 GHz
LQP03HQ15N0J02	15	±5%	300mA	0.7	603	General	50 MHz - 20 GHz
LQP03HQ16N0H02	16	±3%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ16N0J02	16	±5%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ18N0H02	18	±3%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ18N0J02	18	±5%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ20N0H02	20	±3%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ20N0J02	20	±5%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03HQ22N0H02	22	±3%	250mA	0.82	603	General	50 MHz - 20 GHz
LQP03HQ22N0J02	22	±5%	250mA	0.82	603	General	50 MHz - 20 GHz
LQP03HQ24N0H02	24	±3%	170mA	1.6	603	General	50 MHz - 20 GHz
LQP03HQ24N0J02	24	±5%	170mA	1.6	603	General	50 MHz - 20 GHz
LQP03HQ27N0H02	27	±3%	170mA	1.6	603	General	50 MHz - 20 GHz
LQP03HQ27N0J02	27	±5%	170mA	1.6	603	General	50 MHz - 20 GHz
LQP03HQ30N0H02	30	±3%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ30N0J02	30	±5%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ33N0H02	33	±3%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ33N0J02	33	±5%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ36N0H02	36	±3%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ36N0J02	36	±5%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ39N0H02	39	±3%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ39N0J02	39	±5%	150mA	2	603	General	50 MHz - 20 GHz
LQP03HQ43N0H02	43	±3%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ43N0J02	43	±5%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ47N0H02	47	±3%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ47N0J02	47	±5%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ51N0H02	51	±3%	130mA	2.5	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03HQ51NJ02	51	±5%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ56NH02	56	±3%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ56NJ02	56	±5%	130mA	2.5	603	General	50 MHz - 20 GHz
LQP03HQ62NH02	62	±3%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ62NJ02	62	±5%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ68NH02	68	±3%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ68NJ02	68	±5%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ75NH02	75	±3%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ75NJ02	75	±5%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ82NH02	82	±3%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ82NJ02	82	±5%	100mA	5	603	General	50 MHz - 20 GHz
LQP03HQ91NH02	91	±3%	80mA	7	603	General	50 MHz - 20 GHz
LQP03HQ91NJ02	91	±5%	80mA	7	603	General	50 MHz - 20 GHz
LQP03HQ10H02	100	±3%	80mA	7	603	General	50 MHz - 20 GHz
LQP03HQ10J02	100	±5%	80mA	7	603	General	50 MHz - 20 GHz
LQP03HQ11H02	110	±3%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ11J02	110	±5%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ12H02	120	±3%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ12J02	120	±5%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ13H02	130	±3%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ13J02	130	±5%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ15H02	150	±3%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ15J02	150	±5%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ16H02	160	±3%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ16J02	160	±5%	80mA	8	603	General	50 MHz - 20 GHz
LQP03HQ18H02	180	±3%	80mA	8.5	603	General	50 MHz - 20 GHz
LQP03HQ18J02	180	±5%	80mA	8.5	603	General	50 MHz - 20 GHz
LQP03HQ20H02	200	±3%	75mA	9	603	General	50 MHz - 20 GHz
LQP03HQ20J02	200	±5%	75mA	9	603	General	50 MHz - 20 GHz
LQP03HQ22H02	220	±3%	75mA	9.5	603	General	50 MHz - 20 GHz
LQP03HQ22J02	220	±5%	75mA	9.5	603	General	50 MHz - 20 GHz
LQP03HQ24H02	240	±3%	70mA	10	603	General	50 MHz - 20 GHz
LQP03HQ24J02	240	±5%	70mA	10	603	General	50 MHz - 20 GHz
LQP03HQ27H02	270	±3%	70mA	11	603	General	50 MHz - 20 GHz
LQP03HQ27J02	270	±5%	70mA	11	603	General	50 MHz - 20 GHz
LQP03HQ30H02	300	±3%	65mA	12	603	General	50 MHz - 20 GHz
LQP03HQ30J02	300	±5%	65mA	12	603	General	50 MHz - 20 GHz
LQP03HQ33H02	330	±3%	65mA	13	603	General	50 MHz - 20 GHz
LQP03HQ33J02	330	±5%	65mA	13	603	General	50 MHz - 20 GHz
LQP03HQ36H02	360	±3%	60mA	13.5	603	General	50 MHz - 20 GHz
LQP03HQ36J02	360	±5%	60mA	13.5	603	General	50 MHz - 20 GHz
LQP03HQ39H02	390	±3%	60mA	14.5	603	General	50 MHz - 20 GHz
LQP03HQ39J02	390	±5%	60mA	14.5	603	General	50 MHz - 20 GHz
LQP03HQ43H02	430	±3%	50mA	15.5	603	General	50 MHz - 20 GHz
LQP03HQ43J02	430	±5%	50mA	15.5	603	General	50 MHz - 20 GHz
LQP03HQ47H02	470	±3%	50mA	16.5	603	General	50 MHz - 20 GHz
LQP03HQ47J02	470	±5%	50mA	16.5	603	General	50 MHz - 20 GHz
LQP03PN2N2C02	2.2	±0.2nH	1400mA	0.055	603	General	50 MHz - 20 GHz
LQP03PN2N7C02	2.7	±0.2nH	1300mA	0.065	603	General	50 MHz - 20 GHz
LQP03PN3N3C02	3.3	±0.2nH	1200mA	0.08	603	General	50 MHz - 20 GHz
LQP03PN3N9C02	3.9	±0.2nH	1000mA	0.1	603	General	50 MHz - 20 GHz
LQP03PN4N7J02	4.7	±5%	900mA	0.14	603	General	50 MHz - 20 GHz
LQP03TG0N1B02	0.1	±0.1nH	850mA	0.07	603	General	50 MHz - 20 GHz
LQP03TG0N2B02	0.2	±0.1nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N2C02	0.2	±0.2nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N3B02	0.3	±0.1nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N3C02	0.3	±0.2nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N4B02	0.4	±0.1nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N4C02	0.4	±0.2nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N5B02	0.5	±0.1nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N5C02	0.5	±0.2nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N6B02	0.6	±0.1nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N6C02	0.6	±0.2nH	850mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG0N7B02	0.7	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG0N7C02	0.7	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG0N8B02	0.8	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG0N8C02	0.8	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG0N9B02	0.9	±0.1nH	700mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG0N9C02	0.9	±0.2nH	700mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG1N0B02	1	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N0C02	1	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N1B02	1.1	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N1C02	1.1	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N2B02	1.2	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N2C02	1.2	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N3B02	1.3	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N3C02	1.3	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N4B02	1.4	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N4C02	1.4	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N5B02	1.5	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N5C02	1.5	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N6B02	1.6	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N6C02	1.6	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG1N7B02	1.7	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TG1N7C02	1.7	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TG1N8B02	1.8	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TG1N8C02	1.8	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TG1N9B02	1.9	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG1N9C02	1.9	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N0B02	2	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N0C02	2	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N1B02	2.1	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N1C02	2.1	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N2B02	2.2	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N2C02	2.2	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N3B02	2.3	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N3C02	2.3	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N4B02	2.4	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N4C02	2.4	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N5B02	2.5	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N5C02	2.5	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N6B02	2.6	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N6C02	2.6	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N7B02	2.7	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N7C02	2.7	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N8B02	2.8	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N8C02	2.8	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03TG2N9B02	2.9	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG2N9C02	2.9	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG3N0B02	3	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG3N0C02	3	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TG3N1B02	3.1	±0.1nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N1C02	3.1	±0.2nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N2B02	3.2	±0.1nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N2C02	3.2	±0.2nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N3B02	3.3	±0.1nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N3C02	3.3	±0.2nH	400mA	0.32	603	General	50 MHz - 20 GHz
LQP03TG3N4B02	3.4	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N4C02	3.4	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N5B02	3.5	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N5C02	3.5	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N6B02	3.6	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N6C02	3.6	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N7B02	3.7	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N7C02	3.7	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N8B02	3.8	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N8C02	3.8	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N9B02	3.9	±0.1nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG3N9C02	3.9	±0.2nH	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TG4N3H02	4.3	±3%	300mA	0.58	603	General	50 MHz - 20 GHz
LQP03TG4N3J02	4.3	±5%	300mA	0.58	603	General	50 MHz - 20 GHz
LQP03TG4N7H02	4.7	±3%	250mA	0.72	603	General	50 MHz - 20 GHz
LQP03TG4N7J02	4.7	±5%	250mA	0.72	603	General	50 MHz - 20 GHz
LQP03TG5N1H02	5.1	±3%	250mA	0.72	603	General	50 MHz - 20 GHz
LQP03TG5N1J02	5.1	±5%	250mA	0.72	603	General	50 MHz - 20 GHz
LQP03TG5N6H02	5.6	±3%	250mA	0.88	603	General	50 MHz - 20 GHz
LQP03TG5N6J02	5.6	±5%	250mA	0.88	603	General	50 MHz - 20 GHz
LQP03TG6N2H02	6.2	±3%	200mA	1.15	603	General	50 MHz - 20 GHz
LQP03TG6N2J02	6.2	±5%	200mA	1.15	603	General	50 MHz - 20 GHz
LQP03TG6N8H02	6.8	±3%	200mA	1.15	603	General	50 MHz - 20 GHz
LQP03TG6N8J02	6.8	±5%	200mA	1.15	603	General	50 MHz - 20 GHz
LQP03TG7N5H02	7.5	±3%	200mA	1.22	603	General	50 MHz - 20 GHz
LQP03TG7N5J02	7.5	±5%	200mA	1.22	603	General	50 MHz - 20 GHz
LQP03TG8N2H02	8.2	±3%	200mA	1.4	603	General	50 MHz - 20 GHz
LQP03TG8N2J02	8.2	±5%	200mA	1.4	603	General	50 MHz - 20 GHz
LQP03TG9N1H02	9.1	±3%	200mA	1.4	603	General	50 MHz - 20 GHz
LQP03TG9N1J02	9.1	±5%	200mA	1.4	603	General	50 MHz - 20 GHz
LQP03TG10NH02	10	±3%	190mA	1.52	603	General	50 MHz - 20 GHz
LQP03TG10NJ02	10	±5%	190mA	1.52	603	General	50 MHz - 20 GHz
LQP03TG11NH02	11	±3%	180mA	1.65	603	General	50 MHz - 20 GHz
LQP03TG11NJ02	11	±5%	180mA	1.65	603	General	50 MHz - 20 GHz
LQP03TG12NH02	12	±3%	180mA	1.78	603	General	50 MHz - 20 GHz
LQP03TG12NJ02	12	±5%	180mA	1.78	603	General	50 MHz - 20 GHz
LQP03TG13NH02	13	±3%	170mA	1.82	603	General	50 MHz - 20 GHz
LQP03TG13NJ02	13	±5%	170mA	1.82	603	General	50 MHz - 20 GHz
LQP03TG15NH02	15	±3%	170mA	1.9	603	General	50 MHz - 20 GHz
LQP03TG15NJ02	15	±5%	170mA	1.9	603	General	50 MHz - 20 GHz
LQP03TG16NH02	16	±3%	160mA	2.03	603	General	50 MHz - 20 GHz
LQP03TG16NJ02	16	±5%	160mA	2.03	603	General	50 MHz - 20 GHz
LQP03TG18NH02	18	±3%	160mA	2.28	603	General	50 MHz - 20 GHz
LQP03TG18NJ02	18	±5%	160mA	2.28	603	General	50 MHz - 20 GHz
LQP03TG20NH02	20	±3%	140mA	2.57	603	General	50 MHz - 20 GHz
LQP03TG20NJ02	20	±5%	140mA	2.57	603	General	50 MHz - 20 GHz
LQP03TG22NH02	22	±3%	140mA	2.85	603	General	50 MHz - 20 GHz
LQP03TG22NJ02	22	±5%	140mA	2.85	603	General	50 MHz - 20 GHz
LQP03TG24NH02	24	±3%	120mA	3.17	603	General	50 MHz - 20 GHz
LQP03TG24NJ02	24	±5%	120mA	3.17	603	General	50 MHz - 20 GHz
LQP03TG27NH02	27	±3%	120mA	3.65	603	General	50 MHz - 20 GHz
LQP03TG27NJ02	27	±5%	120mA	3.65	603	General	50 MHz - 20 GHz
LQP03TG33NJ02	33	±5%	110mA	4.25	603	General	50 MHz - 20 GHz
LQP03TG39NJ02	39	±5%	110mA	4.6	603	General	50 MHz - 20 GHz
LQP03TG47NJ02	47	±5%	100mA	5.2	603	General	50 MHz - 20 GHz
LQP03TG56NJ02	56	±5%	100mA	5.6	603	General	50 MHz - 20 GHz
LQP03TG68NJ02	68	±5%	90mA	6.25	603	General	50 MHz - 20 GHz
LQP03TG82NJ02	82	±5%	90mA	7.15	603	General	50 MHz - 20 GHz
LQP03TGR10J02	100	±5%	80mA	8.05	603	General	50 MHz - 20 GHz
LQP03TGR12J02	120	±5%	80mA	8.75	603	General	50 MHz - 20 GHz
LQP03TN0N6B02	0.6	±0.1nH	850mA	0.07	603	General	50 MHz - 20 GHz
LQP03TN0N6C02	0.6	±0.2nH	850mA	0.07	603	General	50 MHz - 20 GHz
LQP03TN0N7B02	0.7	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TN0N7C02	0.7	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TN0N8B02	0.8	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TN0N8C02	0.8	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TN0N9B02	0.9	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN0N9C02	0.9	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N0B02	1	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N0C02	1	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N1B02	1.1	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N1C02	1.1	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N2B02	1.2	±0.1nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N2C02	1.2	±0.2nH	750mA	0.1	603	General	50 MHz - 20 GHz
LQP03TN1N3B02	1.3	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N3C02	1.3	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N4B02	1.4	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N4C02	1.4	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N5B02	1.5	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N5C02	1.5	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N6B02	1.6	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N6C02	1.6	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N7B02	1.7	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N7C02	1.7	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N8B02	1.8	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N8C02	1.8	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N9B02	1.9	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN1N9C02	1.9	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N0B02	2	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N0C02	2	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N1B02	2.1	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N1C02	2.1	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N2B02	2.2	±0.1nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N2C02	2.2	±0.2nH	600mA	0.15	603	General	50 MHz - 20 GHz
LQP03TN2N3B02	2.3	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N3C02	2.3	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N4B02	2.4	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03TN2N4C02	2.4	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N5B02	2.5	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N5C02	2.5	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N6B02	2.6	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N6C02	2.6	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N7B02	2.7	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N7C02	2.7	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N8B02	2.8	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N8C02	2.8	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N9B02	2.9	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN2N9C02	2.9	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TN3N0B02	3	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N0C02	3	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N1B02	3.1	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N1C02	3.1	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N2B02	3.2	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N2C02	3.2	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N3B02	3.3	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N3C02	3.3	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N4B02	3.4	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N4C02	3.4	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N5B02	3.5	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N5C02	3.5	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TN3N6B02	3.6	±0.1nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N6C02	3.6	±0.2nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N7B02	3.7	±0.1nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N7C02	3.7	±0.2nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N8B02	3.8	±0.1nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N8C02	3.8	±0.2nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N9B02	3.9	±0.1nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN3N9C02	3.9	±0.2nH	400mA	0.3	603	General	50 MHz - 20 GHz
LQP03TN4N0B02	4	±0.1nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N0C02	4	±0.2nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N1B02	4.1	±0.1nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N1C02	4.1	±0.2nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N2B02	4.2	±0.1nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N2C02	4.2	±0.2nH	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N3H02	4.3	±3%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N3J02	4.3	±5%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N7H02	4.7	±3%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN4N7J02	4.7	±5%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN5N1H02	5.1	±3%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN5N1J02	5.1	±5%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN5N6H02	5.6	±3%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN5N6J02	5.6	±5%	350mA	0.4	603	General	50 MHz - 20 GHz
LQP03TN6N2H02	6.2	±3%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN6N2J02	6.2	±5%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN6N8H02	6.8	±3%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN6N8J02	6.8	±5%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN7N5H02	7.5	±3%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN7N5J02	7.5	±5%	300mA	0.6	603	General	50 MHz - 20 GHz
LQP03TN8N2H02	8.2	±3%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN8N2J02	8.2	±5%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN9N1H02	9.1	±3%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN9N1J02	9.1	±5%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN10NH02	10	±3%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN10NJ02	10	±5%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN11NH02	11	±3%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN11NJ02	11	±5%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN12NH02	12	±3%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN12NJ02	12	±5%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN13NH02	13	±3%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN13NJ02	13	±5%	250mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN15NH02	15	±3%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN15NJ02	15	±5%	250mA	0.7	603	General	50 MHz - 20 GHz
LQP03TN16NH02	16	±3%	200mA	0.95	603	General	50 MHz - 20 GHz
LQP03TN16NJ02	16	±5%	200mA	0.95	603	General	50 MHz - 20 GHz
LQP03TN18NH02	18	±3%	200mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN18NJ02	18	±5%	200mA	0.8	603	General	50 MHz - 20 GHz
LQP03TN20NH02	20	±3%	150mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN20NJ02	20	±5%	150mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN22NH02	22	±3%	150mA	1.9	603	General	50 MHz - 20 GHz
LQP03TN22NJ02	22	±5%	150mA	1.9	603	General	50 MHz - 20 GHz
LQP03TN24NH02	24	±3%	140mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN24NJ02	24	±5%	140mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN27NH02	27	±3%	140mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN27NJ02	27	±5%	140mA	2.3	603	General	50 MHz - 20 GHz
LQP03TN30NH02	30	±3%	120mA	2.95	603	General	50 MHz - 20 GHz
LQP03TN30NJ02	30	±5%	120mA	2.95	603	General	50 MHz - 20 GHz
LQP03TN33NH02	33	±3%	120mA	2.95	603	General	50 MHz - 20 GHz
LQP03TN33NJ02	33	±5%	120mA	2.95	603	General	50 MHz - 20 GHz
LQP03TN36NH02	36	±3%	120mA	3	603	General	50 MHz - 20 GHz
LQP03TN36NJ02	36	±5%	120mA	3	603	General	50 MHz - 20 GHz
LQP03TN39NH02	39	±3%	120mA	3	603	General	50 MHz - 20 GHz
LQP03TN39NJ02	39	±5%	120mA	3	603	General	50 MHz - 20 GHz
LQP03TN43NH02	43	±3%	100mA	3.6	603	General	50 MHz - 20 GHz
LQP03TN43NJ02	43	±5%	100mA	3.6	603	General	50 MHz - 20 GHz
LQP03TN47NH02	47	±3%	100mA	3.6	603	General	50 MHz - 20 GHz
LQP03TN47NJ02	47	±5%	100mA	3.6	603	General	50 MHz - 20 GHz
LQP03TN51NH02	51	±3%	100mA	3.9	603	General	50 MHz - 20 GHz
LQP03TN51NJ02	51	±5%	100mA	3.9	603	General	50 MHz - 20 GHz
LQP03TN56NH02	56	±3%	100mA	3.9	603	General	50 MHz - 20 GHz
LQP03TN56NJ02	56	±5%	100mA	3.9	603	General	50 MHz - 20 GHz
LQP03TN62NH02	62	±3%	100mA	8	603	General	50 MHz - 20 GHz
LQP03TN62NJ02	62	±5%	100mA	8	603	General	50 MHz - 20 GHz
LQP03TN68NH02	68	±3%	100mA	8	603	General	50 MHz - 20 GHz
LQP03TN68NJ02	68	±5%	100mA	8	603	General	50 MHz - 20 GHz
LQP03TN75NH02	75	±3%	100mA	10	603	General	50 MHz - 20 GHz
LQP03TN75NJ02	75	±5%	100mA	10	603	General	50 MHz - 20 GHz
LQP03TN82NH02	82	±3%	100mA	10	603	General	50 MHz - 20 GHz
LQP03TN82NJ02	82	±5%	100mA	10	603	General	50 MHz - 20 GHz
LQP03TN91NH02	91	±3%	80mA	10	603	General	50 MHz - 20 GHz
LQP03TN91NJ02	91	±5%	80mA	10	603	General	50 MHz - 20 GHz
LQP03TNR10H02	100	±3%	80mA	10	603	General	50 MHz - 20 GHz
LQP03TNR10J02	100	±5%	80mA	10	603	General	50 MHz - 20 GHz
LQP03TNR11H02	110	±3%	80mA	12	603	General	50 MHz - 20 GHz
LQP03TNR11J02	110	±5%	80mA	12	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03TNR12H02	120	±3%	80mA	12	603	General	50 MHz - 20 GHz
LQP03TNR12J02	120	±5%	80mA	12	603	General	50 MHz - 20 GHz
LQP03TNR13H02	130	±3%	80mA	9	603	General	50 MHz - 20 GHz
LQP03TNR13J02	130	±5%	80mA	9	603	General	50 MHz - 20 GHz
LQP03TNR15H02	150	±3%	80mA	9	603	General	50 MHz - 20 GHz
LQP03TNR15J02	150	±5%	80mA	9	603	General	50 MHz - 20 GHz
LQP03TNR16H02	160	±3%	70mA	11	603	General	50 MHz - 20 GHz
LQP03TNR16J02	160	±5%	70mA	11	603	General	50 MHz - 20 GHz
LQP03TNR18H02	180	±3%	70mA	11	603	General	50 MHz - 20 GHz
LQP03TNR18J02	180	±5%	70mA	11	603	General	50 MHz - 20 GHz
LQP03TNR20H02	200	±3%	60mA	13	603	General	50 MHz - 20 GHz
LQP03TNR20J02	200	±5%	60mA	13	603	General	50 MHz - 20 GHz
LQP03TNR22H02	220	±3%	60mA	13	603	General	50 MHz - 20 GHz
LQP03TNR22J02	220	±5%	60mA	13	603	General	50 MHz - 20 GHz
LQP03TNR24H02	240	±3%	60mA	15	603	General	50 MHz - 20 GHz
LQP03TNR24J02	240	±5%	60mA	15	603	General	50 MHz - 20 GHz
LQP03TNR27H02	270	±3%	60mA	15	603	General	50 MHz - 20 GHz
LQP03TNR27J02	270	±5%	60mA	15	603	General	50 MHz - 20 GHz
LQP03TN0N6BZ2	0.6	±0.1nH	850mA	0.07	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N6CZ2	0.6	±0.2nH	850mA	0.07	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N7BZ2	0.7	±0.1nH	800mA	0.08	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N7CZ2	0.7	±0.2nH	800mA	0.08	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N8BZ2	0.8	±0.1nH	800mA	0.08	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N8CZ2	0.8	±0.2nH	800mA	0.08	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N9BZ2	0.9	±0.1nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN0N9CZ2	0.9	±0.2nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N0BZ2	1	±0.1nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N0CZ2	1	±0.2nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N1BZ2	1.1	±0.1nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N1CZ2	1.1	±0.2nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N2BZ2	1.2	±0.1nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N2CZ2	1.2	±0.2nH	750mA	0.1	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N3BZ2	1.3	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N3CZ2	1.3	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N4BZ2	1.4	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N4CZ2	1.4	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N5BZ2	1.5	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N5CZ2	1.5	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N6BZ2	1.6	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N6CZ2	1.6	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N7BZ2	1.7	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N7CZ2	1.7	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N8BZ2	1.8	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N8CZ2	1.8	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N9BZ2	1.9	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN1N9CZ2	1.9	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N0BZ2	2	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N0CZ2	2	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N1BZ2	2.1	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N1CZ2	2.1	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N2BZ2	2.2	±0.1nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N2CZ2	2.2	±0.2nH	600mA	0.15	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N3BZ2	2.3	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N3CZ2	2.3	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N4BZ2	2.4	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N4CZ2	2.4	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N5BZ2	2.5	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N5CZ2	2.5	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N6BZ2	2.6	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N6CZ2	2.6	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N7BZ2	2.7	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N7CZ2	2.7	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N8BZ2	2.8	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N8CZ2	2.8	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N9BZ2	2.9	±0.1nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN2N9CZ2	2.9	±0.2nH	500mA	0.2	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N0BZ2	3	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N0CZ2	3	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N1BZ2	3.1	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N1CZ2	3.1	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N2BZ2	3.2	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N2CZ2	3.2	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N3BZ2	3.3	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N3CZ2	3.3	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N4BZ2	3.4	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N4CZ2	3.4	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N5BZ2	3.5	±0.1nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N5CZ2	3.5	±0.2nH	450mA	0.25	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N6BZ2	3.6	±0.1nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N6CZ2	3.6	±0.2nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N7BZ2	3.7	±0.1nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N7CZ2	3.7	±0.2nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N8BZ2	3.8	±0.1nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N8CZ2	3.8	±0.2nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N9BZ2	3.9	±0.1nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN3N9CZ2	3.9	±0.2nH	400mA	0.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N0BZ2	4	±0.1nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N0CZ2	4	±0.2nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N1BZ2	4.1	±0.1nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N1CZ2	4.1	±0.2nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N2BZ2	4.2	±0.1nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N2CZ2	4.2	±0.2nH	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N3HJ2	4.3	±3%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N3JZ2	4.3	±5%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N7HJ2	4.7	±3%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN4N7JZ2	4.7	±5%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN5N1HJ2	5.1	±3%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN5N1JZ2	5.1	±5%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN5N6HJ2	5.6	±3%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN5N6JZ2	5.6	±5%	350mA	0.4	603	Infotainment	50 MHz - 20 GHz
LQP03TN6N2HJ2	6.2	±3%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN6N2JZ2	6.2	±5%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN6N8HJ2	6.8	±3%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN6N8JZ2	6.8	±5%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN7N5HJ2	7.5	±3%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN7N5JZ2	7.5	±5%	300mA	0.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN8N2HJ2	8.2	±3%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03TN8N2JZ2	8.2	±5%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN9N1HZ2	9.1	±3%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN9N1JZ2	9.1	±5%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN10NHZ2	10	±3%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN10NJZ2	10	±5%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN11NHZ2	11	±3%	250mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN11NJZ2	11	±5%	250mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN12NHZ2	12	±3%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN12NJZ2	12	±5%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN13NHZ2	13	±3%	250mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN13NJZ2	13	±5%	250mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN15NHZ2	15	±3%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN15NJZ2	15	±5%	250mA	0.7	603	Infotainment	50 MHz - 20 GHz
LQP03TN16NHZ2	16	±3%	200mA	0.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN16NJZ2	16	±5%	200mA	0.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN18NHZ2	18	±3%	200mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN18NJZ2	18	±5%	200mA	0.8	603	Infotainment	50 MHz - 20 GHz
LQP03TN20NHZ2	20	±3%	150mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN20NJZ2	20	±5%	150mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN22NHZ2	22	±3%	150mA	1.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN22NJZ2	22	±5%	150mA	1.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN24NHZ2	24	±3%	140mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN24NJZ2	24	±5%	140mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN27NHZ2	27	±3%	140mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN27NJZ2	27	±5%	140mA	2.3	603	Infotainment	50 MHz - 20 GHz
LQP03TN30NHZ2	30	±3%	120mA	2.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN30NJZ2	30	±5%	120mA	2.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN33NHZ2	33	±3%	120mA	2.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN33NJZ2	33	±5%	120mA	2.95	603	Infotainment	50 MHz - 20 GHz
LQP03TN36NHZ2	36	±3%	120mA	3	603	Infotainment	50 MHz - 20 GHz
LQP03TN36NJZ2	36	±5%	120mA	3	603	Infotainment	50 MHz - 20 GHz
LQP03TN39NHZ2	39	±3%	120mA	3	603	Infotainment	50 MHz - 20 GHz
LQP03TN39NJZ2	39	±5%	120mA	3	603	Infotainment	50 MHz - 20 GHz
LQP03TN43NHZ2	43	±3%	100mA	3.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN43NJZ2	43	±5%	100mA	3.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN47NHZ2	47	±3%	100mA	3.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN47NJZ2	47	±5%	100mA	3.6	603	Infotainment	50 MHz - 20 GHz
LQP03TN51NHZ2	51	±3%	100mA	3.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN51NJZ2	51	±5%	100mA	3.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN56NHZ2	56	±3%	100mA	3.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN56NJZ2	56	±5%	100mA	3.9	603	Infotainment	50 MHz - 20 GHz
LQP03TN62NHZ2	62	±3%	100mA	8	603	Infotainment	50 MHz - 20 GHz
LQP03TN62NJZ2	62	±5%	100mA	8	603	Infotainment	50 MHz - 20 GHz
LQP03TN68NHZ2	68	±3%	100mA	8	603	Infotainment	50 MHz - 20 GHz
LQP03TN68NJZ2	68	±5%	100mA	8	603	Infotainment	50 MHz - 20 GHz
LQP03TN75NHZ2	75	±3%	100mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TN75NJZ2	75	±5%	100mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TN82NHZ2	82	±3%	100mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TN82NJZ2	82	±5%	100mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TN91NHZ2	91	±3%	80mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TN91NJZ2	91	±5%	80mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TNR10HZ2	100	±3%	80mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TNR10JZ2	100	±5%	80mA	10	603	Infotainment	50 MHz - 20 GHz
LQP03TNR11HZ2	110	±3%	80mA	12	603	Infotainment	50 MHz - 20 GHz
LQP03TNR11JZ2	110	±5%	80mA	12	603	Infotainment	50 MHz - 20 GHz
LQP03TNR12HZ2	120	±3%	80mA	12	603	Infotainment	50 MHz - 20 GHz
LQP03TNR12JZ2	120	±5%	80mA	12	603	Infotainment	50 MHz - 20 GHz
LQP03TQ0N6B02	0.6	±0.1nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N6C02	0.6	±0.2nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N6W02	0.6	±0.05nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N7B02	0.7	±0.1nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N7C02	0.7	±0.2nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N7W02	0.7	±0.05nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N8B02	0.8	±0.1nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N8C02	0.8	±0.2nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N8W02	0.8	±0.05nH	1000mA	0.05	603	General	50 MHz - 20 GHz
LQP03TQ0N9B02	0.9	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TQ0N9C02	0.9	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TQ0N9W02	0.9	±0.05nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N0B02	1	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N0C02	1	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N0W02	1	±0.05nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N1B02	1.1	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N1C02	1.1	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N1W02	1.1	±0.05nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N2B02	1.2	±0.1nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N2C02	1.2	±0.2nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N2W02	1.2	±0.05nH	800mA	0.08	603	General	50 MHz - 20 GHz
LQP03TG1N3B02	1.3	±0.1nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N3C02	1.3	±0.2nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N3W02	1.3	±0.05nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N4B02	1.4	±0.1nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N4C02	1.4	±0.2nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N4W02	1.4	±0.05nH	700mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N5B02	1.5	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N5C02	1.5	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N5W02	1.5	±0.05nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N6B02	1.6	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N6C02	1.6	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N7B02	1.7	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N7C02	1.7	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N8B02	1.8	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N8C02	1.8	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N9B02	1.9	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG1N9C02	1.9	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG2N0B02	2	±0.1nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG2N0C02	2	±0.2nH	650mA	0.1	603	General	50 MHz - 20 GHz
LQP03TG2N1B02	2.1	±0.1nH	650mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG2N1C02	2.1	±0.2nH	650mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG2N2B02	2.2	±0.1nH	650mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG2N2C02	2.2	±0.2nH	650mA	0.12	603	General	50 MHz - 20 GHz
LQP03TG2N3B02	2.3	±0.1nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG2N3C02	2.3	±0.2nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG2N4B02	2.4	±0.1nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG2N4C02	2.4	±0.2nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG2N5B02	2.5	±0.1nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TG2N5C02	2.5	±0.2nH	550mA	0.15	603	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQP03TQ2N6B02	2.6	±0.1nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TQ2N6C02	2.6	±0.2nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TQ2N7B02	2.7	±0.1nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TQ2N7C02	2.7	±0.2nH	550mA	0.15	603	General	50 MHz - 20 GHz
LQP03TQ2N8B02	2.8	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ2N8C02	2.8	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ2N9B02	2.9	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ2N9C02	2.9	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ3N0B02	3	±0.1nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ3N0C02	3	±0.2nH	500mA	0.2	603	General	50 MHz - 20 GHz
LQP03TQ3N1B02	3.1	±0.1nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N1C02	3.1	±0.2nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N2B02	3.2	±0.1nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N2C02	3.2	±0.2nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N3B02	3.3	±0.1nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N3C02	3.3	±0.2nH	450mA	0.24	603	General	50 MHz - 20 GHz
LQP03TQ3N4B02	3.4	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N4C02	3.4	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N5B02	3.5	±0.1nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N5C02	3.5	±0.2nH	450mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N6B02	3.6	±0.1nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N6C02	3.6	±0.2nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N7B02	3.7	±0.1nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N7C02	3.7	±0.2nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N8B02	3.8	±0.1nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N8C02	3.8	±0.2nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N9B02	3.9	±0.1nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ3N9C02	3.9	±0.2nH	400mA	0.25	603	General	50 MHz - 20 GHz
LQP03TQ4N0B02	4	±0.1nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N0C02	4	±0.2nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N1B02	4.1	±0.1nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N1C02	4.1	±0.2nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N2B02	4.2	±0.1nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N2C02	4.2	±0.2nH	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N3H02	4.3	±3%	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N3J02	4.3	±5%	360mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N7H02	4.7	±3%	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ4N7J02	4.7	±5%	350mA	0.35	603	General	50 MHz - 20 GHz
LQP03TQ5N1H02	5.1	±3%	350mA	0.39	603	General	50 MHz - 20 GHz
LQP03TQ5N1J02	5.1	±5%	350mA	0.39	603	General	50 MHz - 20 GHz
LQP03TQ5N6H02	5.6	±3%	350mA	0.39	603	General	50 MHz - 20 GHz
LQP03TQ5N6J02	5.6	±5%	350mA	0.39	603	General	50 MHz - 20 GHz
LQP03TQ6N2H02	6.2	±3%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ6N2J02	6.2	±5%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ6N8H02	6.8	±3%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ6N8J02	6.8	±5%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ7N5H02	7.5	±3%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ7N5J02	7.5	±5%	300mA	0.55	603	General	50 MHz - 20 GHz
LQP03TQ8N2H02	8.2	±3%	250mA	0.65	603	General	50 MHz - 20 GHz
LQP03TQ8N2J02	8.2	±5%	250mA	0.65	603	General	50 MHz - 20 GHz
LQP03TQ9N1H02	9.1	±3%	250mA	0.65	603	General	50 MHz - 20 GHz
LQP03TQ9N1J02	9.1	±5%	250mA	0.65	603	General	50 MHz - 20 GHz
LQP03TQ10NH02	10	±3%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ10NJ02	10	±5%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ11NH02	11	±3%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ11NJ02	11	±5%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ12NH02	12	±3%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ12NJ02	12	±5%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ13NH02	13	±3%	250mA	0.69	603	General	50 MHz - 20 GHz
LQP03TQ13NJ02	13	±5%	250mA	0.69	603	General	50 MHz - 20 GHz
LQW03AW1N0C00	1	±0.2nH	900mA	0.03	603	General	50 MHz - 20 GHz
LQW03AW1N1C00	1.1	±0.2nH	660mA	0.06	603	General	50 MHz - 20 GHz
LQW03AW1N7C00	1.7	±0.2nH	600mA	0.07	603	General	50 MHz - 20 GHz
LQW03AW1N8C00	1.8	±0.2nH	520mA	0.1	603	General	50 MHz - 20 GHz
LQW03AW1N9C00	1.9	±0.2nH	620mA	0.08	603	General	50 MHz - 20 GHz
LQW03AW2N0C00	2	±0.2nH	490mA	0.1	603	General	50 MHz - 20 GHz
LQW03AW2N1C00	2.1	±0.2nH	400mA	0.16	603	General	50 MHz - 20 GHz
LQW03AW2N2C00	2.2	±0.2nH	400mA	0.16	603	General	50 MHz - 20 GHz
LQW03AW2N7C00	2.7	±0.2nH	720mA	0.06	603	General	50 MHz - 20 GHz
LQW03AW2N8C00	2.8	±0.2nH	600mA	0.08	603	General	50 MHz - 20 GHz
LQW03AW2N9C00	2.9	±0.2nH	540mA	0.1	603	General	50 MHz - 20 GHz
LQW03AW3N0C00	3	±0.2nH	350mA	0.22	603	General	50 MHz - 20 GHz
LQW03AW3N1C00	3.1	±0.2nH	720mA	0.07	603	General	50 MHz - 20 GHz
LQW03AW3N2C00	3.2	±0.2nH	580mA	0.08	603	General	50 MHz - 20 GHz
LQW03AW3N3C00	3.3	±0.2nH	520mA	0.11	603	General	50 MHz - 20 GHz
LQW03AW3N4C00	3.4	±0.2nH	440mA	0.15	603	General	50 MHz - 20 GHz
LQW03AW3N5C00	3.5	±0.2nH	440mA	0.15	603	General	50 MHz - 20 GHz
LQW03AW3N6C00	3.6	±0.2nH	340mA	0.23	603	General	50 MHz - 20 GHz
LQW03AW3N7C00	3.7	±0.2nH	340mA	0.23	603	General	50 MHz - 20 GHz
LQW03AW3N9C00	3.9	±0.2nH	650mA	0.07	603	General	50 MHz - 20 GHz
LQW03AW4N3J00	4.3	±5%	480mA	0.12	603	General	50 MHz - 20 GHz
LQW03AW4N7J00	4.7	±5%	620mA	0.09	603	General	50 MHz - 20 GHz
LQW03AW5N1J00	5.1	±5%	480mA	0.14	603	General	50 MHz - 20 GHz
LQW03AW5N4J00	5.4	±5%	420mA	0.21	603	General	50 MHz - 20 GHz
LQW03AW5N6J00	5.6	±5%	330mA	0.33	603	General	50 MHz - 20 GHz
LQW03AW5N8J00	5.8	±5%	460mA	0.16	603	General	50 MHz - 20 GHz
LQW03AW6N2J00	6.2	±5%	360mA	0.22	603	General	50 MHz - 20 GHz
LQW03AW6N8J00	6.8	±5%	460mA	0.18	603	General	50 MHz - 20 GHz
LQW03AW7N5J00	7.5	±5%	400mA	0.24	603	General	50 MHz - 20 GHz
LQW03AW8N2J00	8.2	±5%	290mA	0.26	603	General	50 MHz - 20 GHz
LQW03AW8N7J00	8.7	±5%	290mA	0.42	603	General	50 MHz - 20 GHz
LQW03AW9N1J00	9.1	±5%	460mA	0.22	603	General	50 MHz - 20 GHz
LQW03AW10N1J00	10	±5%	250mA	0.46	603	General	50 MHz - 20 GHz
LQW03AW11N1J00	11	±5%	260mA	0.47	603	General	50 MHz - 20 GHz
LQW03AW12N1J00	12.5	±5%	280mA	0.54	603	General	50 MHz - 20 GHz
LQW03AW13N1J00	13	±5%	280mA	0.54	603	General	50 MHz - 20 GHz
LQW03AW14N1J00	13.5	±5%	240mA	0.53	603	General	50 MHz - 20 GHz
LQW03AW15N1J00	15.5	±5%	230mA	0.6	603	General	50 MHz - 20 GHz
LQW04AN0N8C00	0.8	±0.2nH	1800mA	0.02	804	General	50 MHz - 20 GHz
LQW04AN0N8D00	0.8	±0.5nH	1800mA	0.02	804	General	50 MHz - 20 GHz
LQW04AN1N1C00	1.1	±0.2nH	990mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N1D00	1.1	±0.5nH	990mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N3C00	1.3	±0.2nH	1500mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N3D00	1.3	±0.5nH	1500mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N4C00	1.4	±0.2nH	1200mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N4D00	1.4	±0.5nH	1200mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN1N5C00	1.5	±0.2nH	940mA	0.05	804	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW04AN1N5D00	1.5	±0.5nH	940mA	0.05	804	General	50 MHz - 20 GHz
LQW04AN1N6C00	1.6	±0.2nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN1N6D00	1.6	±0.5nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN1N7C00	1.7	±0.2nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN1N7D00	1.7	±0.5nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN1N8C00	1.8	±0.2nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN1N8D00	1.8	±0.5nH	700mA	0.06	804	General	50 MHz - 20 GHz
LQW04AN2N0C00	2	±0.2nH	1100mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN2N0D00	2	±0.5nH	1100mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN2N1C00	2.1	±0.2nH	1100mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN2N1D00	2.1	±0.5nH	1100mA	0.03	804	General	50 MHz - 20 GHz
LQW04AN2N2C00	2.2	±0.2nH	1100mA	0.04	804	General	50 MHz - 20 GHz
LQW04AN2N2D00	2.2	±0.5nH	1100mA	0.04	804	General	50 MHz - 20 GHz
LQW04AN2N3C00	2.3	±0.2nH	780mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N3D00	2.3	±0.5nH	780mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N4C00	2.4	±0.2nH	570mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N4D00	2.4	±0.5nH	570mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N5C00	2.5	±0.2nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN2N5D00	2.5	±0.5nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN2N6C00	2.6	±0.2nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N6D00	2.6	±0.5nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N7C00	2.7	±0.2nH	570mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N7D00	2.7	±0.5nH	570mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N8C00	2.8	±0.2nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N8D00	2.8	±0.5nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN2N9C00	2.9	±0.2nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN2N9D00	2.9	±0.5nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN3N0C00	3	±0.2nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN3N0D00	3	±0.5nH	620mA	0.07	804	General	50 MHz - 20 GHz
LQW04AN3N1C00	3.1	±0.2nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN3N1D00	3.1	±0.5nH	490mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN3N2C00	3.2	±0.2nH	400mA	0.17	804	General	50 MHz - 20 GHz
LQW04AN3N2D00	3.2	±0.5nH	400mA	0.17	804	General	50 MHz - 20 GHz
LQW04AN3N3C00	3.3	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN3N3D00	3.3	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN3N6C00	3.6	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN3N6D00	3.6	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN3N7C00	3.7	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN3N7D00	3.7	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN3N8C00	3.8	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN3N8D00	3.8	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN3N9C00	3.9	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN3N9D00	3.9	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N0C00	4	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N0D00	4	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N1C00	4.1	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N1D00	4.1	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N2C00	4.2	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N2D00	4.2	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N3C00	4.3	±0.2nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N3D00	4.3	±0.5nH	530mA	0.1	804	General	50 MHz - 20 GHz
LQW04AN4N4C00	4.4	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N4D00	4.4	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N5C00	4.5	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N5D00	4.5	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N6C00	4.6	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N6D00	4.6	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N7C00	4.7	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N7D00	4.7	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN4N8C00	4.8	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN4N8D00	4.8	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN4N9C00	4.9	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN4N9D00	4.9	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN5N0C00	5	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN5N0D00	5	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN5N1C00	5.1	±0.2nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N1D00	5.1	±0.5nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N2C00	5.2	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N2D00	5.2	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N3C00	5.3	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N3D00	5.3	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N4C00	5.4	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N4D00	5.4	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N5C00	5.5	±0.2nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N5D00	5.5	±0.5nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N6C00	5.6	±0.2nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N6D00	5.6	±0.5nH	470mA	0.12	804	General	50 MHz - 20 GHz
LQW04AN5N7C00	5.7	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N7D00	5.7	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N8C00	5.8	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N8D00	5.8	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N9C00	5.9	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN5N9D00	5.9	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N0C00	6	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N0D00	6	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N1C00	6.1	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N1D00	6.1	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N2C00	6.2	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N2D00	6.2	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N3C00	6.3	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N3D00	6.3	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N4C00	6.4	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N4D00	6.4	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N5C00	6.5	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N5D00	6.5	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N6C00	6.6	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N6D00	6.6	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N7C00	6.7	±0.2nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N7D00	6.7	±0.5nH	390mA	0.19	804	General	50 MHz - 20 GHz
LQW04AN6N8C00	6.8	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN6N8D00	6.8	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN6N9C00	6.9	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN6N9D00	6.9	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N0C00	7	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N0D00	7	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N1C00	7.1	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N1D00	7.1	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW04AN7N2C00	7.2	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N2D00	7.2	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N3C00	7.3	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N3D00	7.3	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N4C00	7.4	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N4D00	7.4	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N5C00	7.5	±0.2nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N5D00	7.5	±0.5nH	440mA	0.14	804	General	50 MHz - 20 GHz
LQW04AN7N6C00	7.6	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N6D00	7.6	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N7C00	7.7	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N7D00	7.7	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N8C00	7.8	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N8D00	7.8	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N9C00	7.9	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN7N9D00	7.9	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N0C00	8	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N0D00	8	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N1C00	8.1	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N1D00	8.1	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N2C00	8.2	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N2D00	8.2	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N3C00	8.3	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N3D00	8.3	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N4C00	8.4	±0.2nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N4D00	8.4	±0.5nH	350mA	0.23	804	General	50 MHz - 20 GHz
LQW04AN8N5C00	8.5	±0.2nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N5D00	8.5	±0.5nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N6C00	8.6	±0.2nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N6D00	8.6	±0.5nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N7C00	8.7	±0.2nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N7D00	8.7	±0.5nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N8C00	8.8	±0.2nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N8D00	8.8	±0.5nH	290mA	0.33	804	General	50 MHz - 20 GHz
LQW04AN8N9C00	8.9	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN8N9D00	8.9	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N0C00	9	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N0D00	9	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N1C00	9.1	±0.2nH	400mA	0.16	804	General	50 MHz - 20 GHz
LQW04AN9N1D00	9.1	±0.5nH	400mA	0.16	804	General	50 MHz - 20 GHz
LQW04AN9N2C00	9.2	±0.2nH	400mA	0.16	804	General	50 MHz - 20 GHz
LQW04AN9N2D00	9.2	±0.5nH	400mA	0.16	804	General	50 MHz - 20 GHz
LQW04AN9N3C00	9.3	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N3D00	9.3	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N4C00	9.4	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N4D00	9.4	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N5C00	9.5	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N5D00	9.5	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N6C00	9.6	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N6D00	9.6	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N7C00	9.7	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N7D00	9.7	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N8C00	9.8	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N8D00	9.8	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N9C00	9.9	±0.2nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN9N9D00	9.9	±0.5nH	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN10NH00	10	±3%	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN10NJ00	10	±5%	330mA	0.26	804	General	50 MHz - 20 GHz
LQW04AN11NH00	11	±3%	310mA	0.28	804	General	50 MHz - 20 GHz
LQW04AN11NJ00	11	±5%	310mA	0.28	804	General	50 MHz - 20 GHz
LQW04AN12NH00	12	±3%	310mA	0.28	804	General	50 MHz - 20 GHz
LQW04AN12NJ00	12	±5%	310mA	0.28	804	General	50 MHz - 20 GHz
LQW04AN13NH00	13	±3%	280mA	0.34	804	General	50 MHz - 20 GHz
LQW04AN13NJ00	13	±5%	280mA	0.34	804	General	50 MHz - 20 GHz
LQW04AN14NH00	14	±3%	280mA	0.34	804	General	50 MHz - 20 GHz
LQW04AN14NJ00	14	±5%	280mA	0.34	804	General	50 MHz - 20 GHz
LQW04AN15NH00	15	±3%	240mA	0.48	804	General	50 MHz - 20 GHz
LQW04AN15NJ00	15	±5%	240mA	0.48	804	General	50 MHz - 20 GHz
LQW04AN16NH00	16	±3%	270mA	0.38	804	General	50 MHz - 20 GHz
LQW04AN16NJ00	16	±5%	270mA	0.38	804	General	50 MHz - 20 GHz
LQW04AN18NH00	18	±3%	220mA	0.54	804	General	50 MHz - 20 GHz
LQW04AN18NJ00	18	±5%	220mA	0.54	804	General	50 MHz - 20 GHz
LQW04AN19NH00	19	±3%	160mA	0.73	804	General	50 MHz - 20 GHz
LQW04AN19NJ00	19	±5%	160mA	0.73	804	General	50 MHz - 20 GHz
LQW04AN20NH00	20	±3%	210mA	0.56	804	General	50 MHz - 20 GHz
LQW04AN20NJ00	20	±5%	210mA	0.56	804	General	50 MHz - 20 GHz
LQW04AN22NH00	22	±3%	200mA	0.63	804	General	50 MHz - 20 GHz
LQW04AN22NJ00	22	±5%	200mA	0.63	804	General	50 MHz - 20 GHz
LQW04AN23NH00	23	±3%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN23NJ00	23	±5%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN24NH00	24	±3%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN24NJ00	24	±5%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN25NH00	25	±3%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN25NJ00	25	±5%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN27NH00	27	±3%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN27NJ00	27	±5%	160mA	0.95	804	General	50 MHz - 20 GHz
LQW04AN33NH00	33	±3%	140mA	1.11	804	General	50 MHz - 20 GHz
LQW04AN33NJ00	33	±5%	140mA	1.11	804	General	50 MHz - 20 GHz
LQW04AN36NJ10	36	±5%	200mA	1.08	804	General	50 MHz - 20 GHz
LQW04AN39NJ10	39	±5%	200mA	1.08	804	General	50 MHz - 20 GHz
LQW04AN43NJ10	43	±5%	180mA	1.2	804	General	50 MHz - 20 GHz
LQW04AN47NJ10	47	±5%	180mA	1.2	804	General	50 MHz - 20 GHz
LQW04AN52NJ10	52	±5%	180mA	1.32	804	General	50 MHz - 20 GHz
LQW04AN56NJ10	56	±5%	180mA	1.32	804	General	50 MHz - 20 GHz
LQW04AN36NH20	36	±3%	155mA	1.4	804	General	50 MHz - 20 GHz
LQW04AN36NJ20	36	±5%	155mA	1.4	804	General	50 MHz - 20 GHz
LQW04AN39NH20	39	±3%	150mA	1.5	804	General	50 MHz - 20 GHz
LQW04AN39NJ20	39	±5%	150mA	1.5	804	General	50 MHz - 20 GHz
LQW04AN43NH20	43	±3%	145mA	1.6	804	General	50 MHz - 20 GHz
LQW04AN43NJ20	43	±5%	145mA	1.6	804	General	50 MHz - 20 GHz
LQW04AN47NH20	47	±3%	140mA	1.68	804	General	50 MHz - 20 GHz
LQW04AN47NJ20	47	±5%	140mA	1.68	804	General	50 MHz - 20 GHz
LQW04AN52NH20	52	±3%	120mA	2.28	804	General	50 MHz - 20 GHz
LQW04AN52NJ20	52	±5%	120mA	2.28	804	General	50 MHz - 20 GHz
LQW04AN56NH20	56	±3%	120mA	2.28	804	General	50 MHz - 20 GHz
LQW04AN56NJ20	56	±5%	120mA	2.28	804	General	50 MHz - 20 GHz
LQW15AN1N5B00	1.5	±0.1nH	1000mA	0.03	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN1N5C00	1.5	±0.2nH	1000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN1N5D00	1.5	±0.5nH	1000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN1N6C00	1.6	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN1N6D00	1.6	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN1N7C00	1.7	±0.2nH	640mA	0.1	1005	General	50 MHz - 20 GHz
LQW15AN1N7D00	1.7	±0.5nH	640mA	0.1	1005	General	50 MHz - 20 GHz
LQW15AN1N8C00	1.8	±0.2nH	460mA	0.16	1005	General	50 MHz - 20 GHz
LQW15AN1N8D00	1.8	±0.5nH	460mA	0.16	1005	General	50 MHz - 20 GHz
LQW15AN2N4B00	2.4	±0.1nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N4C00	2.4	±0.2nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N4D00	2.4	±0.5nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N5B00	2.5	±0.1nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N5C00	2.5	±0.2nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N5D00	2.5	±0.5nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N6B00	2.6	±0.1nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N6C00	2.6	±0.2nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N6D00	2.6	±0.5nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N7B00	2.7	±0.1nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N7C00	2.7	±0.2nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N7D00	2.7	±0.5nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N8B00	2.8	±0.1nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N8C00	2.8	±0.2nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N8D00	2.8	±0.5nH	850mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN2N9B00	2.9	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN2N9C00	2.9	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN2N9D00	2.9	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N0B00	3	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N0C00	3	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N0D00	3	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N1B00	3.1	±0.1nH	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN3N1C00	3.1	±0.2nH	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN3N1D00	3.1	±0.5nH	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN3N2B00	3.2	±0.1nH	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN3N2C00	3.2	±0.2nH	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN3N2D00	3.2	±0.5nH	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN3N9B00	3.9	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N9C00	3.9	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN3N9D00	3.9	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N1B00	4.1	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N1C00	4.1	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N1D00	4.1	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N3B00	4.3	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N3C00	4.3	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N3D00	4.3	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N4B00	4.4	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N4C00	4.4	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N4D00	4.4	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N5B00	4.5	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N5C00	4.5	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N5D00	4.5	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N6B00	4.6	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N6C00	4.6	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N6D00	4.6	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N7B00	4.7	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N7C00	4.7	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N7D00	4.7	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N8B00	4.8	±0.1nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N8C00	4.8	±0.2nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N8D00	4.8	±0.5nH	750mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN4N9B00	4.9	±0.1nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN4N9C00	4.9	±0.2nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN4N9D00	4.9	±0.5nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N0B00	5	±0.1nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N0C00	5	±0.2nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N0D00	5	±0.5nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N1B00	5.1	±0.1nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N1C00	5.1	±0.2nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N1D00	5.1	±0.5nH	600mA	0.12	1005	General	50 MHz - 20 GHz
LQW15AN5N8B00	5.8	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN5N8C00	5.8	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN5N8D00	5.8	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N2B00	6.2	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N2C00	6.2	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N2D00	6.2	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N3B00	6.3	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N3C00	6.3	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N3D00	6.3	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N4B00	6.4	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N4C00	6.4	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N4D00	6.4	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N5B00	6.5	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N5C00	6.5	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N5D00	6.5	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N6B00	6.6	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N6C00	6.6	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N6D00	6.6	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N7B00	6.7	±0.1nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N7C00	6.7	±0.2nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N7D00	6.7	±0.5nH	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N8G00	6.8	±2%	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N8H00	6.8	±3%	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N8J00	6.8	±5%	700mA	0.09	1005	General	50 MHz - 20 GHz
LQW15AN6N9G00	6.9	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN6N9H00	6.9	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN6N9J00	6.9	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N0G00	7	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N0H00	7	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N0J00	7	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N1G00	7.1	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N1H00	7.1	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N1J00	7.1	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N2G00	7.2	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N2H00	7.2	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N2J00	7.2	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N3G00	7.3	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N3H00	7.3	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N3J00	7.3	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN7N5G00	7.5	±2%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N5H00	7.5	±3%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN7N5J00	7.5	±5%	570mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN8N2G00	8.2	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N2H00	8.2	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N2J00	8.2	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N6G00	8.6	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N6H00	8.6	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N6J00	8.6	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N7G00	8.7	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N7H00	8.7	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N7J00	8.7	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N8G00	8.8	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N8H00	8.8	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N8J00	8.8	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N9G00	8.9	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N9H00	8.9	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN8N9J00	8.9	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N0G00	9	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N0H00	9	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N0J00	9	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N1G00	9.1	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N1H00	9.1	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N1J00	9.1	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N2G00	9.2	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N2H00	9.2	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N2J00	9.2	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N3G00	9.3	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N3H00	9.3	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N3J00	9.3	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N4G00	9.4	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N4H00	9.4	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N4J00	9.4	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N5G00	9.5	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N5H00	9.5	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N5J00	9.5	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N6G00	9.6	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N6H00	9.6	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N6J00	9.6	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N7G00	9.7	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N7H00	9.7	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N7J00	9.7	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N8G00	9.8	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N8H00	9.8	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N8J00	9.8	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N9G00	9.9	±2%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N9H00	9.9	±3%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN9N9J00	9.9	±5%	540mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN10NG00	10	±2%	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN10NH00	10	±3%	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN10NJ00	10	±5%	500mA	0.17	1005	General	50 MHz - 20 GHz
LQW15AN11NG00	11	±2%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN11NH00	11	±3%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN11NJ00	11	±5%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN12NG00	12	±2%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN12NH00	12	±3%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN12NJ00	12	±5%	500mA	0.14	1005	General	50 MHz - 20 GHz
LQW15AN13NG00	13	±2%	430mA	0.21	1005	General	50 MHz - 20 GHz
LQW15AN13NH00	13	±3%	430mA	0.21	1005	General	50 MHz - 20 GHz
LQW15AN13NJ00	13	±5%	430mA	0.21	1005	General	50 MHz - 20 GHz
LQW15AN15NG00	15	±2%	460mA	0.16	1005	General	50 MHz - 20 GHz
LQW15AN15NH00	15	±3%	460mA	0.16	1005	General	50 MHz - 20 GHz
LQW15AN15NJ00	15	±5%	460mA	0.16	1005	General	50 MHz - 20 GHz
LQW15AN16NG00	16	±2%	370mA	0.24	1005	General	50 MHz - 20 GHz
LQW15AN16NH00	16	±3%	370mA	0.24	1005	General	50 MHz - 20 GHz
LQW15AN16NJ00	16	±5%	370mA	0.24	1005	General	50 MHz - 20 GHz
LQW15AN18NG00	18	±2%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN18NH00	18	±3%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN18NJ00	18	±5%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN19NG00	19	±2%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN19NH00	19	±3%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN19NJ00	19	±5%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN20NG00	20	±2%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN20NH00	20	±3%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN20NJ00	20	±5%	370mA	0.27	1005	General	50 MHz - 20 GHz
LQW15AN22NG00	22	±2%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN22NH00	22	±3%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN22NJ00	22	±5%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN23NG00	23	±2%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN23NH00	23	±3%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN23NJ00	23	±5%	310mA	0.3	1005	General	50 MHz - 20 GHz
LQW15AN24NG00	24	±2%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN24NH00	24	±3%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN24NJ00	24	±5%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN27NG00	27	±2%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN27NH00	27	±3%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN27NJ00	27	±5%	280mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AN30NG00	30	±2%	270mA	0.58	1005	General	50 MHz - 20 GHz
LQW15AN30NH00	30	±3%	270mA	0.58	1005	General	50 MHz - 20 GHz
LQW15AN30NJ00	30	±5%	270mA	0.58	1005	General	50 MHz - 20 GHz
LQW15AN33NG00	33	±2%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN33NH00	33	±3%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN33NJ00	33	±5%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN36NG00	36	±2%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN36NH00	36	±3%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN36NJ00	36	±5%	260mA	0.63	1005	General	50 MHz - 20 GHz
LQW15AN39NG00	39	±2%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN39NH00	39	±3%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN39NJ00	39	±5%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN40NG00	40	±2%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN40NH00	40	±3%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN40NJ00	40	±5%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN43NG00	43	±2%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN43NH00	43	±3%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN43NJ00	43	±5%	250mA	0.7	1005	General	50 MHz - 20 GHz
LQW15AN47NG00	47	±2%	210mA	1.08	1005	General	50 MHz - 20 GHz
LQW15AN47NH00	47	±3%	210mA	1.08	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN47NJ00	47	±5%	210mA	1.08	1005	General	50 MHz - 20 GHz
LQW15AN51NG00	51	±2%	210mA	1.08	1005	General	50 MHz - 20 GHz
LQW15AN51NH00	51	±3%	210mA	1.08	1005	General	50 MHz - 20 GHz
LQW15AN51NJ00	51	±5%	210mA	1.08	1005	General	50 MHz - 20 GHz
LQW15AN56NG00	56	±2%	200mA	1.17	1005	General	50 MHz - 20 GHz
LQW15AN56NH00	56	±3%	200mA	1.17	1005	General	50 MHz - 20 GHz
LQW15AN56NJ00	56	±5%	200mA	1.17	1005	General	50 MHz - 20 GHz
LQW15AN62NG00	62	±2%	145mA	1.82	1005	General	50 MHz - 20 GHz
LQW15AN62NH00	62	±3%	145mA	1.82	1005	General	50 MHz - 20 GHz
LQW15AN62NJ00	62	±5%	145mA	1.82	1005	General	50 MHz - 20 GHz
LQW15AN68NG00	68	±2%	140mA	1.96	1005	General	50 MHz - 20 GHz
LQW15AN68NJ00	68	±5%	140mA	1.96	1005	General	50 MHz - 20 GHz
LQW15AN72NG00	72	±2%	135mA	2.1	1005	General	50 MHz - 20 GHz
LQW15AN72NJ00	72	±5%	135mA	2.1	1005	General	50 MHz - 20 GHz
LQW15AN75NG00	75	±2%	135mA	2.1	1005	General	50 MHz - 20 GHz
LQW15AN75NJ00	75	±5%	135mA	2.1	1005	General	50 MHz - 20 GHz
LQW15AN82NG00	82	±2%	130mA	2.24	1005	General	50 MHz - 20 GHz
LQW15AN82NJ00	82	±5%	130mA	2.24	1005	General	50 MHz - 20 GHz
LQW15AN91NG00	91	±2%	125mA	2.38	1005	General	50 MHz - 20 GHz
LQW15AN91NJ00	91	±5%	125mA	2.38	1005	General	50 MHz - 20 GHz
LQW15ANR10J00	100	±5%	120mA	2.52	1005	General	50 MHz - 20 GHz
LQW15ANR12J00	120	±5%	110mA	2.66	1005	General	50 MHz - 20 GHz
LQW15AN1N5B0Z	1.5	±0.1nH	1000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N5C0Z	1.5	±0.2nH	1000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N5D0Z	1.5	±0.5nH	1000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N6C0Z	1.6	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N6D0Z	1.6	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N7C0Z	1.7	±0.2nH	640mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N7D0Z	1.7	±0.5nH	640mA	0.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N8C0Z	1.8	±0.2nH	460mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N8D0Z	1.8	±0.5nH	460mA	0.16	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4B0Z	2.4	±0.1nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4C0Z	2.4	±0.2nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4D0Z	2.4	±0.5nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5B0Z	2.5	±0.1nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5C0Z	2.5	±0.2nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5D0Z	2.5	±0.5nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6B0Z	2.6	±0.1nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6C0Z	2.6	±0.2nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6D0Z	2.6	±0.5nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7B0Z	2.7	±0.1nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7C0Z	2.7	±0.2nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7D0Z	2.7	±0.5nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8B0Z	2.8	±0.1nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8C0Z	2.8	±0.2nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8D0Z	2.8	±0.5nH	850mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9B0Z	2.9	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9C0Z	2.9	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9D0Z	2.9	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0B0Z	3	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0C0Z	3	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0D0Z	3	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N1B0Z	3.1	±0.1nH	570mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N1C0Z	3.1	±0.2nH	570mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N1D0Z	3.1	±0.5nH	570mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N2B0Z	3.2	±0.1nH	500mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N2C0Z	3.2	±0.2nH	500mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N2D0Z	3.2	±0.5nH	500mA	0.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N9B0Z	3.9	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N9C0Z	3.9	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N9D0Z	3.9	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N1B0Z	4.1	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N1C0Z	4.1	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N1D0Z	4.1	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N3B0Z	4.3	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N3C0Z	4.3	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N3D0Z	4.3	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N4B0Z	4.4	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N4C0Z	4.4	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N4D0Z	4.4	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N5B0Z	4.5	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N5C0Z	4.5	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N5D0Z	4.5	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N6B0Z	4.6	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N6C0Z	4.6	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N6D0Z	4.6	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N7B0Z	4.7	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N7C0Z	4.7	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N7D0Z	4.7	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N8B0Z	4.8	±0.1nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N8C0Z	4.8	±0.2nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N8D0Z	4.8	±0.5nH	750mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N9B0Z	4.9	±0.1nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N9C0Z	4.9	±0.2nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N9D0Z	4.9	±0.5nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N0B0Z	5	±0.1nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N0C0Z	5	±0.2nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N0D0Z	5	±0.5nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N1B0Z	5.1	±0.1nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N1C0Z	5.1	±0.2nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N1D0Z	5.1	±0.5nH	600mA	0.12	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N8B0Z	5.8	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N8C0Z	5.8	±0.2nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N8D0Z	5.8	±0.5nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N2B0Z	6.2	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N2C0Z	6.2	±0.2nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N2D0Z	6.2	±0.5nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N3B0Z	6.3	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N3C0Z	6.3	±0.2nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N3D0Z	6.3	±0.5nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N4B0Z	6.4	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N4C0Z	6.4	±0.2nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N4D0Z	6.4	±0.5nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N5B0Z	6.5	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N5C0Z	6.5	±0.2nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N5D0Z	6.5	±0.5nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N6B0Z	6.6	±0.1nH	700mA	0.09	1005	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN27NGOZ	27	±2%	280mA	0.52	1005	Infotainment	50 MHz - 20 GHz
LQW15AN27NH0Z	27	±3%	280mA	0.52	1005	Infotainment	50 MHz - 20 GHz
LQW15AN27NJ0Z	27	±5%	280mA	0.52	1005	Infotainment	50 MHz - 20 GHz
LQW15AN30NGOZ	30	±2%	270mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQW15AN30NH0Z	30	±3%	270mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQW15AN30NJ0Z	30	±5%	270mA	0.58	1005	Infotainment	50 MHz - 20 GHz
LQW15AN33NGOZ	33	±2%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN33NH0Z	33	±3%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN33NJ0Z	33	±5%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN36NGOZ	36	±2%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN36NH0Z	36	±3%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN36NJ0Z	36	±5%	260mA	0.63	1005	Infotainment	50 MHz - 20 GHz
LQW15AN39NGOZ	39	±2%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN39NH0Z	39	±3%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN39NJ0Z	39	±5%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN40NGOZ	40	±2%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN40NH0Z	40	±3%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN40NJ0Z	40	±5%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN43NGOZ	43	±2%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN43NH0Z	43	±3%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN43NJ0Z	43	±5%	250mA	0.7	1005	Infotainment	50 MHz - 20 GHz
LQW15AN47NGOZ	47	±2%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN47NH0Z	47	±3%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN47NJ0Z	47	±5%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN51NGOZ	51	±2%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN51NH0Z	51	±3%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN51NJ0Z	51	±5%	210mA	1.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN56NGOZ	56	±2%	200mA	1.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN56NH0Z	56	±3%	200mA	1.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN56NJ0Z	56	±5%	200mA	1.17	1005	Infotainment	50 MHz - 20 GHz
LQW15AN62NGOZ	62	±2%	145mA	1.82	1005	Infotainment	50 MHz - 20 GHz
LQW15AN62NH0Z	62	±3%	145mA	1.82	1005	Infotainment	50 MHz - 20 GHz
LQW15AN62NJ0Z	62	±5%	145mA	1.82	1005	Infotainment	50 MHz - 20 GHz
LQW15AN68NGOZ	68	±2%	140mA	1.96	1005	Infotainment	50 MHz - 20 GHz
LQW15AN68NH0Z	68	±3%	140mA	1.96	1005	Infotainment	50 MHz - 20 GHz
LQW15AN72NGOZ	72	±2%	135mA	2.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN72NH0Z	72	±3%	135mA	2.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN75NGOZ	75	±2%	135mA	2.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN75NJ0Z	75	±5%	135mA	2.1	1005	Infotainment	50 MHz - 20 GHz
LQW15AN82NGOZ	82	±2%	130mA	2.24	1005	Infotainment	50 MHz - 20 GHz
LQW15AN82NH0Z	82	±3%	130mA	2.24	1005	Infotainment	50 MHz - 20 GHz
LQW15AN82NJ0Z	82	±5%	130mA	2.24	1005	Infotainment	50 MHz - 20 GHz
LQW15AN91NGOZ	91	±2%	125mA	2.38	1005	Infotainment	50 MHz - 20 GHz
LQW15AN91NH0Z	91	±3%	125mA	2.38	1005	Infotainment	50 MHz - 20 GHz
LQW15AN91NJ0Z	91	±5%	125mA	2.38	1005	Infotainment	50 MHz - 20 GHz
LQW15ANR10J0Z	100	±5%	120mA	2.52	1005	Infotainment	50 MHz - 20 GHz
LQW15ANR12J0Z	120	±5%	110mA	2.66	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N3C10	1.3	±0.2nH	1200mA	0.017	1005	General	50 MHz - 20 GHz
LQW15AN1N3D10	1.3	±0.5nH	1200mA	0.017	1005	General	50 MHz - 20 GHz
LQW15AN1N4C10	1.4	±0.2nH	1100mA	0.019	1005	General	50 MHz - 20 GHz
LQW15AN1N4D10	1.4	±0.5nH	1100mA	0.019	1005	General	50 MHz - 20 GHz
LQW15AN2N2C10	2.2	±0.2nH	1000mA	0.027	1005	General	50 MHz - 20 GHz
LQW15AN2N2D10	2.2	±0.5nH	1000mA	0.027	1005	General	50 MHz - 20 GHz
LQW15AN2N3C10	2.3	±0.2nH	1000mA	0.027	1005	General	50 MHz - 20 GHz
LQW15AN2N3D10	2.3	±0.5nH	1000mA	0.027	1005	General	50 MHz - 20 GHz
LQW15AN2N4D10	2.4	±0.5nH	1000mA	0.027	1005	General	50 MHz - 20 GHz
LQW15AN3N3C10	3.3	±0.2nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N3D10	3.3	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N4C10	3.4	±0.2nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N4D10	3.4	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N5C10	3.5	±0.2nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N5D10	3.5	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N6C10	3.6	±0.2nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N6D10	3.6	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N8C10	3.8	±0.2nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N8D10	3.8	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN3N9D10	3.9	±0.5nH	900mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN4N0C10	4	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN4N0D10	4	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN4N2C10	4.2	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN4N2D10	4.2	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN4N7D10	4.7	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N1C10	5.1	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N1D10	5.1	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N2C10	5.2	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N2D10	5.2	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N3C10	5.3	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N3D10	5.3	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N4C10	5.4	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N4D10	5.4	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N5C10	5.5	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N5D10	5.5	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N6C10	5.6	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N6D10	5.6	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N7C10	5.7	±0.2nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N7D10	5.7	±0.5nH	800mA	0.051	1005	General	50 MHz - 20 GHz
LQW15AN5N9C10	5.9	±0.2nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN5N9D10	5.9	±0.5nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N0C10	6	±0.2nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N0D10	6	±0.5nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1C10	6.1	±0.2nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1D10	6.1	±0.5nH	760mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN7N4C10	7.4	±0.2nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N4D10	7.4	±0.5nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N6C10	7.6	±0.2nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N6D10	7.6	±0.5nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N7C10	7.7	±0.2nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N7D10	7.7	±0.5nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N8C10	7.8	±0.2nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N8D10	7.8	±0.5nH	750mA	0.058	1005	General	50 MHz - 20 GHz
LQW15AN7N9C10	7.9	±0.2nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN7N9D10	7.9	±0.5nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N0C10	8	±0.2nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N0D10	8	±0.5nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N1C10	8.1	±0.2nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N1D10	8.1	±0.5nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N3C10	8.3	±0.2nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N3D10	8.3	±0.5nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN8N4C10	8.4	±0.2nH	640mA	0.079	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN8N4D10	8.4	±0.5nH	640mA	0.079	1005	General	50 MHz - 20 GHz
LQW15AN1N3C1Z	1.3	±0.2nH	1200mA	0.017	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N3D1Z	1.3	±0.5nH	1200mA	0.017	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N4C1Z	1.4	±0.2nH	1100mA	0.019	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N4D1Z	1.4	±0.5nH	1100mA	0.019	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2C1Z	2.2	±0.2nH	1000mA	0.027	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2D1Z	2.2	±0.5nH	1000mA	0.027	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3C1Z	2.3	±0.2nH	1000mA	0.027	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3D1Z	2.3	±0.5nH	1000mA	0.027	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4D1Z	2.4	±0.5nH	1000mA	0.027	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N3D1Z	3.3	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4C1Z	3.4	±0.2nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4D1Z	3.4	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5C1Z	3.5	±0.2nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5D1Z	3.5	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6C1Z	3.6	±0.2nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6D1Z	3.6	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8C1Z	3.8	±0.2nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8D1Z	3.8	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N9D1Z	3.9	±0.5nH	900mA	0.04	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N0C1Z	4	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N0D1Z	4	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N2C1Z	4.2	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N2D1Z	4.2	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN4N7D1Z	4.7	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N1C1Z	5.1	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N1D1Z	5.1	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N2C1Z	5.2	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N2D1Z	5.2	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N3C1Z	5.3	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N3D1Z	5.3	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N4C1Z	5.4	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N4D1Z	5.4	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N5C1Z	5.5	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N5D1Z	5.5	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N6C1Z	5.6	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N6D1Z	5.6	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N7C1Z	5.7	±0.2nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N7D1Z	5.7	±0.5nH	800mA	0.051	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N9C1Z	5.9	±0.2nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN5N9D1Z	5.9	±0.5nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N0C1Z	6	±0.2nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N0D1Z	6	±0.5nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N1C1Z	6.1	±0.2nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N1D1Z	6.1	±0.5nH	760mA	0.056	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N4C1Z	7.4	±0.2nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N4D1Z	7.4	±0.5nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N6C1Z	7.6	±0.2nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N6D1Z	7.6	±0.5nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N7C1Z	7.7	±0.2nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N7D1Z	7.7	±0.5nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N8C1Z	7.8	±0.2nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N8D1Z	7.8	±0.5nH	750mA	0.058	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N9C1Z	7.9	±0.2nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N9D1Z	7.9	±0.5nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N0C1Z	8	±0.2nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N0D1Z	8	±0.5nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N1C1Z	8.1	±0.2nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N1D1Z	8.1	±0.5nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N3C1Z	8.3	±0.2nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N3D1Z	8.3	±0.5nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N4C1Z	8.4	±0.2nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N4D1Z	8.4	±0.5nH	640mA	0.079	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N3C80	1.3	±0.2nH	3150mA	0.012	1005	General	50 MHz - 20 GHz
LQW15AN1N3D80	1.3	±0.5nH	3150mA	0.012	1005	General	50 MHz - 20 GHz
LQW15AN1N5C80	1.5	±0.2nH	2100mA	0.028	1005	General	50 MHz - 20 GHz
LQW15AN1N5D80	1.5	±0.5nH	2100mA	0.028	1005	General	50 MHz - 20 GHz
LQW15AN1N6C80	1.6	±0.2nH	1450mA	0.045	1005	General	50 MHz - 20 GHz
LQW15AN1N6D80	1.6	±0.5nH	1450mA	0.045	1005	General	50 MHz - 20 GHz
LQW15AN1N7C80	1.7	±0.2nH	1150mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN1N7D80	1.7	±0.5nH	1150mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN2N2B80	2.2	±0.1nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N2C80	2.2	±0.2nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N2D80	2.2	±0.5nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N2G80	2.2	±2%	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N3B80	2.3	±0.1nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N3C80	2.3	±0.2nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N3D80	2.3	±0.5nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N3G80	2.3	±2%	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N4B80	2.4	±0.1nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N4C80	2.4	±0.2nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N4D80	2.4	±0.5nH	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N4G80	2.4	±2%	2530mA	0.022	1005	General	50 MHz - 20 GHz
LQW15AN2N5B80	2.5	±0.1nH	2100mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN2N5C80	2.5	±0.2nH	2100mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN2N5D80	2.5	±0.5nH	2100mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN2N5G80	2.5	±2%	2100mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN2N6B80	2.6	±0.1nH	1950mA	0.035	1005	General	50 MHz - 20 GHz
LQW15AN2N6C80	2.6	±0.2nH	1950mA	0.035	1005	General	50 MHz - 20 GHz
LQW15AN2N6D80	2.6	±0.5nH	1950mA	0.035	1005	General	50 MHz - 20 GHz
LQW15AN2N6G80	2.6	±2%	1950mA	0.035	1005	General	50 MHz - 20 GHz
LQW15AN2N7B80	2.7	±0.1nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N7C80	2.7	±0.2nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N7D80	2.7	±0.5nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N7G80	2.7	±2%	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N8B80	2.8	±0.1nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N8C80	2.8	±0.2nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N8D80	2.8	±0.5nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N8G80	2.8	±2%	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N9B80	2.9	±0.1nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N9C80	2.9	±0.2nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N9D80	2.9	±0.5nH	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN2N9G80	2.9	±2%	1500mA	0.047	1005	General	50 MHz - 20 GHz
LQW15AN3N0B80	3	±0.1nH	1350mA	0.063	1005	General	50 MHz - 20 GHz
LQW15AN3N0C80	3	±0.2nH	1350mA	0.063	1005	General	50 MHz - 20 GHz
LQW15AN3N0D80	3	±0.5nH	1350mA	0.063	1005	General	50 MHz - 20 GHz
LQW15AN3N0G80	3	±2%	1350mA	0.063	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN3N3B80	3.3	±0.1nH	2000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N3C80	3.3	±0.2nH	2000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N3D80	3.3	±0.5nH	2000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N3G80	3.3	±2%	2000mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N4B80	3.4	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N4C80	3.4	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N4D80	3.4	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N4G80	3.4	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N5B80	3.5	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N5C80	3.5	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N5D80	3.5	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N5G80	3.5	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N6B80	3.6	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N6C80	3.6	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N6D80	3.6	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N6G80	3.6	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N7B80	3.7	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N7C80	3.7	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N7D80	3.7	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N7G80	3.7	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N8B80	3.8	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N8C80	3.8	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N8D80	3.8	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N8G80	3.8	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N9B80	3.9	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N9C80	3.9	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N9D80	3.9	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN3N9G80	3.9	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN4N0B80	4	±0.1nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN4N0C80	4	±0.2nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN4N0D80	4	±0.5nH	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN4N0G80	4	±2%	1950mA	0.03	1005	General	50 MHz - 20 GHz
LQW15AN4N1B80	4.1	±0.1nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N1C80	4.1	±0.2nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N1D80	4.1	±0.5nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N1G80	4.1	±2%	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N2B80	4.2	±0.1nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N2C80	4.2	±0.2nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N2D80	4.2	±0.5nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N2G80	4.2	±2%	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N3B80	4.3	±0.1nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N3C80	4.3	±0.2nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N3D80	4.3	±0.5nH	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N3G80	4.3	±2%	1800mA	0.044	1005	General	50 MHz - 20 GHz
LQW15AN4N4B80	4.4	±0.1nH	1600mA	0.052	1005	General	50 MHz - 20 GHz
LQW15AN4N4C80	4.4	±0.2nH	1600mA	0.052	1005	General	50 MHz - 20 GHz
LQW15AN4N4D80	4.4	±0.5nH	1600mA	0.052	1005	General	50 MHz - 20 GHz
LQW15AN4N4G80	4.4	±2%	1600mA	0.052	1005	General	50 MHz - 20 GHz
LQW15AN4N5B80	4.5	±0.1nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N5C80	4.5	±0.2nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N5D80	4.5	±0.5nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N5G80	4.5	±2%	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N6B80	4.6	±0.1nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N6C80	4.6	±0.2nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N6D80	4.6	±0.5nH	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N6G80	4.6	±2%	1450mA	0.06	1005	General	50 MHz - 20 GHz
LQW15AN4N7B80	4.7	±0.1nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N7C80	4.7	±0.2nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N7D80	4.7	±0.5nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N7G80	4.7	±2%	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N8B80	4.8	±0.1nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N8C80	4.8	±0.2nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N8D80	4.8	±0.5nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N8G80	4.8	±2%	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N9B80	4.9	±0.1nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N9C80	4.9	±0.2nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N9D80	4.9	±0.5nH	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN4N9G80	4.9	±2%	1200mA	0.071	1005	General	50 MHz - 20 GHz
LQW15AN5N0B80	5	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N0C80	5	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N0D80	5	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N0G80	5	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N1B80	5.1	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N1C80	5.1	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N1D80	5.1	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N1G80	5.1	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N2B80	5.2	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N2C80	5.2	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N2D80	5.2	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N2G80	5.2	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N3B80	5.3	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N3C80	5.3	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N3D80	5.3	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N3G80	5.3	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N4B80	5.4	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N4C80	5.4	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N4D80	5.4	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N4G80	5.4	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N5B80	5.5	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N5C80	5.5	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N5D80	5.5	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N5G80	5.5	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N6B80	5.6	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N6C80	5.6	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N6D80	5.6	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N6G80	5.6	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N7B80	5.7	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N7C80	5.7	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N7D80	5.7	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N7G80	5.7	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N8B80	5.8	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N8C80	5.8	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N8D80	5.8	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N8G80	5.8	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N9B80	5.9	±0.1nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N9C80	5.9	±0.2nH	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN5N9D80	5.9	±0.5nH	1770mA	0.04	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN5N9G80	5.9	±2%	1770mA	0.04	1005	General	50 MHz - 20 GHz
LQW15AN6N0B80	6	±0.1nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N0C80	6	±0.2nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N0D80	6	±0.5nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N0G80	6	±2%	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1B80	6.1	±0.1nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1C80	6.1	±0.2nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1D80	6.1	±0.5nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N1G80	6.1	±2%	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N2B80	6.2	±0.1nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N2C80	6.2	±0.2nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N2D80	6.2	±0.5nH	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N2G80	6.2	±2%	1600mA	0.056	1005	General	50 MHz - 20 GHz
LQW15AN6N3G80	6.3	±2%	1600mA	0.057	1005	General	50 MHz - 20 GHz
LQW15AN6N3J80	6.3	±5%	1600mA	0.057	1005	General	50 MHz - 20 GHz
LQW15AN6N4G80	6.4	±2%	1380mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN6N4J80	6.4	±5%	1380mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN6N5G80	6.5	±2%	1380mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN6N5J80	6.5	±5%	1380mA	0.065	1005	General	50 MHz - 20 GHz
LQW15AN6N6G80	6.6	±2%	1280mA	0.078	1005	General	50 MHz - 20 GHz
LQW15AN6N6J80	6.6	±5%	1280mA	0.078	1005	General	50 MHz - 20 GHz
LQW15AN6N7G80	6.7	±2%	1280mA	0.078	1005	General	50 MHz - 20 GHz
LQW15AN6N7J80	6.7	±5%	1280mA	0.078	1005	General	50 MHz - 20 GHz
LQW15AN6N8G80	6.8	±2%	1450mA	0.068	1005	General	50 MHz - 20 GHz
LQW15AN6N8J80	6.8	±5%	1450mA	0.068	1005	General	50 MHz - 20 GHz
LQW15AN6N9G80	6.9	±2%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN6N9J80	6.9	±5%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN7N0G80	7	±2%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN7N0J80	7	±5%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN7N1G80	7.1	±2%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN7N1J80	7.1	±5%	1420mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN7N2G80	7.2	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N2J80	7.2	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N3G80	7.3	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N3J80	7.3	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N4G80	7.4	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N4J80	7.4	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N5G80	7.5	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N5J80	7.5	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N6G80	7.6	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N6J80	7.6	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N7G80	7.7	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N7J80	7.7	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N8G80	7.8	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N8J80	7.8	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N9G80	7.9	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN7N9J80	7.9	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN8N0G80	8	±2%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN8N0J80	8	±5%	1700mA	0.05	1005	General	50 MHz - 20 GHz
LQW15AN8N1G80	8.1	±2%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N1J80	8.1	±5%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N2G80	8.2	±2%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N2J80	8.2	±5%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N3G80	8.3	±2%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N3J80	8.3	±5%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N4G80	8.4	±2%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N4J80	8.4	±5%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N5G80	8.5	±2%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N5J80	8.5	±5%	1500mA	0.069	1005	General	50 MHz - 20 GHz
LQW15AN8N6G80	8.6	±2%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N6J80	8.6	±5%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N7G80	8.7	±2%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N7J80	8.7	±5%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N8G80	8.8	±2%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N8J80	8.8	±5%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N9G80	8.9	±2%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN8N9J80	8.9	±5%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN9N0G80	9	±2%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN9N0J80	9	±5%	1420mA	0.07	1005	General	50 MHz - 20 GHz
LQW15AN9N1G80	9.1	±2%	1400mA	0.08	1005	General	50 MHz - 20 GHz
LQW15AN9N1J80	9.1	±5%	1400mA	0.08	1005	General	50 MHz - 20 GHz
LQW15AN9N2G80	9.2	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N2J80	9.2	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N3G80	9.3	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N3J80	9.3	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N4G80	9.4	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N4J80	9.4	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N5G80	9.5	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N5J80	9.5	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N6G80	9.6	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N6J80	9.6	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N7G80	9.7	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N7J80	9.7	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N8G80	9.8	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N8J80	9.8	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N9G80	9.9	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN9N9J80	9.9	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN10NG80	10	±2%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN10NJ80	10	±5%	1400mA	0.081	1005	General	50 MHz - 20 GHz
LQW15AN11NG80	11	±2%	1400mA	0.083	1005	General	50 MHz - 20 GHz
LQW15AN11NJ80	11	±5%	1400mA	0.083	1005	General	50 MHz - 20 GHz
LQW15AN12NG80	12	±2%	1240mA	0.093	1005	General	50 MHz - 20 GHz
LQW15AN12NJ80	12	±5%	1240mA	0.093	1005	General	50 MHz - 20 GHz
LQW15AN13NG80	13	±2%	1240mA	0.093	1005	General	50 MHz - 20 GHz
LQW15AN13NJ80	13	±5%	1240mA	0.093	1005	General	50 MHz - 20 GHz
LQW15AN14NG80	14	±2%	1150mA	0.111	1005	General	50 MHz - 20 GHz
LQW15AN14NJ80	14	±5%	1150mA	0.111	1005	General	50 MHz - 20 GHz
LQW15AN15NG80	15	±2%	1150mA	0.114	1005	General	50 MHz - 20 GHz
LQW15AN15NJ80	15	±5%	1150mA	0.114	1005	General	50 MHz - 20 GHz
LQW15AN16NG80	16	±2%	1000mA	0.126	1005	General	50 MHz - 20 GHz
LQW15AN16NJ80	16	±5%	1000mA	0.126	1005	General	50 MHz - 20 GHz
LQW15AN17NG80	17	±2%	1000mA	0.126	1005	General	50 MHz - 20 GHz
LQW15AN17NJ80	17	±5%	1000mA	0.126	1005	General	50 MHz - 20 GHz
LQW15AN18NG80	18	±2%	1050mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN18NJ80	18	±5%	1050mA	0.13	1005	General	50 MHz - 20 GHz
LQW15AN19NG80	19	±2%	920mA	0.156	1005	General	50 MHz - 20 GHz
LQW15AN19NJ80	19	±5%	920mA	0.156	1005	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN20NG80	20	±2%	800mA	0.186	1005	General	50 MHz - 20 GHz
LQW15AN20NJ80	20	±5%	800mA	0.186	1005	General	50 MHz - 20 GHz
LQW15AN21NG80	21	±2%	780mA	0.202	1005	General	50 MHz - 20 GHz
LQW15AN21NJ80	21	±5%	780mA	0.202	1005	General	50 MHz - 20 GHz
LQW15AN22NG80	22	±2%	780mA	0.202	1005	General	50 MHz - 20 GHz
LQW15AN22NJ80	22	±5%	780mA	0.202	1005	General	50 MHz - 20 GHz
LQW15AN23NG80	23	±2%	760mA	0.201	1005	General	50 MHz - 20 GHz
LQW15AN23NJ80	23	±5%	760mA	0.201	1005	General	50 MHz - 20 GHz
LQW15AN24NG80	24	±2%	770mA	0.212	1005	General	50 MHz - 20 GHz
LQW15AN24NJ80	24	±5%	770mA	0.212	1005	General	50 MHz - 20 GHz
LQW15AN25NG80	25	±2%	750mA	0.221	1005	General	50 MHz - 20 GHz
LQW15AN25NJ80	25	±5%	750mA	0.221	1005	General	50 MHz - 20 GHz
LQW15AN26NG80	26	±2%	720mA	0.282	1005	General	50 MHz - 20 GHz
LQW15AN26NJ80	26	±5%	720mA	0.282	1005	General	50 MHz - 20 GHz
LQW15AN27NG80	27	±2%	680mA	0.288	1005	General	50 MHz - 20 GHz
LQW15AN27NJ80	27	±5%	680mA	0.288	1005	General	50 MHz - 20 GHz
LQW15AN30NG80	30	±2%	660mA	0.309	1005	General	50 MHz - 20 GHz
LQW15AN30NJ80	30	±5%	660mA	0.309	1005	General	50 MHz - 20 GHz
LQW15AN33NG80	33	±2%	620mA	0.336	1005	General	50 MHz - 20 GHz
LQW15AN33NJ80	33	±5%	620mA	0.336	1005	General	50 MHz - 20 GHz
LQW15AN36NG80	36	±2%	540mA	0.431	1005	General	50 MHz - 20 GHz
LQW15AN36NJ80	36	±5%	540mA	0.431	1005	General	50 MHz - 20 GHz
LQW15AN39NG80	39	±2%	530mA	0.456	1005	General	50 MHz - 20 GHz
LQW15AN39NJ80	39	±5%	530mA	0.456	1005	General	50 MHz - 20 GHz
LQW15AN43NG80	43	±2%	515mA	0.516	1005	General	50 MHz - 20 GHz
LQW15AN43NJ80	43	±5%	515mA	0.516	1005	General	50 MHz - 20 GHz
LQW15AN47NG80	47	±2%	440mA	0.648	1005	General	50 MHz - 20 GHz
LQW15AN47NJ80	47	±5%	440mA	0.648	1005	General	50 MHz - 20 GHz
LQW15AN51NG80	51	±2%	415mA	0.696	1005	General	50 MHz - 20 GHz
LQW15AN51NJ80	51	±5%	415mA	0.696	1005	General	50 MHz - 20 GHz
LQW15AN53NG80	53	±2%	415mA	0.696	1005	General	50 MHz - 20 GHz
LQW15AN53NJ80	53	±5%	415mA	0.696	1005	General	50 MHz - 20 GHz
LQW15AN56NG80	56	±2%	340mA	0.996	1005	General	50 MHz - 20 GHz
LQW15AN56NJ80	56	±5%	340mA	0.996	1005	General	50 MHz - 20 GHz
LQW15AN68NG80	68	±2%	320mA	1.128	1005	General	50 MHz - 20 GHz
LQW15AN68NJ80	68	±5%	320mA	1.128	1005	General	50 MHz - 20 GHz
LQW15AN75NG80	75	±2%	320mA	1.224	1005	General	50 MHz - 20 GHz
LQW15AN75NJ80	75	±5%	320mA	1.224	1005	General	50 MHz - 20 GHz
LQW15AN1N3C8Z	1.3	±0.2nH	3150mA	0.012	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N3D8Z	1.3	±0.5nH	3150mA	0.012	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N5C8Z	1.5	±0.2nH	2100mA	0.028	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N5D8Z	1.5	±0.5nH	2100mA	0.028	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N6C8Z	1.6	±0.2nH	1450mA	0.045	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N6D8Z	1.6	±0.5nH	1450mA	0.045	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N7C8Z	1.7	±0.2nH	1150mA	0.065	1005	Infotainment	50 MHz - 20 GHz
LQW15AN1N7D8Z	1.7	±0.5nH	1150mA	0.065	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2B8Z	2.2	±0.1nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2C8Z	2.2	±0.2nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2D8Z	2.2	±0.5nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N2G8Z	2.2	±2%	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3B8Z	2.3	±0.1nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3C8Z	2.3	±0.2nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3D8Z	2.3	±0.5nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N3G8Z	2.3	±2%	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4B8Z	2.4	±0.1nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4C8Z	2.4	±0.2nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4D8Z	2.4	±0.5nH	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N4G8Z	2.4	±2%	2530mA	0.022	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5B8Z	2.5	±0.1nH	2100mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5C8Z	2.5	±0.2nH	2100mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5D8Z	2.5	±0.5nH	2100mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N5G8Z	2.5	±2%	2100mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6B8Z	2.6	±0.1nH	1950mA	0.035	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6C8Z	2.6	±0.2nH	1950mA	0.035	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6D8Z	2.6	±0.5nH	1950mA	0.035	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N6G8Z	2.6	±2%	1950mA	0.035	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7B8Z	2.7	±0.1nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7C8Z	2.7	±0.2nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7D8Z	2.7	±0.5nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N7G8Z	2.7	±2%	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8B8Z	2.8	±0.1nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8C8Z	2.8	±0.2nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8D8Z	2.8	±0.5nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N8G8Z	2.8	±2%	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9B8Z	2.9	±0.1nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9C8Z	2.9	±0.2nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9D8Z	2.9	±0.5nH	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN2N9G8Z	2.9	±2%	1500mA	0.047	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0B8Z	3	±0.1nH	1350mA	0.063	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0C8Z	3	±0.2nH	1350mA	0.063	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0D8Z	3	±0.5nH	1350mA	0.063	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N0G8Z	3	±2%	1350mA	0.063	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N3B8Z	3.3	±0.1nH	2000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N3C8Z	3.3	±0.2nH	2000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N3D8Z	3.3	±0.5nH	2000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N3G8Z	3.3	±2%	2000mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4B8Z	3.4	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4C8Z	3.4	±0.2nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4D8Z	3.4	±0.5nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N4G8Z	3.4	±2%	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5B8Z	3.5	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5C8Z	3.5	±0.2nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5D8Z	3.5	±0.5nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N5G8Z	3.5	±2%	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6B8Z	3.6	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6C8Z	3.6	±0.2nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6D8Z	3.6	±0.5nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N6G8Z	3.6	±2%	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N7B8Z	3.7	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N7C8Z	3.7	±0.2nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N7D8Z	3.7	±0.5nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N7G8Z	3.7	±2%	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8B8Z	3.8	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8C8Z	3.8	±0.2nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8D8Z	3.8	±0.5nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N8G8Z	3.8	±2%	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz
LQW15AN3N9B8Z	3.9	±0.1nH	1950mA	0.03	1005	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN6N9G8Z	6.9	±2%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN6N9J8Z	6.9	±5%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N0G8Z	7	±2%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N0J8Z	7	±5%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N1G8Z	7.1	±2%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N1J8Z	7.1	±5%	1420mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N2G8Z	7.2	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N2J8Z	7.2	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N3G8Z	7.3	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N3J8Z	7.3	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N4G8Z	7.4	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N4J8Z	7.4	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N5G8Z	7.5	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N5J8Z	7.5	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N6G8Z	7.6	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N6J8Z	7.6	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N7G8Z	7.7	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N7J8Z	7.7	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N8G8Z	7.8	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N8J8Z	7.8	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N9G8Z	7.9	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN7N9J8Z	7.9	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N0G8Z	8	±2%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N0J8Z	8	±5%	1700mA	0.05	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N1G8Z	8.1	±2%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N1J8Z	8.1	±5%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N2G8Z	8.2	±2%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N2J8Z	8.2	±5%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N3G8Z	8.3	±2%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N3J8Z	8.3	±5%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N4G8Z	8.4	±2%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N4J8Z	8.4	±5%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N5G8Z	8.5	±2%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N5J8Z	8.5	±5%	1500mA	0.069	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N6G8Z	8.6	±2%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N6J8Z	8.6	±5%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N7G8Z	8.7	±2%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N7J8Z	8.7	±5%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N8G8Z	8.8	±2%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N8J8Z	8.8	±5%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N9G8Z	8.9	±2%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN8N9J8Z	8.9	±5%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N0G8Z	9	±2%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N0J8Z	9	±5%	1420mA	0.07	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N1G8Z	9.1	±2%	1400mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N1J8Z	9.1	±5%	1400mA	0.08	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N2G8Z	9.2	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N2J8Z	9.2	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N3G8Z	9.3	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N3J8Z	9.3	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N4G8Z	9.4	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N4J8Z	9.4	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N5G8Z	9.5	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N5J8Z	9.5	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N6G8Z	9.6	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N6J8Z	9.6	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N7G8Z	9.7	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N7J8Z	9.7	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N8G8Z	9.8	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N8J8Z	9.8	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N9G8Z	9.9	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN9N9J8Z	9.9	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN10NG8Z	10	±2%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN10NJ8Z	10	±5%	1400mA	0.081	1005	Infotainment	50 MHz - 20 GHz
LQW15AN11NG8Z	11	±2%	1400mA	0.083	1005	Infotainment	50 MHz - 20 GHz
LQW15AN11NJ8Z	11	±5%	1400mA	0.083	1005	Infotainment	50 MHz - 20 GHz
LQW15AN12NG8Z	12	±2%	1240mA	0.093	1005	Infotainment	50 MHz - 20 GHz
LQW15AN12NJ8Z	12	±5%	1240mA	0.093	1005	Infotainment	50 MHz - 20 GHz
LQW15AN13NG8Z	13	±2%	1240mA	0.093	1005	Infotainment	50 MHz - 20 GHz
LQW15AN13NJ8Z	13	±5%	1240mA	0.093	1005	Infotainment	50 MHz - 20 GHz
LQW15AN14NG8Z	14	±2%	1150mA	0.111	1005	Infotainment	50 MHz - 20 GHz
LQW15AN14NJ8Z	14	±5%	1150mA	0.111	1005	Infotainment	50 MHz - 20 GHz
LQW15AN15NG8Z	15	±2%	1150mA	0.114	1005	Infotainment	50 MHz - 20 GHz
LQW15AN15NJ8Z	15	±5%	1150mA	0.114	1005	Infotainment	50 MHz - 20 GHz
LQW15AN16NG8Z	16	±2%	1000mA	0.126	1005	Infotainment	50 MHz - 20 GHz
LQW15AN16NJ8Z	16	±5%	1000mA	0.126	1005	Infotainment	50 MHz - 20 GHz
LQW15AN17NG8Z	17	±2%	1000mA	0.126	1005	Infotainment	50 MHz - 20 GHz
LQW15AN17NJ8Z	17	±5%	1000mA	0.126	1005	Infotainment	50 MHz - 20 GHz
LQW15AN18NG8Z	18	±2%	1050mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQW15AN18NJ8Z	18	±5%	1050mA	0.13	1005	Infotainment	50 MHz - 20 GHz
LQW15AN19NG8Z	19	±2%	920mA	0.156	1005	Infotainment	50 MHz - 20 GHz
LQW15AN19NJ8Z	19	±5%	920mA	0.156	1005	Infotainment	50 MHz - 20 GHz
LQW15AN20NG8Z	20	±2%	800mA	0.186	1005	Infotainment	50 MHz - 20 GHz
LQW15AN20NJ8Z	20	±5%	800mA	0.186	1005	Infotainment	50 MHz - 20 GHz
LQW15AN21NG8Z	21	±2%	780mA	0.202	1005	Infotainment	50 MHz - 20 GHz
LQW15AN21NJ8Z	21	±5%	780mA	0.202	1005	Infotainment	50 MHz - 20 GHz
LQW15AN22NG8Z	22	±2%	780mA	0.202	1005	Infotainment	50 MHz - 20 GHz
LQW15AN22NJ8Z	22	±5%	780mA	0.202	1005	Infotainment	50 MHz - 20 GHz
LQW15AN23NG8Z	23	±2%	760mA	0.201	1005	Infotainment	50 MHz - 20 GHz
LQW15AN23NJ8Z	23	±5%	760mA	0.201	1005	Infotainment	50 MHz - 20 GHz
LQW15AN24NG8Z	24	±2%	770mA	0.212	1005	Infotainment	50 MHz - 20 GHz
LQW15AN24NJ8Z	24	±5%	770mA	0.212	1005	Infotainment	50 MHz - 20 GHz
LQW15AN25NG8Z	25	±2%	750mA	0.221	1005	Infotainment	50 MHz - 20 GHz
LQW15AN25NJ8Z	25	±5%	750mA	0.221	1005	Infotainment	50 MHz - 20 GHz
LQW15AN26NG8Z	26	±2%	720mA	0.282	1005	Infotainment	50 MHz - 20 GHz
LQW15AN26NJ8Z	26	±5%	720mA	0.282	1005	Infotainment	50 MHz - 20 GHz
LQW15AN27NG8Z	27	±2%	680mA	0.288	1005	Infotainment	50 MHz - 20 GHz
LQW15AN27NJ8Z	27	±5%	680mA	0.288	1005	Infotainment	50 MHz - 20 GHz
LQW15AN30NG8Z	30	±2%	660mA	0.309	1005	Infotainment	50 MHz - 20 GHz
LQW15AN30NJ8Z	30	±5%	660mA	0.309	1005	Infotainment	50 MHz - 20 GHz
LQW15AN33NG8Z	33	±2%	620mA	0.336	1005	Infotainment	50 MHz - 20 GHz
LQW15AN33NJ8Z	33	±5%	620mA	0.336	1005	Infotainment	50 MHz - 20 GHz
LQW15AN36NG8Z	36	±2%	540mA	0.431	1005	Infotainment	50 MHz - 20 GHz
LQW15AN36NJ8Z	36	±5%	540mA	0.431	1005	Infotainment	50 MHz - 20 GHz
LQW15AN39NG8Z	39	±2%	530mA	0.456	1005	Infotainment	50 MHz - 20 GHz
LQW15AN39NJ8Z	39	±5%	530mA	0.456	1005	Infotainment	50 MHz - 20 GHz
LQW15AN43NG8Z	43	±2%	515mA	0.516	1005	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15AN43NJ8Z	43	±5%	515mA	0.516	1005	Infotainment	50 MHz - 20 GHz
LQW15AN47NGBZ	47	±2%	440mA	0.648	1005	Infotainment	50 MHz - 20 GHz
LQW15AN47NJ8Z	47	±5%	440mA	0.648	1005	Infotainment	50 MHz - 20 GHz
LQW15AN51NGBZ	51	±2%	415mA	0.696	1005	Infotainment	50 MHz - 20 GHz
LQW15AN51NJ8Z	51	±5%	415mA	0.696	1005	Infotainment	50 MHz - 20 GHz
LQW15AN53NGBZ	53	±2%	415mA	0.696	1005	Infotainment	50 MHz - 20 GHz
LQW15AN53NJ8Z	53	±5%	415mA	0.696	1005	Infotainment	50 MHz - 20 GHz
LQW15AN56NGBZ	56	±2%	340mA	0.996	1005	Infotainment	50 MHz - 20 GHz
LQW15AN56NJ8Z	56	±5%	340mA	0.996	1005	Infotainment	50 MHz - 20 GHz
LQW15AN68NGBZ	68	±2%	320mA	1.128	1005	Infotainment	50 MHz - 20 GHz
LQW15AN68NJ8Z	68	±5%	320mA	1.128	1005	Infotainment	50 MHz - 20 GHz
LQW15AN75NGBZ	75	±2%	320mA	1.224	1005	Infotainment	50 MHz - 20 GHz
LQW15AN75NJ8Z	75	±5%	320mA	1.224	1005	Infotainment	50 MHz - 20 GHz
LQW15AW51NGB0	51	±2%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW51NH80	51	±3%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW51NJ80	51	±5%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW53NGB0	53	±2%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW53NH80	53	±3%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW53NJ80	53	±5%	480mA	0.47	1005	General	50 MHz - 20 GHz
LQW15AW56NGB0	56	±2%	480mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AW56NH80	56	±3%	480mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AW56NJ80	56	±5%	480mA	0.52	1005	General	50 MHz - 20 GHz
LQW15AW68NGB0	68	±2%	480mA	0.56	1005	General	50 MHz - 20 GHz
LQW15AW68NH80	68	±3%	480mA	0.56	1005	General	50 MHz - 20 GHz
LQW15AW68NJ80	68	±5%	480mA	0.56	1005	General	50 MHz - 20 GHz
LQW15AW75NGB0	75	±2%	450mA	0.61	1005	General	50 MHz - 20 GHz
LQW15AW75NH80	75	±3%	450mA	0.61	1005	General	50 MHz - 20 GHz
LQW15AW75NJ80	75	±5%	450mA	0.61	1005	General	50 MHz - 20 GHz
LQW15AW82NGB0	82	±2%	370mA	0.87	1005	General	50 MHz - 20 GHz
LQW15AW82NH80	82	±3%	370mA	0.87	1005	General	50 MHz - 20 GHz
LQW15AW82NJ80	82	±5%	370mA	0.87	1005	General	50 MHz - 20 GHz
LQW15AWR10G80	100	±2%	350mA	1	1005	General	50 MHz - 20 GHz
LQW15AWR10H80	100	±3%	350mA	1	1005	General	50 MHz - 20 GHz
LQW15AWR10J80	100	±5%	350mA	1	1005	General	50 MHz - 20 GHz
LQW15AWR12G80	120	±2%	320mA	1.2	1005	General	50 MHz - 20 GHz
LQW15AWR12H80	120	±3%	320mA	1.2	1005	General	50 MHz - 20 GHz
LQW15AWR12J80	120	±5%	320mA	1.2	1005	General	50 MHz - 20 GHz
LQW15AWR15G80	150	±2%	280mA	1.71	1005	General	50 MHz - 20 GHz
LQW15AWR15H80	150	±3%	280mA	1.71	1005	General	50 MHz - 20 GHz
LQW15AWR15J80	150	±5%	280mA	1.71	1005	General	50 MHz - 20 GHz
LQW15AWR16G80	160	±2%	280mA	1.86	1005	General	50 MHz - 20 GHz
LQW15AWR16H80	160	±3%	280mA	1.86	1005	General	50 MHz - 20 GHz
LQW15AWR16J80	160	±5%	280mA	1.86	1005	General	50 MHz - 20 GHz
LQW15AWR18G80	180	±2%	260mA	2.2	1005	General	50 MHz - 20 GHz
LQW15AWR18H80	180	±3%	260mA	2.2	1005	General	50 MHz - 20 GHz
LQW15AWR18J80	180	±5%	260mA	2.2	1005	General	50 MHz - 20 GHz
LQW15AWR22G80	220	±2%	220mA	2.75	1005	General	50 MHz - 20 GHz
LQW15AWR22H80	220	±3%	220mA	2.75	1005	General	50 MHz - 20 GHz
LQW15AWR22J80	220	±5%	220mA	2.75	1005	General	50 MHz - 20 GHz
LQW15CA22NJ00	22	±5%	1300mA	0.06	1005	General	10 MHz - 20 GHz
LQW15CA22NK00	22	±10%	1300mA	0.06	1005	General	10 MHz - 20 GHz
LQW15CA39NJ00	39	±5%	1100mA	0.075	1005	General	10 MHz - 20 GHz
LQW15CA39NK00	39	±10%	1100mA	0.075	1005	General	10 MHz - 20 GHz
LQW15CA59NJ00	59	±5%	1000mA	0.095	1005	General	10 MHz - 20 GHz
LQW15CA59NK00	59	±10%	1000mA	0.095	1005	General	10 MHz - 20 GHz
LQW15CA83NJ00	83	±5%	970mA	0.12	1005	General	10 MHz - 20 GHz
LQW15CA83NK00	83	±10%	970mA	0.12	1005	General	10 MHz - 20 GHz
LQW15CAR11J00	110	±5%	900mA	0.13	1005	General	10 MHz - 20 GHz
LQW15CAR11K00	110	±10%	900mA	0.13	1005	General	10 MHz - 20 GHz
LQW15CAR14J00	140	±5%	680mA	0.18	1005	General	10 MHz - 20 GHz
LQW15CAR14K00	140	±10%	680mA	0.18	1005	General	10 MHz - 20 GHz
LQW15CAR18J00	180	±5%	640mA	0.21	1005	General	10 MHz - 20 GHz
LQW15CAR18K00	180	±10%	640mA	0.21	1005	General	10 MHz - 20 GHz
LQW15CAR22J00	220	±5%	540mA	0.29	1005	General	10 MHz - 20 GHz
LQW15CAR22K00	220	±10%	540mA	0.29	1005	General	10 MHz - 20 GHz
LQW15CAR27J00	270	±5%	480mA	0.38	1005	General	10 MHz - 20 GHz
LQW15CAR27K00	270	±10%	480mA	0.38	1005	General	10 MHz - 20 GHz
LQW15CAR32J00	320	±5%	420mA	0.41	1005	General	10 MHz - 20 GHz
LQW15CAR32K00	320	±10%	420mA	0.41	1005	General	10 MHz - 20 GHz
LQW15CAR37J00	370	±5%	360mA	0.575	1005	General	10 MHz - 20 GHz
LQW15CAR37K00	370	±10%	360mA	0.575	1005	General	10 MHz - 20 GHz
LQW15CAR39J00	390	±5%	320mA	0.72	1005	General	10 MHz - 20 GHz
LQW15CAR39K00	390	±10%	320mA	0.72	1005	General	10 MHz - 20 GHz
LQW15CAR43J00	430	±5%	360mA	0.68	1005	General	10 MHz - 20 GHz
LQW15CAR43K00	430	±10%	360mA	0.68	1005	General	10 MHz - 20 GHz
LQW15CAR50J00	500	±5%	270mA	0.97	1005	General	10 MHz - 20 GHz
LQW15CAR50K00	500	±10%	270mA	0.97	1005	General	10 MHz - 20 GHz
LQW15CAR56J00	560	±5%	270mA	1	1005	General	10 MHz - 20 GHz
LQW15CAR56K00	560	±10%	270mA	1	1005	General	10 MHz - 20 GHz
LQW15CAR64J00	640	±5%	240mA	1.4	1005	General	10 MHz - 20 GHz
LQW15CAR64K00	640	±10%	240mA	1.4	1005	General	10 MHz - 20 GHz
LQW15CAR73J00	730	±5%	200mA	1.95	1005	General	10 MHz - 20 GHz
LQW15CAR73K00	730	±10%	200mA	1.95	1005	General	10 MHz - 20 GHz
LQW15CAR80J00	800	±5%	190mA	2.1	1005	General	10 MHz - 20 GHz
LQW15CAR80K00	800	±10%	190mA	2.1	1005	General	10 MHz - 20 GHz
LQW15CA1R0K00	1000	±10%	180mA	2.2	1005	General	10 MHz - 20 GHz
LQW15CA2R0K00	2000	±10%	130mA	3.2	1005	General	10 MHz - 20 GHz
LQW15CE1R0M10	1000	±20%	270mA	0.94	1005	General	10 MHz - 20 GHz
LQW15CE1R5M10	1500	±20%	190mA	1.5	1005	General	10 MHz - 20 GHz
LQW15CE2R2M10	2200	±20%	170mA	1.8	1005	General	10 MHz - 20 GHz
LQW15CE3R3M10	3300	±20%	130mA	3.65	1005	General	10 MHz - 20 GHz
LQW15CN18NJ00	18	±5%	1400mA	0.046	1005	General	10 MHz - 20 GHz
LQW15CN33NJ00	33	±5%	1300mA	0.065	1005	General	10 MHz - 20 GHz
LQW15CN48NJ00	48	±5%	1100mA	0.078	1005	General	10 MHz - 20 GHz
LQW15CN70NJ00	70	±5%	820mA	0.12	1005	General	10 MHz - 20 GHz
LQW15CN96NJ00	96	±5%	730mA	0.16	1005	General	10 MHz - 20 GHz
LQW15CNR13J00	130	±5%	640mA	0.23	1005	General	10 MHz - 20 GHz
LQW15CNR16J00	160	±5%	480mA	0.33	1005	General	10 MHz - 20 GHz
LQW15CNR20J00	200	±5%	390mA	0.47	1005	General	10 MHz - 20 GHz
LQW15CN18NJ0Z	18	±5%	1400mA	0.046	1005	Infotainment	10 MHz - 20 GHz
LQW15CN33NJ0Z	33	±5%	1300mA	0.065	1005	Infotainment	10 MHz - 20 GHz
LQW15CN48NJ0Z	48	±5%	1100mA	0.078	1005	Infotainment	10 MHz - 20 GHz
LQW15CN70NJ0Z	70	±5%	820mA	0.12	1005	Infotainment	10 MHz - 20 GHz
LQW15CN96NJ0Z	96	±5%	730mA	0.16	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR13J0Z	130	±5%	640mA	0.23	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR16J0Z	160	±5%	480mA	0.33	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR20J0Z	200	±5%	390mA	0.47	1005	Infotainment	10 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW15CN20NJ10	20	±5%	2200mA	0.028	1005	General	10 MHz - 20 GHz
LQW15CN20NK10	20	±10%	2200mA	0.028	1005	General	10 MHz - 20 GHz
LQW15CN34NJ10	34	±5%	1800mA	0.036	1005	General	10 MHz - 20 GHz
LQW15CN34NK10	34	±10%	1800mA	0.036	1005	General	10 MHz - 20 GHz
LQW15CN53NJ10	53	±5%	1300mA	0.06	1005	General	10 MHz - 20 GHz
LQW15CN53NK10	53	±10%	1300mA	0.06	1005	General	10 MHz - 20 GHz
LQW15CN77NJ10	77	±5%	1100mA	0.09	1005	General	10 MHz - 20 GHz
LQW15CN77NK10	77	±10%	1100mA	0.09	1005	General	10 MHz - 20 GHz
LQW15CNR11J10	106	±5%	850mA	0.144	1005	General	10 MHz - 20 GHz
LQW15CNR11K10	106	±10%	850mA	0.144	1005	General	10 MHz - 20 GHz
LQW15CNR14J10	140	±5%	650mA	0.216	1005	General	10 MHz - 20 GHz
LQW15CNR14K10	140	±10%	650mA	0.216	1005	General	10 MHz - 20 GHz
LQW15CNR18J10	180	±5%	560mA	0.312	1005	General	10 MHz - 20 GHz
LQW15CNR18K10	180	±10%	560mA	0.312	1005	General	10 MHz - 20 GHz
LQW15CNR22J10	220	±5%	450mA	0.47	1005	General	10 MHz - 20 GHz
LQW15CNR22K10	220	±10%	450mA	0.47	1005	General	10 MHz - 20 GHz
LQW15CNR27J10	270	±5%	420mA	0.52	1005	General	10 MHz - 20 GHz
LQW15CNR27K10	270	±10%	420mA	0.52	1005	General	10 MHz - 20 GHz
LQW15CNR33J10	330	±5%	390mA	0.56	1005	General	10 MHz - 20 GHz
LQW15CNR33K10	330	±10%	390mA	0.56	1005	General	10 MHz - 20 GHz
LQW15CNR39J10	390	±5%	370mA	0.62	1005	General	10 MHz - 20 GHz
LQW15CNR39K10	390	±10%	370mA	0.62	1005	General	10 MHz - 20 GHz
LQW15CNR42J10	420	±5%	370mA	0.62	1005	General	10 MHz - 20 GHz
LQW15CNR42K10	420	±10%	370mA	0.62	1005	General	10 MHz - 20 GHz
LQW15CNR47J10	470	±5%	350mA	0.66	1005	General	10 MHz - 20 GHz
LQW15CNR47K10	470	±10%	350mA	0.66	1005	General	10 MHz - 20 GHz
LQW15CNR56J10	560	±5%	300mA	0.71	1005	General	10 MHz - 20 GHz
LQW15CNR56K10	560	±10%	300mA	0.71	1005	General	10 MHz - 20 GHz
LQW15CNR68M10	680	±20%	290mA	0.78	1005	General	10 MHz - 20 GHz
LQW15CNR82M10	820	±20%	275mA	0.84	1005	General	10 MHz - 20 GHz
LQW15CN1R0M10	1000	±20%	270mA	0.94	1005	General	10 MHz - 20 GHz
LQW15CN1R5M10	1500	±20%	190mA	1.5	1005	General	10 MHz - 20 GHz
LQW15CN2R2M10	2200	±20%	170mA	1.8	1005	General	10 MHz - 20 GHz
LQW15CN3R3M10	3300	±20%	130mA	3.65	1005	General	10 MHz - 20 GHz
LQW15CN20NJZ	20	±5%	2200mA	0.028	1005	Infotainment	10 MHz - 20 GHz
LQW15CN20NKZ	20	±10%	2200mA	0.028	1005	Infotainment	10 MHz - 20 GHz
LQW15CN34NJZ	34	±5%	1800mA	0.036	1005	Infotainment	10 MHz - 20 GHz
LQW15CN34NKZ	34	±10%	1800mA	0.036	1005	Infotainment	10 MHz - 20 GHz
LQW15CN53NJZ	53	±5%	1300mA	0.06	1005	Infotainment	10 MHz - 20 GHz
LQW15CN53NKZ	53	±10%	1300mA	0.06	1005	Infotainment	10 MHz - 20 GHz
LQW15CN77NJZ	77	±5%	1100mA	0.09	1005	Infotainment	10 MHz - 20 GHz
LQW15CN77NKZ	77	±10%	1100mA	0.09	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR11JZ	106	±5%	850mA	0.144	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR11KZ	106	±10%	850mA	0.144	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR14JZ	140	±5%	650mA	0.216	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR14KZ	140	±10%	650mA	0.216	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR18JZ	180	±5%	560mA	0.312	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR18KZ	180	±10%	560mA	0.312	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR22JZ	220	±5%	450mA	0.47	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR22KZ	220	±10%	450mA	0.47	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR27JZ	270	±5%	420mA	0.52	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR27KZ	270	±10%	420mA	0.52	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR33JZ	330	±5%	390mA	0.56	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR33KZ	330	±10%	390mA	0.56	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR39JZ	390	±5%	370mA	0.62	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR39KZ	390	±10%	370mA	0.62	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR42JZ	420	±5%	370mA	0.62	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR42KZ	420	±10%	370mA	0.62	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR47JZ	470	±5%	350mA	0.66	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR47KZ	470	±10%	350mA	0.66	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR56JZ	560	±5%	300mA	0.71	1005	Infotainment	10 MHz - 20 GHz
LQW15CNR56KZ	560	±10%	300mA	0.71	1005	Infotainment	10 MHz - 20 GHz
LQW15DN100M00	10000	±20%	120mA	5.405	1005	General	50 MHz - 20 GHz
LQW15DN150M00	15000	±20%	100mA	6.555	1005	General	50 MHz - 20 GHz
LQW18AN2N2D00	2.2	±0.5nH	700mA	0.42	1608	General	50 MHz - 20 GHz
LQW18AN3N6C00	3.6	±0.2nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN3N6D00	3.6	±0.5nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN3N9C00	3.9	±0.2nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN3N9D00	3.9	±0.5nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN4N3C00	4.3	±0.2nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN4N3D00	4.3	±0.5nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN4N7D00	4.7	±0.5nH	850mA	0.059	1608	General	50 MHz - 20 GHz
LQW18AN5N6C00	5.6	±0.2nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN5N6D00	5.6	±0.5nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN6N2C00	6.2	±0.2nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN6N2D00	6.2	±0.5nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN6N8C00	6.8	±0.2nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN6N8D00	6.8	±0.5nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN7N5C00	7.5	±0.2nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN7N5D00	7.5	±0.5nH	750mA	0.082	1608	General	50 MHz - 20 GHz
LQW18AN8N2C00	8.2	±0.2nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN8N2D00	8.2	±0.5nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN8N7C00	8.7	±0.2nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN8N7D00	8.7	±0.5nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN9N1C00	9.1	±0.2nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN9N1D00	9.1	±0.5nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN9N5D00	9.5	±0.5nH	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN10NG00	10	±2%	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN10NJ00	10	±5%	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN11NG00	11	±2%	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN11NJ00	11	±5%	650mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN12NG00	12	±2%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN12NJ00	12	±5%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN13NG00	13	±2%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN13NJ00	13	±5%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN15NG00	15	±2%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN15NJ00	15	±5%	600mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AN16NG00	16	±2%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN16NJ00	16	±5%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN18NG00	18	±2%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN18NJ00	18	±5%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN20NG00	20	±2%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN20NJ00	20	±5%	550mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN22NG00	22	±2%	500mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AN22NJ00	22	±5%	500mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AN24NG00	24	±2%	500mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN24NJ00	24	±5%	500mA	0.21	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18AN27NG00	27	±2%	440mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN27NJ00	27	±5%	440mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN30NG00	30	±2%	420mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN30NJ00	30	±5%	420mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN33NG00	33	±2%	420mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN33NJ00	33	±5%	420mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN36NG00	36	±2%	400mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN36NJ00	36	±5%	400mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN39NG00	39	±2%	400mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN39NJ00	39	±5%	400mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN43NG00	43	±2%	380mA	0.29	1608	General	50 MHz - 20 GHz
LQW18AN43NJ00	43	±5%	380mA	0.29	1608	General	50 MHz - 20 GHz
LQW18AN47NG00	47	±2%	380mA	0.29	1608	General	50 MHz - 20 GHz
LQW18AN47NJ00	47	±5%	380mA	0.29	1608	General	50 MHz - 20 GHz
LQW18AN51NG00	51	±2%	370mA	0.33	1608	General	50 MHz - 20 GHz
LQW18AN51NJ00	51	±5%	370mA	0.33	1608	General	50 MHz - 20 GHz
LQW18AN56NG00	56	±2%	360mA	0.35	1608	General	50 MHz - 20 GHz
LQW18AN56NJ00	56	±5%	360mA	0.35	1608	General	50 MHz - 20 GHz
LQW18AN62NG00	62	±2%	280mA	0.51	1608	General	50 MHz - 20 GHz
LQW18AN62NJ00	62	±5%	280mA	0.51	1608	General	50 MHz - 20 GHz
LQW18AN68NG00	68	±2%	340mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN68NJ00	68	±5%	340mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN72NG00	72	±2%	270mA	0.56	1608	General	50 MHz - 20 GHz
LQW18AN72NJ00	72	±5%	270mA	0.56	1608	General	50 MHz - 20 GHz
LQW18AN75NG00	75	±2%	270mA	0.56	1608	General	50 MHz - 20 GHz
LQW18AN75NJ00	75	±5%	270mA	0.56	1608	General	50 MHz - 20 GHz
LQW18AN82NG00	82	±2%	250mA	0.6	1608	General	50 MHz - 20 GHz
LQW18AN82NJ00	82	±5%	250mA	0.6	1608	General	50 MHz - 20 GHz
LQW18AN91NG00	91	±2%	230mA	0.64	1608	General	50 MHz - 20 GHz
LQW18AN91NJ00	91	±5%	230mA	0.64	1608	General	50 MHz - 20 GHz
LQW18ANR10G00	100	±2%	220mA	0.68	1608	General	50 MHz - 20 GHz
LQW18ANR10J00	100	±5%	220mA	0.68	1608	General	50 MHz - 20 GHz
LQW18ANR11G00	110	±2%	200mA	1.2	1608	General	50 MHz - 20 GHz
LQW18ANR11J00	110	±5%	200mA	1.2	1608	General	50 MHz - 20 GHz
LQW18ANR12G00	120	±2%	180mA	1.3	1608	General	50 MHz - 20 GHz
LQW18ANR12J00	120	±5%	180mA	1.3	1608	General	50 MHz - 20 GHz
LQW18ANR13G00	130	±2%	170mA	1.4	1608	General	50 MHz - 20 GHz
LQW18ANR13J00	130	±5%	170mA	1.4	1608	General	50 MHz - 20 GHz
LQW18ANR15G00	150	±2%	160mA	1.5	1608	General	50 MHz - 20 GHz
LQW18ANR15J00	150	±5%	160mA	1.5	1608	General	50 MHz - 20 GHz
LQW18ANR16G00	160	±2%	150mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ANR16J00	160	±5%	150mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ANR18G00	180	±2%	140mA	2.2	1608	General	50 MHz - 20 GHz
LQW18ANR18J00	180	±5%	140mA	2.2	1608	General	50 MHz - 20 GHz
LQW18ANR20G00	200	±2%	120mA	2.4	1608	General	50 MHz - 20 GHz
LQW18ANR20J00	200	±5%	120mA	2.4	1608	General	50 MHz - 20 GHz
LQW18ANR22G00	220	±2%	120mA	2.5	1608	General	50 MHz - 20 GHz
LQW18ANR22J00	220	±5%	120mA	2.5	1608	General	50 MHz - 20 GHz
LQW18ANR27G00	270	±2%	110mA	3.4	1608	General	50 MHz - 20 GHz
LQW18ANR27J00	270	±5%	110mA	3.4	1608	General	50 MHz - 20 GHz
LQW18ANR33G00	330	±2%	85mA	5.5	1608	General	50 MHz - 20 GHz
LQW18ANR33J00	330	±5%	85mA	5.5	1608	General	50 MHz - 20 GHz
LQW18ANR39G00	390	±2%	80mA	6.2	1608	General	50 MHz - 20 GHz
LQW18ANR39J00	390	±5%	80mA	6.2	1608	General	50 MHz - 20 GHz
LQW18ANR47G00	470	±2%	75mA	7	1608	General	50 MHz - 20 GHz
LQW18ANR47J00	470	±5%	75mA	7	1608	General	50 MHz - 20 GHz
LQW18AN2ND0Z	2.2	±0.5nH	700mA	0.042	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N6C0Z	3.6	±0.2nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N6D0Z	3.6	±0.5nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9C0Z	3.9	±0.2nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9D0Z	3.9	±0.5nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N3C0Z	4.3	±0.2nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N3D0Z	4.3	±0.5nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N7D0Z	4.7	±0.5nH	850mA	0.059	1608	Infotainment	50 MHz - 20 GHz
LQW18AN5N6C0Z	5.6	±0.2nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN5N6D0Z	5.6	±0.5nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N2C0Z	6.2	±0.2nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N2D0Z	6.2	±0.5nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8C0Z	6.8	±0.2nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8D0Z	6.8	±0.5nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N5C0Z	7.5	±0.2nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N5D0Z	7.5	±0.5nH	750mA	0.082	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N2C0Z	8.2	±0.2nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N2D0Z	8.2	±0.5nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N7C0Z	8.7	±0.2nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N7D0Z	8.7	±0.5nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N1C0Z	9.1	±0.2nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N1D0Z	9.1	±0.5nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N5D0Z	9.5	±0.5nH	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NG0Z	10	±2%	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NJ0Z	10	±5%	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN11NG0Z	11	±2%	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN11NJ0Z	11	±5%	650mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NG0Z	12	±2%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NJ0Z	12	±5%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN13NG0Z	13	±2%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN13NJ0Z	13	±5%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN15NG0Z	15	±2%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN15NJ0Z	15	±5%	600mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AN16NG0Z	16	±2%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN16NJ0Z	16	±5%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NG0Z	18	±2%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NJ0Z	18	±5%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN20NG0Z	20	±2%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN20NJ0Z	20	±5%	550mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NG0Z	22	±2%	500mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NJ0Z	22	±5%	500mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AN24NG0Z	24	±2%	500mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN24NJ0Z	24	±5%	500mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NG0Z	27	±2%	440mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NJ0Z	27	±5%	440mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN30NG0Z	30	±2%	420mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN30NJ0Z	30	±5%	420mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN33NG0Z	33	±2%	420mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN33NJ0Z	33	±5%	420mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN36NG0Z	36	±2%	400mA	0.26	1608	Infotainment	50 MHz - 20 GHz
LQW18AN36NJ0Z	36	±5%	400mA	0.26	1608	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18AN39NGOZ	39	±2%	400mA	0.26	1608	Infotainment	50 MHz - 20 GHz
LQW18AN39NJ0Z	39	±5%	400mA	0.26	1608	Infotainment	50 MHz - 20 GHz
LQW18AN43NGOZ	43	±2%	380mA	0.29	1608	Infotainment	50 MHz - 20 GHz
LQW18AN43NJ0Z	43	±5%	380mA	0.29	1608	Infotainment	50 MHz - 20 GHz
LQW18AN47NGOZ	47	±2%	380mA	0.29	1608	Infotainment	50 MHz - 20 GHz
LQW18AN47NJ0Z	47	±5%	380mA	0.29	1608	Infotainment	50 MHz - 20 GHz
LQW18AN51NGOZ	51	±2%	370mA	0.33	1608	Infotainment	50 MHz - 20 GHz
LQW18AN51NJ0Z	51	±5%	370mA	0.33	1608	Infotainment	50 MHz - 20 GHz
LQW18AN56NGOZ	56	±2%	360mA	0.35	1608	Infotainment	50 MHz - 20 GHz
LQW18AN56NJ0Z	56	±5%	360mA	0.35	1608	Infotainment	50 MHz - 20 GHz
LQW18AN62NGOZ	62	±2%	280mA	0.51	1608	Infotainment	50 MHz - 20 GHz
LQW18AN62NJ0Z	62	±5%	280mA	0.51	1608	Infotainment	50 MHz - 20 GHz
LQW18AN68NGOZ	68	±2%	340mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN68NJ0Z	68	±5%	340mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN72NGOZ	72	±2%	270mA	0.56	1608	Infotainment	50 MHz - 20 GHz
LQW18AN72NJ0Z	72	±5%	270mA	0.56	1608	Infotainment	50 MHz - 20 GHz
LQW18AN75NGOZ	75	±2%	270mA	0.56	1608	Infotainment	50 MHz - 20 GHz
LQW18AN75NJ0Z	75	±5%	270mA	0.56	1608	Infotainment	50 MHz - 20 GHz
LQW18AN82NGOZ	82	±2%	250mA	0.6	1608	Infotainment	50 MHz - 20 GHz
LQW18AN82NJ0Z	82	±5%	250mA	0.6	1608	Infotainment	50 MHz - 20 GHz
LQW18AN91NGOZ	91	±2%	230mA	0.64	1608	Infotainment	50 MHz - 20 GHz
LQW18AN91NJ0Z	91	±5%	230mA	0.64	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR10GOZ	100	±2%	220mA	0.68	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR10J0Z	100	±5%	220mA	0.68	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR11GOZ	110	±2%	200mA	1.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR11J0Z	110	±5%	200mA	1.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR12GOZ	120	±2%	180mA	1.3	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR12J0Z	120	±5%	180mA	1.3	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR13GOZ	130	±2%	170mA	1.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR13J0Z	130	±5%	170mA	1.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR15GOZ	150	±2%	160mA	1.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR15J0Z	150	±5%	160mA	1.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR16GOZ	160	±2%	150mA	2.1	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR16J0Z	160	±5%	150mA	2.1	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR18GOZ	180	±2%	140mA	2.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR18J0Z	180	±5%	140mA	2.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR20GOZ	200	±2%	120mA	2.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR20J0Z	200	±5%	120mA	2.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR22GOZ	220	±2%	120mA	2.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR22J0Z	220	±5%	120mA	2.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR27GOZ	270	±2%	110mA	3.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR27J0Z	270	±5%	110mA	3.4	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR33GOZ	330	±2%	85mA	5.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR33J0Z	330	±5%	85mA	5.5	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR39GOZ	390	±2%	80mA	6.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR39J0Z	390	±5%	80mA	6.2	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR47GOZ	470	±2%	75mA	7	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR47J0Z	470	±5%	75mA	7	1608	Infotainment	50 MHz - 20 GHz
LQW18AN2ND10	2.2	±0.5nH	1400mA	0.018	1608	General	50 MHz - 20 GHz
LQW18AN3N9C10	3.9	±0.2nH	1000mA	0.032	1608	General	50 MHz - 20 GHz
LQW18AN3N9D10	3.9	±0.5nH	1000mA	0.032	1608	General	50 MHz - 20 GHz
LQW18AN5N6D10	5.6	±0.5nH	900mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AN6N8C10	6.8	±0.2nH	900mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AN6N8D10	6.8	±0.5nH	900mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AN8N2D10	8.2	±0.5nH	800mA	0.058	1608	General	50 MHz - 20 GHz
LQW18AN10NG10	10	±2%	800mA	0.058	1608	General	50 MHz - 20 GHz
LQW18AN10NJ10	10	±5%	800mA	0.058	1608	General	50 MHz - 20 GHz
LQW18AN12NG10	12	±2%	750mA	0.071	1608	General	50 MHz - 20 GHz
LQW18AN12NJ10	12	±5%	750mA	0.071	1608	General	50 MHz - 20 GHz
LQW18AN15NJ10	15	±5%	700mA	0.085	1608	General	50 MHz - 20 GHz
LQW18AN18NG10	18	±2%	700mA	0.085	1608	General	50 MHz - 20 GHz
LQW18AN18NJ10	18	±5%	700mA	0.085	1608	General	50 MHz - 20 GHz
LQW18AN22NG10	22	±2%	640mA	0.099	1608	General	50 MHz - 20 GHz
LQW18AN22NJ10	22	±5%	640mA	0.099	1608	General	50 MHz - 20 GHz
LQW18AN27NG10	27	±2%	590mA	0.116	1608	General	50 MHz - 20 GHz
LQW18AN27NJ10	27	±5%	590mA	0.116	1608	General	50 MHz - 20 GHz
LQW18AN33NJ10	33	±5%	550mA	0.132	1608	General	50 MHz - 20 GHz
LQW18AN2ND1Z	2.2	±0.5nH	1400mA	0.018	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9C1Z	3.9	±0.2nH	1000mA	0.032	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9D1Z	3.9	±0.5nH	1000mA	0.032	1608	Infotainment	50 MHz - 20 GHz
LQW18AN5N6D1Z	5.6	±0.5nH	900mA	0.045	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8C1Z	6.8	±0.2nH	900mA	0.045	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8D1Z	6.8	±0.5nH	900mA	0.045	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N2D1Z	8.2	±0.5nH	800mA	0.058	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NG1Z	10	±2%	800mA	0.058	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NJ1Z	10	±5%	800mA	0.058	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NG1Z	12	±2%	750mA	0.071	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NJ1Z	12	±5%	750mA	0.071	1608	Infotainment	50 MHz - 20 GHz
LQW18AN15NJ1Z	15	±5%	700mA	0.085	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NG1Z	18	±2%	700mA	0.085	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NJ1Z	18	±5%	700mA	0.085	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NG1Z	22	±2%	640mA	0.099	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NJ1Z	22	±5%	640mA	0.099	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NG1Z	27	±2%	590mA	0.116	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NJ1Z	27	±5%	590mA	0.116	1608	Infotainment	50 MHz - 20 GHz
LQW18AN33NJ1Z	33	±5%	550mA	0.132	1608	Infotainment	50 MHz - 20 GHz
LQW18AN2N2C80	2.2	±0.2nH	3200mA	0.018	1608	General	50 MHz - 20 GHz
LQW18AN2N4C80	2.4	±0.2nH	2400mA	0.026	1608	General	50 MHz - 20 GHz
LQW18AN3N0C80	3	±0.2nH	670mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AN3N9B80	3.9	±0.1nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN3N9C80	3.9	±0.2nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN3N9G80	3.9	±2%	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N1B80	4.1	±0.1nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N1C80	4.1	±0.2nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N1G80	4.1	±2%	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N2B80	4.2	±0.1nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N2C80	4.2	±0.2nH	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N2G80	4.2	±2%	2200mA	0.028	1608	General	50 MHz - 20 GHz
LQW18AN4N3B80	4.3	±0.1nH	2100mA	0.036	1608	General	50 MHz - 20 GHz
LQW18AN4N3C80	4.3	±0.2nH	2100mA	0.036	1608	General	50 MHz - 20 GHz
LQW18AN4N3G80	4.3	±2%	2100mA	0.036	1608	General	50 MHz - 20 GHz
LQW18AN4N7B80	4.7	±0.1nH	1500mA	0.054	1608	General	50 MHz - 20 GHz
LQW18AN4N7C80	4.7	±0.2nH	1500mA	0.054	1608	General	50 MHz - 20 GHz
LQW18AN4N7G80	4.7	±2%	1500mA	0.054	1608	General	50 MHz - 20 GHz
LQW18AN4N9B80	4.9	±0.1nH	1200mA	0.081	1608	General	50 MHz - 20 GHz
LQW18AN4N9C80	4.9	±0.2nH	1200mA	0.081	1608	General	50 MHz - 20 GHz
LQW18AN4N9G80	4.9	±2%	1200mA	0.081	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18AN5N6C80	5.6	±0.2nH	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN5N6G80	5.6	±2%	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N0C80	6	±0.2nH	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N0G80	6	±2%	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N5C80	6.5	±0.2nH	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N5G80	6.5	±2%	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N8C80	6.8	±0.2nH	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN6N8G80	6.8	±2%	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN7N2C80	7.2	±0.2nH	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN7N2G80	7.2	±2%	1900mA	0.04	1608	General	50 MHz - 20 GHz
LQW18AN7N5C80	7.5	±0.2nH	1500mA	0.048	1608	General	50 MHz - 20 GHz
LQW18AN7N5G80	7.5	±2%	1500mA	0.048	1608	General	50 MHz - 20 GHz
LQW18AN8N2C80	8.2	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN8N2G80	8.2	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN8N4C80	8.4	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN8N4G80	8.4	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN8N7C80	8.7	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN8N7G80	8.7	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N1C80	9.1	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N1G80	9.1	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N5C80	9.5	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N5G80	9.5	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N9C80	9.9	±0.2nH	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN9N9G80	9.9	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN10NG80	10	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN10NJ80	10	±5%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN11NG80	11	±2%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN11NJ80	11	±5%	1600mA	0.052	1608	General	50 MHz - 20 GHz
LQW18AN12NG80	12	±2%	1500mA	0.064	1608	General	50 MHz - 20 GHz
LQW18AN12NJ80	12	±5%	1500mA	0.064	1608	General	50 MHz - 20 GHz
LQW18AN13NG80	13	±2%	1500mA	0.064	1608	General	50 MHz - 20 GHz
LQW18AN13NJ80	13	±5%	1500mA	0.064	1608	General	50 MHz - 20 GHz
LQW18AN15NG80	15	±2%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN15NJ80	15	±5%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN16NG80	16	±2%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN16NJ80	16	±5%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN17NG80	17	±2%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN17NJ80	17	±5%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN18NG80	18	±2%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN18NJ80	18	±5%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN19NG80	19	±2%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN19NJ80	19	±5%	1400mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AN22NG80	22	±2%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN22NJ80	22	±5%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN23NG80	23	±2%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN23NJ80	23	±5%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN24NG80	24	±2%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN24NJ80	24	±5%	1300mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AN25NG80	25	±2%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN25NJ80	25	±5%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN27NG80	27	±2%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN27NJ80	27	±5%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN28NG80	28	±2%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN28NJ80	28	±5%	1200mA	0.098	1608	General	50 MHz - 20 GHz
LQW18AN30NG80	30	±2%	1100mA	0.12	1608	General	50 MHz - 20 GHz
LQW18AN30NJ80	30	±5%	1100mA	0.12	1608	General	50 MHz - 20 GHz
LQW18AN31NG80	31	±2%	1100mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN31NJ80	31	±5%	1100mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN33NG80	33	±2%	1100mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN33NJ80	33	±5%	1100mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AN34NG80	34	±2%	1050mA	0.15	1608	General	50 MHz - 20 GHz
LQW18AN34NJ80	34	±5%	1050mA	0.15	1608	General	50 MHz - 20 GHz
LQW18AN36NG80	36	±2%	910mA	0.2	1608	General	50 MHz - 20 GHz
LQW18AN36NJ80	36	±5%	910mA	0.2	1608	General	50 MHz - 20 GHz
LQW18AN37NG80	37	±2%	910mA	0.2	1608	General	50 MHz - 20 GHz
LQW18AN37NJ80	37	±5%	910mA	0.2	1608	General	50 MHz - 20 GHz
LQW18AN39NG80	39	±2%	1000mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN39NJ80	39	±5%	1000mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN41NG80	41	±2%	1000mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN41NJ80	41	±5%	1000mA	0.16	1608	General	50 MHz - 20 GHz
LQW18AN43NG80	43	±2%	840mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN43NJ80	43	±5%	840mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN44NG80	44	±2%	840mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN44NJ80	44	±5%	840mA	0.21	1608	General	50 MHz - 20 GHz
LQW18AN47NG80	47	±2%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN47NJ80	47	±5%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN48NG80	48	±2%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN48NJ80	48	±5%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN51NG80	51	±2%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN51NJ80	51	±5%	830mA	0.23	1608	General	50 MHz - 20 GHz
LQW18AN52NG80	52	±2%	750mA	0.27	1608	General	50 MHz - 20 GHz
LQW18AN52NJ80	52	±5%	750mA	0.27	1608	General	50 MHz - 20 GHz
LQW18AN56NG80	56	±2%	770mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN56NJ80	56	±5%	770mA	0.26	1608	General	50 MHz - 20 GHz
LQW18AN58NG80	58	±2%	700mA	0.3	1608	General	50 MHz - 20 GHz
LQW18AN58NJ80	58	±5%	700mA	0.3	1608	General	50 MHz - 20 GHz
LQW18AN68NG80	68	±2%	630mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN68NJ80	68	±5%	630mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN69NG80	69	±2%	630mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN69NJ80	69	±5%	630mA	0.38	1608	General	50 MHz - 20 GHz
LQW18AN72NG80	72	±2%	560mA	0.47	1608	General	50 MHz - 20 GHz
LQW18AN72NJ80	72	±5%	560mA	0.47	1608	General	50 MHz - 20 GHz
LQW18AN73NG80	73	±2%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN73NJ80	73	±5%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN75NG80	75	±2%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN75NJ80	75	±5%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN78NG80	78	±2%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN78NJ80	78	±5%	590mA	0.41	1608	General	50 MHz - 20 GHz
LQW18AN82NG80	82	±2%	550mA	0.5	1608	General	50 MHz - 20 GHz
LQW18AN82NJ80	82	±5%	550mA	0.5	1608	General	50 MHz - 20 GHz
LQW18AN83NG80	83	±2%	550mA	0.5	1608	General	50 MHz - 20 GHz
LQW18AN83NJ80	83	±5%	550mA	0.5	1608	General	50 MHz - 20 GHz
LQW18AN91NG80	91	±2%	520mA	0.54	1608	General	50 MHz - 20 GHz
LQW18AN91NJ80	91	±5%	520mA	0.54	1608	General	50 MHz - 20 GHz
LQW18AN94NG80	94	±2%	490mA	0.63	1608	General	50 MHz - 20 GHz
LQW18AN94NJ80	94	±5%	490mA	0.63	1608	General	50 MHz - 20 GHz
LQW18ANR10G80	100	±2%	490mA	0.63	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18ANR10J80	100	±5%	490mA	0.63	1608	General	50 MHz - 20 GHz
LQW18ANR11G80	110	±2%	450mA	0.7	1608	General	50 MHz - 20 GHz
LQW18ANR11J80	110	±5%	450mA	0.7	1608	General	50 MHz - 20 GHz
LQW18ANR12G80	120	±2%	450mA	0.72	1608	General	50 MHz - 20 GHz
LQW18ANR12J80	120	±5%	450mA	0.72	1608	General	50 MHz - 20 GHz
LQW18ANR15G80	150	±2%	420mA	0.87	1608	General	50 MHz - 20 GHz
LQW18ANR15J80	150	±5%	420mA	0.87	1608	General	50 MHz - 20 GHz
LQW18ANR18G80	180	±2%	310mA	1.65	1608	General	50 MHz - 20 GHz
LQW18ANR18J80	180	±5%	310mA	1.65	1608	General	50 MHz - 20 GHz
LQW18ANR20G80	200	±2%	290mA	1.74	1608	General	50 MHz - 20 GHz
LQW18ANR20J80	200	±5%	290mA	1.74	1608	General	50 MHz - 20 GHz
LQW18ANR21G80	210	±2%	280mA	1.98	1608	General	50 MHz - 20 GHz
LQW18ANR21J80	210	±5%	280mA	1.98	1608	General	50 MHz - 20 GHz
LQW18ANR22G80	220	±2%	280mA	2.08	1608	General	50 MHz - 20 GHz
LQW18ANR22J80	220	±5%	280mA	2.08	1608	General	50 MHz - 20 GHz
LQW18ANR25G80	250	±2%	250mA	2.28	1608	General	50 MHz - 20 GHz
LQW18ANR25J80	250	±5%	250mA	2.28	1608	General	50 MHz - 20 GHz
LQW18ANR27G80	270	±2%	260mA	2.42	1608	General	50 MHz - 20 GHz
LQW18ANR27J80	270	±5%	260mA	2.42	1608	General	50 MHz - 20 GHz
LQW18ANR30G80	300	±2%	220mA	3.12	1608	General	50 MHz - 20 GHz
LQW18ANR30J80	300	±5%	220mA	3.12	1608	General	50 MHz - 20 GHz
LQW18ANR33G80	330	±2%	190mA	3.84	1608	General	50 MHz - 20 GHz
LQW18ANR33J80	330	±5%	190mA	3.84	1608	General	50 MHz - 20 GHz
LQW18ANR36G80	360	±2%	190mA	3.98	1608	General	50 MHz - 20 GHz
LQW18ANR36J80	360	±5%	190mA	3.98	1608	General	50 MHz - 20 GHz
LQW18ANR39G80	390	±2%	190mA	4.23	1608	General	50 MHz - 20 GHz
LQW18ANR39J80	390	±5%	190mA	4.23	1608	General	50 MHz - 20 GHz
LQW18AN2N2C8Z	2.2	±0.2nH	3200mA	0.018	1608	Infotainment	50 MHz - 20 GHz
LQW18AN2N4C8Z	2.4	±0.2nH	2400mA	0.026	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N0C8Z	3	±0.2nH	670mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9B8Z	3.9	±0.1nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9C8Z	3.9	±0.2nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN3N9G8Z	3.9	±2%	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N1B8Z	4.1	±0.1nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N1C8Z	4.1	±0.2nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N1G8Z	4.1	±2%	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N2B8Z	4.2	±0.1nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N2C8Z	4.2	±0.2nH	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N2G8Z	4.2	±2%	2200mA	0.028	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N3B8Z	4.3	±0.1nH	2100mA	0.036	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N3C8Z	4.3	±0.2nH	2100mA	0.036	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N3G8Z	4.3	±2%	2100mA	0.036	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N7B8Z	4.7	±0.1nH	1500mA	0.054	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N7C8Z	4.7	±0.2nH	1500mA	0.054	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N7G8Z	4.7	±2%	1500mA	0.054	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N9B8Z	4.9	±0.1nH	1200mA	0.081	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N9C8Z	4.9	±0.2nH	1200mA	0.081	1608	Infotainment	50 MHz - 20 GHz
LQW18AN4N9G8Z	4.9	±2%	1200mA	0.081	1608	Infotainment	50 MHz - 20 GHz
LQW18AN5N6C8Z	5.6	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN5N6G8Z	5.6	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N0C8Z	6	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N0G8Z	6	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N2C8Z	6.2	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N2G8Z	6.2	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N5C8Z	6.5	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N5G8Z	6.5	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8C8Z	6.8	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN6N8G8Z	6.8	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N2C8Z	7.2	±0.2nH	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N2G8Z	7.2	±2%	1900mA	0.04	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N5C8Z	7.5	±0.2nH	1500mA	0.048	1608	Infotainment	50 MHz - 20 GHz
LQW18AN7N5G8Z	7.5	±2%	1500mA	0.048	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N2C8Z	8.2	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N2G8Z	8.2	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N4C8Z	8.4	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N4G8Z	8.4	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N7C8Z	8.7	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN8N7G8Z	8.7	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N1C8Z	9.1	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N1G8Z	9.1	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N5C8Z	9.5	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N5G8Z	9.5	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N9C8Z	9.9	±0.2nH	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN9N9G8Z	9.9	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NG8Z	10	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN10NJ8Z	10	±5%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN11NG8Z	11	±2%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN11NJ8Z	11	±5%	1600mA	0.052	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NG8Z	12	±2%	1500mA	0.064	1608	Infotainment	50 MHz - 20 GHz
LQW18AN12NJ8Z	12	±5%	1500mA	0.064	1608	Infotainment	50 MHz - 20 GHz
LQW18AN13NG8Z	13	±2%	1500mA	0.064	1608	Infotainment	50 MHz - 20 GHz
LQW18AN13NJ8Z	13	±5%	1500mA	0.064	1608	Infotainment	50 MHz - 20 GHz
LQW18AN15NG8Z	15	±2%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN15NJ8Z	15	±5%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN16NG8Z	16	±2%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN16NJ8Z	16	±5%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN17NG8Z	17	±2%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN17NJ8Z	17	±5%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NG8Z	18	±2%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN18NJ8Z	18	±5%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN19NG8Z	19	±2%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN19NJ8Z	19	±5%	1400mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NG8Z	22	±2%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN22NJ8Z	22	±5%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN23NG8Z	23	±2%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN23NJ8Z	23	±5%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN24NG8Z	24	±2%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN24NJ8Z	24	±5%	1300mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AN25NG8Z	25	±2%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN25NJ8Z	25	±5%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NG8Z	27	±2%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN27NJ8Z	27	±5%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN28NG8Z	28	±2%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN28NJ8Z	28	±5%	1200mA	0.098	1608	Infotainment	50 MHz - 20 GHz
LQW18AN30NG8Z	30	±2%	1100mA	0.12	1608	Infotainment	50 MHz - 20 GHz
LQW18AN30NJ8Z	30	±5%	1100mA	0.12	1608	Infotainment	50 MHz - 20 GHz
LQW18AN31NG8Z	31	±2%	1100mA	0.11	1608	Infotainment	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18AN31NJ8Z	31	±5%	1100mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN33NG8Z	33	±2%	1100mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN33NJ8Z	33	±5%	1100mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AN34NG8Z	34	±2%	1050mA	0.15	1608	Infotainment	50 MHz - 20 GHz
LQW18AN34NJ8Z	34	±5%	1050mA	0.15	1608	Infotainment	50 MHz - 20 GHz
LQW18AN36NG8Z	36	±2%	910mA	0.2	1608	Infotainment	50 MHz - 20 GHz
LQW18AN36NJ8Z	36	±5%	910mA	0.2	1608	Infotainment	50 MHz - 20 GHz
LQW18AN37NG8Z	37	±2%	910mA	0.2	1608	Infotainment	50 MHz - 20 GHz
LQW18AN37NJ8Z	37	±5%	910mA	0.2	1608	Infotainment	50 MHz - 20 GHz
LQW18AN39NG8Z	39	±2%	1000mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN39NJ8Z	39	±5%	1000mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN41NG8Z	41	±2%	1000mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN41NJ8Z	41	±5%	1000mA	0.16	1608	Infotainment	50 MHz - 20 GHz
LQW18AN43NG8Z	43	±2%	840mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN43NJ8Z	43	±5%	840mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN44NG8Z	44	±2%	840mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN44NJ8Z	44	±5%	840mA	0.21	1608	Infotainment	50 MHz - 20 GHz
LQW18AN47NG8Z	47	±2%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN47NJ8Z	47	±5%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN48NG8Z	48	±2%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN48NJ8Z	48	±5%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN51NG8Z	51	±2%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN51NJ8Z	51	±5%	830mA	0.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AN52NG8Z	52	±2%	750mA	0.27	1608	Infotainment	50 MHz - 20 GHz
LQW18AN52NJ8Z	52	±5%	750mA	0.27	1608	Infotainment	50 MHz - 20 GHz
LQW18AN56NG8Z	56	±2%	770mA	0.26	1608	Infotainment	50 MHz - 20 GHz
LQW18AN56NJ8Z	56	±5%	770mA	0.26	1608	Infotainment	50 MHz - 20 GHz
LQW18AN58NG8Z	58	±2%	700mA	0.3	1608	Infotainment	50 MHz - 20 GHz
LQW18AN58NJ8Z	58	±5%	700mA	0.3	1608	Infotainment	50 MHz - 20 GHz
LQW18AN68NG8Z	68	±2%	630mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN68NJ8Z	68	±5%	630mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN69NG8Z	69	±2%	630mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN69NJ8Z	69	±5%	630mA	0.38	1608	Infotainment	50 MHz - 20 GHz
LQW18AN72NG8Z	72	±2%	560mA	0.47	1608	Infotainment	50 MHz - 20 GHz
LQW18AN72NJ8Z	72	±5%	560mA	0.47	1608	Infotainment	50 MHz - 20 GHz
LQW18AN73NG8Z	73	±2%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN73NJ8Z	73	±5%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN75NG8Z	75	±2%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN75NJ8Z	75	±5%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN78NG8Z	78	±2%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN78NJ8Z	78	±5%	590mA	0.41	1608	Infotainment	50 MHz - 20 GHz
LQW18AN82NG8Z	82	±2%	550mA	0.5	1608	Infotainment	50 MHz - 20 GHz
LQW18AN82NJ8Z	82	±5%	550mA	0.5	1608	Infotainment	50 MHz - 20 GHz
LQW18AN83NG8Z	83	±2%	550mA	0.5	1608	Infotainment	50 MHz - 20 GHz
LQW18AN83NJ8Z	83	±5%	550mA	0.5	1608	Infotainment	50 MHz - 20 GHz
LQW18AN91NG8Z	91	±2%	520mA	0.54	1608	Infotainment	50 MHz - 20 GHz
LQW18AN91NJ8Z	91	±5%	520mA	0.54	1608	Infotainment	50 MHz - 20 GHz
LQW18AN94NG8Z	94	±2%	490mA	0.63	1608	Infotainment	50 MHz - 20 GHz
LQW18AN94NJ8Z	94	±5%	490mA	0.63	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR10G8Z	100	±2%	490mA	0.63	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR10J8Z	100	±5%	490mA	0.63	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR11G8Z	110	±2%	450mA	0.7	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR11J8Z	110	±5%	450mA	0.7	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR12G8Z	120	±2%	450mA	0.72	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR12J8Z	120	±5%	450mA	0.72	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR15G8Z	150	±2%	420mA	0.87	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR15J8Z	150	±5%	420mA	0.87	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR18G8Z	180	±2%	310mA	1.65	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR18J8Z	180	±5%	310mA	1.65	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR20G8Z	200	±2%	290mA	1.74	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR20J8Z	200	±5%	290mA	1.74	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR21G8Z	210	±2%	280mA	1.98	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR21J8Z	210	±5%	280mA	1.98	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR22G8Z	220	±2%	280mA	2.08	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR22J8Z	220	±5%	280mA	2.08	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR25G8Z	250	±2%	250mA	2.28	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR25J8Z	250	±5%	250mA	2.28	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR27G8Z	270	±2%	260mA	2.42	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR27J8Z	270	±5%	260mA	2.42	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR30G8Z	300	±2%	220mA	3.12	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR30J8Z	300	±5%	220mA	3.12	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR33G8Z	330	±2%	190mA	3.84	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR33J8Z	330	±5%	190mA	3.84	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR36G8Z	360	±2%	190mA	3.98	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR36J8Z	360	±5%	190mA	3.98	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR39G8Z	390	±2%	190mA	4.23	1608	Infotainment	50 MHz - 20 GHz
LQW18ANR39J8Z	390	±5%	190mA	4.23	1608	Infotainment	50 MHz - 20 GHz
LQW18AS1N2C00	1.2	±0.2nH	1400mA	0.02	1608	General	50 MHz - 20 GHz
LQW18AS1N2J00	1.2	±5%	1400mA	0.02	1608	General	50 MHz - 20 GHz
LQW18AS1N6J00	1.6	±5%	700mA	0.03	1608	General	50 MHz - 20 GHz
LQW18AS1N8J00	1.8	±5%	700mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AS2N0J00	2	±5%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS3N3G00	3.3	±2%	700mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AS3N3J00	3.3	±5%	700mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AS3N6G00	3.6	±2%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS3N6J00	3.6	±5%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS3N9G00	3.9	±2%	700mA	0.08	1608	General	50 MHz - 20 GHz
LQW18AS3N9J00	3.9	±5%	700mA	0.08	1608	General	50 MHz - 20 GHz
LQW18AS4N3G00	4.3	±2%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS4N3J00	4.3	±5%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS4N7G00	4.7	±2%	700mA	0.116	1608	General	50 MHz - 20 GHz
LQW18AS4N7J00	4.7	±5%	700mA	0.116	1608	General	50 MHz - 20 GHz
LQW18AS5N1G00	5.1	±2%	700mA	0.14	1608	General	50 MHz - 20 GHz
LQW18AS5N1J00	5.1	±5%	700mA	0.14	1608	General	50 MHz - 20 GHz
LQW18AS5N6G00	5.6	±2%	700mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AS5N6J00	5.6	±5%	700mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AS6N8G00	6.8	±2%	700mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AS6N8J00	6.8	±5%	700mA	0.11	1608	General	50 MHz - 20 GHz
LQW18AS7N5G00	7.5	±2%	700mA	0.106	1608	General	50 MHz - 20 GHz
LQW18AS7N5J00	7.5	±5%	700mA	0.106	1608	General	50 MHz - 20 GHz
LQW18AS8N2G00	8.2	±2%	700mA	0.115	1608	General	50 MHz - 20 GHz
LQW18AS8N2J00	8.2	±5%	700mA	0.115	1608	General	50 MHz - 20 GHz
LQW18AS8N7G00	8.7	±2%	700mA	0.109	1608	General	50 MHz - 20 GHz
LQW18AS8N7J00	8.7	±5%	700mA	0.109	1608	General	50 MHz - 20 GHz
LQW18AS9N5G00	9.5	±2%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS9N5J00	9.5	±5%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS10NG00	10	±2%	700mA	0.13	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18AS10NJ00	10	±5%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS11NG00	11	±2%	700mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AS11NJ00	11	±5%	700mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AS12NG00	12	±2%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS12NJ00	12	±5%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS15NG00	15	±2%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS15NJ00	15	±5%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS16NG00	16	±2%	700mA	0.104	1608	General	50 MHz - 20 GHz
LQW18AS16NJ00	16	±5%	700mA	0.104	1608	General	50 MHz - 20 GHz
LQW18AS18NG00	18	±2%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS18NJ00	18	±5%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS22NG00	22	±2%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS22NJ00	22	±5%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS23NG00	23	±2%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS23NJ00	23	±5%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS24NG00	24	±2%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS24NJ00	24	±5%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS27NG00	27	±2%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS27NJ00	27	±5%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS30NG00	30	±2%	600mA	0.144	1608	General	50 MHz - 20 GHz
LQW18AS30NJ00	30	±5%	600mA	0.144	1608	General	50 MHz - 20 GHz
LQW18AS33NG00	33	±2%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS33NJ00	33	±5%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS36NG00	36	±2%	600mA	0.25	1608	General	5 MHz - 10 GHz
LQW18AS36NJ00	36	±5%	600mA	0.25	1608	General	5 MHz - 10 GHz
LQW18AS39NG00	39	±2%	600mA	0.25	1608	General	5 MHz - 10 GHz
LQW18AS39NJ00	39	±5%	600mA	0.25	1608	General	5 MHz - 10 GHz
LQW18AS43NG00	43	±2%	600mA	0.28	1608	General	5 MHz - 10 GHz
LQW18AS43NJ00	43	±5%	600mA	0.28	1608	General	5 MHz - 10 GHz
LQW18AS47NG00	47	±2%	600mA	0.28	1608	General	5 MHz - 10 GHz
LQW18AS47NJ00	47	±5%	600mA	0.28	1608	General	5 MHz - 10 GHz
LQW18AS51NG00	51	±2%	600mA	0.27	1608	General	5 MHz - 10 GHz
LQW18AS51NJ00	51	±5%	600mA	0.27	1608	General	5 MHz - 10 GHz
LQW18AS56NG00	56	±2%	600mA	0.31	1608	General	50 MHz - 20 GHz
LQW18AS56NJ00	56	±5%	600mA	0.31	1608	General	50 MHz - 20 GHz
LQW18AS68NG00	68	±2%	600mA	0.34	1608	General	50 MHz - 20 GHz
LQW18AS68NJ00	68	±5%	600mA	0.34	1608	General	50 MHz - 20 GHz
LQW18AS72NG00	72	±2%	400mA	0.49	1608	General	5 MHz - 10 GHz
LQW18AS72NJ00	72	±5%	400mA	0.49	1608	General	5 MHz - 10 GHz
LQW18AS82NG00	82	±2%	400mA	0.54	1608	General	50 MHz - 20 GHz
LQW18AS82NJ00	82	±5%	400mA	0.54	1608	General	50 MHz - 20 GHz
LQW18ASR10G00	100	±2%	400mA	0.58	1608	General	50 MHz - 20 GHz
LQW18ASR10J00	100	±5%	400mA	0.58	1608	General	50 MHz - 20 GHz
LQW18ASR11G00	110	±2%	300mA	0.61	1608	General	5 MHz - 10 GHz
LQW18ASR11J00	110	±5%	300mA	0.61	1608	General	5 MHz - 10 GHz
LQW18ASR12G00	120	±2%	300mA	0.65	1608	General	50 MHz - 20 GHz
LQW18ASR12J00	120	±5%	300mA	0.65	1608	General	50 MHz - 20 GHz
LQW18ASR15G00	150	±2%	280mA	0.92	1608	General	50 MHz - 20 GHz
LQW18ASR15J00	150	±5%	280mA	0.92	1608	General	50 MHz - 20 GHz
LQW18ASR18G00	180	±2%	240mA	1.25	1608	General	50 MHz - 20 GHz
LQW18ASR18J00	180	±5%	240mA	1.25	1608	General	50 MHz - 20 GHz
LQW18ASR20G00	200	±2%	200mA	1.98	1608	General	5 MHz - 10 GHz
LQW18ASR20J00	200	±5%	200mA	1.98	1608	General	5 MHz - 10 GHz
LQW18ASR21G00	210	±2%	200mA	2.06	1608	General	5 MHz - 10 GHz
LQW18ASR21J00	210	±5%	200mA	2.06	1608	General	5 MHz - 10 GHz
LQW18ASR22G00	220	±2%	200mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ASR22J00	220	±5%	200mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ASR25G00	250	±2%	120mA	3.55	1608	General	5 MHz - 10 GHz
LQW18ASR25J00	250	±5%	120mA	3.55	1608	General	5 MHz - 10 GHz
LQW18ASR27G00	270	±2%	170mA	2.3	1608	General	50 MHz - 20 GHz
LQW18ASR27J00	270	±5%	170mA	2.3	1608	General	50 MHz - 20 GHz
LQW18ASR33G00	330	±2%	100mA	3.89	1608	General	50 MHz - 20 GHz
LQW18ASR33J00	330	±5%	100mA	3.89	1608	General	50 MHz - 20 GHz
LQW18ASR39G00	390	±2%	100mA	4.35	1608	General	50 MHz - 20 GHz
LQW18ASR39J00	390	±5%	100mA	4.35	1608	General	50 MHz - 20 GHz
LQW18AS1N6J0C	1.6	±5%	700mA	0.03	1608	General	50 MHz - 20 GHz
LQW18AS3N3G0C	3.3	±2%	700mA	0.045	1608	General	50 MHz - 20 GHz
LQW18AS4N3G0C	4.3	±2%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS4N3J0C	4.3	±5%	700mA	0.063	1608	General	50 MHz - 20 GHz
LQW18AS5N6G0C	5.6	±2%	700mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AS5N6J0C	5.6	±5%	700mA	0.075	1608	General	50 MHz - 20 GHz
LQW18AS8N2G0C	8.2	±2%	700mA	0.115	1608	General	50 MHz - 20 GHz
LQW18AS8N2J0C	8.2	±5%	700mA	0.115	1608	General	50 MHz - 20 GHz
LQW18AS10NG0C	10	±2%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS10NJ0C	10	±5%	700mA	0.13	1608	General	50 MHz - 20 GHz
LQW18AS11NG0C	11	±2%	700mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AS11NJ0C	11	±5%	700mA	0.086	1608	General	50 MHz - 20 GHz
LQW18AS15NG0C	15	±2%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS15NJ0C	15	±5%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS16NG0C	16	±2%	700mA	0.104	1608	General	50 MHz - 20 GHz
LQW18AS16NJ0C	16	±5%	700mA	0.104	1608	General	50 MHz - 20 GHz
LQW18AS18NG0C	18	±2%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS18NJ0C	18	±5%	700mA	0.17	1608	General	50 MHz - 20 GHz
LQW18AS22NG0C	22	±2%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS22NJ0C	22	±5%	700mA	0.19	1608	General	50 MHz - 20 GHz
LQW18AS24NG0C	24	±2%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS24NJ0C	24	±5%	700mA	0.135	1608	General	50 MHz - 20 GHz
LQW18AS33NG0C	33	±2%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS33NJ0C	33	±5%	600mA	0.22	1608	General	50 MHz - 20 GHz
LQW18AS47NG0C	47	±2%	600mA	0.28	1608	General	5 MHz - 10 GHz
LQW18AS56NG0C	56	±2%	600mA	0.31	1608	General	50 MHz - 20 GHz
LQW18AS56NJ0C	56	±5%	600mA	0.31	1608	General	50 MHz - 20 GHz
LQW18AS68NG0C	68	±2%	600mA	0.34	1608	General	50 MHz - 20 GHz
LQW18AS68NJ0C	68	±5%	600mA	0.34	1608	General	50 MHz - 20 GHz
LQW18AS82NG0C	82	±2%	400mA	0.54	1608	General	50 MHz - 20 GHz
LQW18AS82NJ0C	82	±5%	400mA	0.54	1608	General	50 MHz - 20 GHz
LQW18ASR10G0C	100	±2%	400mA	0.58	1608	General	50 MHz - 20 GHz
LQW18ASR10J0C	100	±5%	400mA	0.58	1608	General	50 MHz - 20 GHz
LQW18ASR12G0C	120	±2%	300mA	0.65	1608	General	50 MHz - 20 GHz
LQW18ASR12J0C	120	±5%	300mA	0.65	1608	General	50 MHz - 20 GHz
LQW18ASR15G0C	150	±2%	280mA	0.92	1608	General	50 MHz - 20 GHz
LQW18ASR15J0C	150	±5%	280mA	0.92	1608	General	50 MHz - 20 GHz
LQW18ASR18G0C	180	±2%	240mA	1.4	1608	General	50 MHz - 20 GHz
LQW18ASR18J0C	180	±5%	240mA	1.4	1608	General	50 MHz - 20 GHz
LQW18ASR22G0C	220	±2%	200mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ASR22J0C	220	±5%	200mA	2.1	1608	General	50 MHz - 20 GHz
LQW18ASR27G0C	270	±2%	130mA	2.5	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18ASR27JOC	270	±5%	130mA	2.5	1608	General	50 MHz - 20 GHz
LQW18ASR33GOC	330	±2%	100mA	3.89	1608	General	50 MHz - 20 GHz
LQW18ASR33JOC	330	±5%	100mA	3.89	1608	General	50 MHz - 20 GHz
LQW18ASR39GOC	390	±2%	100mA	4.35	1608	General	50 MHz - 20 GHz
LQW18ASR39JOC	390	±5%	100mA	4.35	1608	General	50 MHz - 20 GHz
LQW18AS1N6J0Z	1.6	±5%	700mA	0.03	1608	Infotainment	50 MHz - 20 GHz
LQW18AS1N8J0Z	1.8	±5%	700mA	0.045	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N3G0Z	3.3	±2%	700mA	0.43	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N3J0Z	3.3	±5%	700mA	0.43	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N6G0Z	3.6	±2%	700mA	0.063	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N6J0Z	3.6	±5%	700mA	0.063	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N9G0Z	3.9	±2%	700mA	0.08	1608	Infotainment	50 MHz - 20 GHz
LQW18AS3N9J0Z	3.9	±5%	700mA	0.08	1608	Infotainment	50 MHz - 20 GHz
LQW18AS4N3G0Z	4.3	±2%	700mA	0.063	1608	Infotainment	50 MHz - 20 GHz
LQW18AS4N3J0Z	4.3	±5%	700mA	0.063	1608	Infotainment	50 MHz - 20 GHz
LQW18AS4N7G0Z	4.7	±2%	700mA	0.116	1608	Infotainment	50 MHz - 20 GHz
LQW18AS4N7J0Z	4.7	±5%	700mA	0.116	1608	Infotainment	50 MHz - 20 GHz
LQW18AS5N1G0Z	5.1	±2%	700mA	0.14	1608	Infotainment	50 MHz - 20 GHz
LQW18AS5N1J0Z	5.1	±5%	700mA	0.14	1608	Infotainment	50 MHz - 20 GHz
LQW18AS5N6G0Z	5.6	±2%	700mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AS5N6J0Z	5.6	±5%	700mA	0.075	1608	Infotainment	50 MHz - 20 GHz
LQW18AS6N8G0Z	6.8	±2%	700mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AS6N8J0Z	6.8	±5%	700mA	0.11	1608	Infotainment	50 MHz - 20 GHz
LQW18AS7N5G0Z	7.5	±2%	700mA	0.106	1608	Infotainment	50 MHz - 20 GHz
LQW18AS7N5J0Z	7.5	±5%	700mA	0.106	1608	Infotainment	50 MHz - 20 GHz
LQW18AS8N2G0Z	8.2	±2%	700mA	0.115	1608	Infotainment	50 MHz - 20 GHz
LQW18AS8N2J0Z	8.2	±5%	700mA	0.115	1608	Infotainment	50 MHz - 20 GHz
LQW18AS8N7G0Z	8.7	±2%	700mA	0.109	1608	Infotainment	50 MHz - 20 GHz
LQW18AS8N7J0Z	8.7	±5%	700mA	0.109	1608	Infotainment	50 MHz - 20 GHz
LQW18AS9N5G0Z	9.5	±2%	700mA	0.135	1608	Infotainment	50 MHz - 20 GHz
LQW18AS9N5J0Z	9.5	±5%	700mA	0.135	1608	Infotainment	50 MHz - 20 GHz
LQW18AS10NG0Z	10	±2%	700mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AS10NJ0Z	10	±5%	700mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AS11NG0Z	11	±2%	700mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AS11NJ0Z	11	±5%	700mA	0.086	1608	Infotainment	50 MHz - 20 GHz
LQW18AS12NG0Z	12	±2%	700mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AS12NJ0Z	12	±5%	700mA	0.13	1608	Infotainment	50 MHz - 20 GHz
LQW18AS15NG0Z	15	±2%	700mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AS15NJ0Z	15	±5%	700mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AS16NG0Z	16	±2%	700mA	0.104	1608	Infotainment	50 MHz - 20 GHz
LQW18AS16NJ0Z	16	±5%	700mA	0.104	1608	Infotainment	50 MHz - 20 GHz
LQW18AS18NG0Z	18	±2%	700mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AS18NJ0Z	18	±5%	700mA	0.17	1608	Infotainment	50 MHz - 20 GHz
LQW18AS22NG0Z	22	±2%	700mA	0.19	1608	Infotainment	50 MHz - 20 GHz
LQW18AS22NJ0Z	22	±5%	700mA	0.19	1608	Infotainment	50 MHz - 20 GHz
LQW18AS23NG0Z	23	±2%	700mA	0.19	1608	Infotainment	50 MHz - 20 GHz
LQW18AS23NJ0Z	23	±5%	700mA	0.19	1608	Infotainment	50 MHz - 20 GHz
LQW18AS24NG0Z	24	±2%	700mA	0.135	1608	Infotainment	50 MHz - 20 GHz
LQW18AS24NJ0Z	24	±5%	700mA	0.135	1608	Infotainment	50 MHz - 20 GHz
LQW18AS27NG0Z	27	±2%	600mA	0.22	1608	Infotainment	50 MHz - 20 GHz
LQW18AS27NJ0Z	27	±5%	600mA	0.22	1608	Infotainment	50 MHz - 20 GHz
LQW18AS30NG0Z	30	±2%	600mA	0.144	1608	Infotainment	50 MHz - 20 GHz
LQW18AS30NJ0Z	30	±5%	600mA	0.144	1608	Infotainment	50 MHz - 20 GHz
LQW18AS33NG0Z	33	±2%	600mA	0.22	1608	Infotainment	50 MHz - 20 GHz
LQW18AS33NJ0Z	33	±5%	600mA	0.22	1608	Infotainment	50 MHz - 20 GHz
LQW18AS36NG0Z	36	±2%	600mA	0.25	1608	Infotainment	5 MHz - 10 GHz
LQW18AS36NJ0Z	36	±5%	600mA	0.25	1608	Infotainment	5 MHz - 10 GHz
LQW18AS39NG0Z	39	±2%	600mA	0.25	1608	Infotainment	5 MHz - 10 GHz
LQW18AS39NJ0Z	39	±5%	600mA	0.25	1608	Infotainment	5 MHz - 10 GHz
LQW18AS43NG0Z	43	±2%	600mA	0.28	1608	Infotainment	5 MHz - 10 GHz
LQW18AS43NJ0Z	43	±5%	600mA	0.28	1608	Infotainment	5 MHz - 10 GHz
LQW18AS47NG0Z	47	±2%	600mA	0.28	1608	Infotainment	5 MHz - 10 GHz
LQW18AS47NJ0Z	47	±5%	600mA	0.28	1608	Infotainment	5 MHz - 10 GHz
LQW18AS51NG0Z	51	±2%	600mA	0.27	1608	Infotainment	5 MHz - 10 GHz
LQW18AS51NJ0Z	51	±5%	600mA	0.27	1608	Infotainment	5 MHz - 10 GHz
LQW18AS56NG0Z	56	±2%	600mA	0.31	1608	Infotainment	50 MHz - 20 GHz
LQW18AS56NJ0Z	56	±5%	600mA	0.31	1608	Infotainment	50 MHz - 20 GHz
LQW18AS68NG0Z	68	±2%	600mA	0.34	1608	Infotainment	50 MHz - 20 GHz
LQW18AS68NJ0Z	68	±5%	600mA	0.34	1608	Infotainment	50 MHz - 20 GHz
LQW18AS72NG0Z	72	±2%	400mA	0.49	1608	Infotainment	5 MHz - 10 GHz
LQW18AS72NJ0Z	72	±5%	400mA	0.49	1608	Infotainment	5 MHz - 10 GHz
LQW18AS82NG0Z	82	±2%	400mA	0.54	1608	Infotainment	50 MHz - 20 GHz
LQW18AS82NJ0Z	82	±5%	400mA	0.54	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR10G0Z	100	±2%	400mA	0.58	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR10J0Z	100	±5%	400mA	0.58	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR11G0Z	110	±2%	300mA	0.61	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR11J0Z	110	±5%	300mA	0.61	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR12G0Z	120	±2%	300mA	0.65	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR12J0Z	120	±5%	300mA	0.65	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR15G0Z	150	±2%	280mA	0.92	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR15J0Z	150	±5%	280mA	0.92	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR18G0Z	180	±2%	240mA	1.25	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR18J0Z	180	±5%	240mA	1.25	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR20G0Z	200	±2%	200mA	1.98	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR20J0Z	200	±5%	200mA	1.98	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR21G0Z	210	±2%	200mA	2.06	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR21J0Z	210	±5%	200mA	2.06	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR22G0Z	220	±2%	200mA	2.1	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR22J0Z	220	±5%	200mA	2.1	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR25G0Z	250	±2%	120mA	3.55	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR25J0Z	250	±5%	120mA	3.55	1608	Infotainment	5 MHz - 10 GHz
LQW18ASR27G0Z	270	±2%	170mA	2.3	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR27J0Z	270	±5%	170mA	2.3	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR33G0Z	330	±2%	100mA	3.89	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR33J0Z	330	±5%	100mA	3.89	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR39G0Z	390	±2%	100mA	4.35	1608	Infotainment	50 MHz - 20 GHz
LQW18ASR39J0Z	390	±5%	100mA	4.35	1608	Infotainment	50 MHz - 20 GHz
LQW18CA32NJ00	32	±5%	2200mA	0.03	1608	General	50 MHz - 20 GHz
LQW18CA56NJ00	56	±5%	1850mA	0.04	1608	General	50 MHz - 20 GHz
LQW18CA85NJ00	85	±5%	1650mA	0.048	1608	General	50 MHz - 20 GHz
LQW18CAR12J00	120	±5%	1500mA	0.058	1608	General	50 MHz - 20 GHz
LQW18CAR16J00	160	±5%	1300mA	0.075	1608	General	50 MHz - 20 GHz
LQW18CAR21J00	210	±5%	1050mA	0.115	1608	General	50 MHz - 20 GHz
LQW18CAR27J00	270	±5%	900mA	0.15	1608	General	50 MHz - 20 GHz
LQW18CAR33J00	330	±5%	780mA	0.2	1608	General	50 MHz - 20 GHz
LQW18CAR40J00	400	±5%	680mA	0.26	1608	General	50 MHz - 20 GHz
LQW18CAR48J00	480	±5%	580mA	0.35	1608	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW18CAR58J00	580	±5%	450mA	0.46	1608	General	50 MHz - 20 GHz
LQW18CN4N9D00	4.9	±0.5nH	2600mA	0.015	1608	General	10 MHz - 20 GHz
LQW18CN15NJ00	15	±5%	2200mA	0.025	1608	General	10 MHz - 20 GHz
LQW18CN33NJ00	33	±5%	1700mA	0.035	1608	General	10 MHz - 20 GHz
LQW18CN55NJ00	55	±5%	1500mA	0.045	1608	General	10 MHz - 20 GHz
LQW18CN85NJ00	85	±5%	1400mA	0.06	1608	General	10 MHz - 20 GHz
LQW18CNR10K00	100	±10%	1000mA	0.1	1608	General	10 MHz - 20 GHz
LQW18CNR12J00	120	±5%	1100mA	0.085	1608	General	10 MHz - 20 GHz
LQW18CNR16J00	160	±5%	1000mA	0.1	1608	General	10 MHz - 20 GHz
LQW18CNR21J00	210	±5%	800mA	0.15	1608	General	10 MHz - 20 GHz
LQW18CNR27J00	270	±5%	750mA	0.16	1608	General	10 MHz - 20 GHz
LQW18CNR33J00	330	±5%	630mA	0.25	1608	General	10 MHz - 20 GHz
LQW18CNR39J00	390	±5%	620mA	0.28	1608	General	10 MHz - 20 GHz
LQW18CNR47J00	470	±5%	500mA	0.45	1608	General	10 MHz - 20 GHz
LQW18CNR56J00	560	±5%	450mA	0.48	1608	General	10 MHz - 20 GHz
LQW18CNR65J00	650	±5%	430mA	0.52	1608	General	10 MHz - 20 GHz
LQW18CN4N9D0H	4.9	±0.5nH	2600mA	0.015	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CN15NJ0H	15	±5%	2200mA	0.025	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CN33NJ0H	33	±5%	1700mA	0.035	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CN55NJ0H	55	±5%	1500mA	0.045	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CN85NJ0H	85	±5%	1400mA	0.06	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR10K0H	100	±10%	1000mA	0.1	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR12J0H	120	±5%	1100mA	0.085	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR16J0H	160	±5%	1000mA	0.1	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR21J0H	210	±5%	800mA	0.15	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR27J0H	270	±5%	750mA	0.16	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR33J0H	330	±5%	630mA	0.25	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR39J0H	390	±5%	620mA	0.28	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR47J0H	470	±5%	500mA	0.45	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR56J0H	560	±5%	450mA	0.48	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CNR65J0H	650	±5%	430mA	0.52	1608	Powertrain/Safety	10 MHz - 20 GHz
LQW18CN4N9D0Z	4.9	±0.5nH	2600mA	0.015	1608	Infotainment	10 MHz - 20 GHz
LQW18CN15NJ0Z	15	±5%	2200mA	0.025	1608	Infotainment	10 MHz - 20 GHz
LQW18CN33NJ0Z	33	±5%	1700mA	0.035	1608	Infotainment	10 MHz - 20 GHz
LQW18CN55NJ0Z	55	±5%	1500mA	0.045	1608	Infotainment	10 MHz - 20 GHz
LQW18CN85NJ0Z	85	±5%	1400mA	0.06	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR10K0Z	100	±10%	1000mA	0.1	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR12J0Z	120	±5%	1100mA	0.085	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR16J0Z	160	±5%	1000mA	0.1	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR21J0Z	210	±5%	800mA	0.15	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR27J0Z	270	±5%	750mA	0.16	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR33J0Z	330	±5%	630mA	0.25	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR39J0Z	390	±5%	620mA	0.28	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR47J0Z	470	±5%	500mA	0.45	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR56J0Z	560	±5%	450mA	0.48	1608	Infotainment	10 MHz - 20 GHz
LQW18CNR65J0Z	650	±5%	430mA	0.52	1608	Infotainment	10 MHz - 20 GHz
LQW18CN30NJL0	30	±5%	1350mA	0.05	1608	General	1 MHz - 20 GHz
LQW18CN51NJL0	51	±5%	1150mA	0.066	1608	General	1 MHz - 20 GHz
LQW18CN75NJL0	75	±5%	1050mA	0.082	1608	General	1 MHz - 20 GHz
LQW18CNR12JL0	115	±5%	950mA	0.1	1608	General	1 MHz - 20 GHz
LQW18CNR15JL0	150	±5%	900mA	0.12	1608	General	1 MHz - 20 GHz
LQW18CNR24JL0	240	±5%	770mA	0.15	1608	General	1 MHz - 20 GHz
LQW18CNR30JL0	300	±5%	650mA	0.19	1608	General	1 MHz - 20 GHz
LQW18CNR43JL0	430	±5%	500mA	0.33	1608	General	1 MHz - 20 GHz
LQW18CNR51JL0	510	±5%	430mA	0.45	1608	General	1 MHz - 20 GHz
LQW18CNR59JL0	590	±5%	420mA	0.48	1608	General	1 MHz - 20 GHz
LQW18FT1R55K0H	550	±10%	800mA	0.19	1608	Powertrain/Safety	50 kHz - 20 GHz
LQW18FT1R2K0H	1200	±10%	560mA	0.37	1608	Powertrain/Safety	50 kHz - 20 GHz
LQW18FT1R5K0H	1500	±10%	530mA	0.42	1608	Powertrain/Safety	50 kHz - 20 GHz
LQW18FT2R2K0H	2200	±10%	390mA	0.77	1608	Powertrain/Safety	50 kHz - 20 GHz
LQW21FTR47M0H	470	±20%	1100mA	0.05	2012	Powertrain/Safety	1 MHz - 20 GHz
LQW21FTR82M0H	820	±20%	800mA	0.09	2012	Powertrain/Safety	1 MHz - 20 GHz
LQW21FT1R0M0H	1000	±20%	700mA	0.13	2012	Powertrain/Safety	1 MHz - 20 GHz
LQW21FT1R5M0H	1500	±20%	550mA	0.18	2012	Powertrain/Safety	1 MHz - 20 GHz
LQW21FT2R0M0H	2000	±20%	450mA	0.29	2012	Powertrain/Safety	1 MHz - 20 GHz
LQW2BAN3N2J00	3.2	±5%	3800mA	0.02	2015	General	50 MHz - 20 GHz
LQW2BAN3N6J00	3.6	±5%	2000mA	0.05	2015	General	50 MHz - 20 GHz
LQW2BAN6N8J00	6.8	±5%	3000mA	0.03	2015	General	50 MHz - 20 GHz
LQW2BAN7N5J00	7.5	±5%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN8N2G00	8.2	±2%	1500mA	0.09	2015	General	50 MHz - 20 GHz
LQW2BAN8N2J00	8.2	±5%	1500mA	0.09	2015	General	50 MHz - 20 GHz
LQW2BAN11NG00	11	±2%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN11NJ00	11	±5%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN12NG00	12	±2%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN12NJ00	12	±5%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN13NG00	13	±2%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN13NJ00	13	±5%	2400mA	0.04	2015	General	50 MHz - 20 GHz
LQW2BAN15NG00	15	±2%	1500mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN15NJ00	15	±5%	1500mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN18NG00	18	±2%	2200mA	0.05	2015	General	50 MHz - 20 GHz
LQW2BAN18NJ00	18	±5%	2200mA	0.05	2015	General	50 MHz - 20 GHz
LQW2BAN20NG00	20	±2%	2200mA	0.05	2015	General	50 MHz - 20 GHz
LQW2BAN20NJ00	20	±5%	2200mA	0.05	2015	General	50 MHz - 20 GHz
LQW2BAN22NG00	22	±2%	1900mA	0.07	2015	General	50 MHz - 20 GHz
LQW2BAN22NJ00	22	±5%	1900mA	0.07	2015	General	50 MHz - 20 GHz
LQW2BAN24NG00	24	±2%	1400mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAN24NJ00	24	±5%	1400mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAN27NG00	27	±2%	2000mA	0.07	2015	General	50 MHz - 20 GHz
LQW2BAN27NJ00	27	±5%	2000mA	0.07	2015	General	50 MHz - 20 GHz
LQW2BAN30NG00	30	±2%	2000mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN30NJ00	30	±5%	2000mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN33NG00	33	±2%	1500mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN33NJ00	33	±5%	1500mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN36NG00	36	±2%	1900mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN36NJ00	36	±5%	1900mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN39NG00	39	±2%	1900mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN39NJ00	39	±5%	1900mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAN43NG00	43	±2%	1550mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN43NJ00	43	±5%	1550mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN47NG00	47	±2%	1250mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAN47NJ00	47	±5%	1250mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAN51NG00	51	±2%	1800mA	0.11	2015	General	50 MHz - 20 GHz
LQW2BAN51NJ00	51	±5%	1800mA	0.11	2015	General	50 MHz - 20 GHz
LQW2BAN56NG00	56	±2%	1250mA	0.18	2015	General	50 MHz - 20 GHz
LQW2BAN56NJ00	56	±5%	1250mA	0.18	2015	General	50 MHz - 20 GHz
LQW2BAN62NG00	62	±2%	1650mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAN62NJ00	62	±5%	1650mA	0.12	2015	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW2BAN68NG00	68	±2%	1250mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAN68NJ00	68	±5%	1250mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAN75NG00	75	±2%	1100mA	0.28	2015	General	50 MHz - 20 GHz
LQW2BAN75NJ00	75	±5%	1100mA	0.28	2015	General	50 MHz - 20 GHz
LQW2BAN82NG00	82	±2%	1200mA	0.24	2015	General	50 MHz - 20 GHz
LQW2BAN82NJ00	82	±5%	1200mA	0.24	2015	General	50 MHz - 20 GHz
LQW2BAN91NG00	91	±2%	1300mA	0.21	2015	General	50 MHz - 20 GHz
LQW2BAN91NJ00	91	±5%	1300mA	0.21	2015	General	50 MHz - 20 GHz
LQW2BANR10G00	100	±2%	1050mA	0.35	2015	General	50 MHz - 20 GHz
LQW2BANR10J00	100	±5%	1050mA	0.35	2015	General	50 MHz - 20 GHz
LQW2BANR11G00	110	±2%	970mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BANR11J00	110	±5%	970mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BANR12G00	120	±2%	970mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BANR12J00	120	±5%	970mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BANR13G00	130	±2%	950mA	0.42	2015	General	50 MHz - 20 GHz
LQW2BANR13J00	130	±5%	950mA	0.42	2015	General	50 MHz - 20 GHz
LQW2BANR15G00	150	±2%	930mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BANR15J00	150	±5%	930mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BANR16G00	160	±2%	930mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BANR16J00	160	±5%	930mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BANR18G00	180	±2%	800mA	0.58	2015	General	50 MHz - 20 GHz
LQW2BANR18J00	180	±5%	800mA	0.58	2015	General	50 MHz - 20 GHz
LQW2BANR20G00	200	±2%	750mA	0.63	2015	General	50 MHz - 20 GHz
LQW2BANR20J00	200	±5%	750mA	0.63	2015	General	50 MHz - 20 GHz
LQW2BAS2N7J00	2.7	±5%	910mA	0.03	2015	General	50 MHz - 20 GHz
LQW2BAS2N8J00	2.8	±5%	800mA	0.06	2015	General	50 MHz - 20 GHz
LQW2BAS3N0J00	3	±5%	800mA	0.06	2015	General	50 MHz - 20 GHz
LQW2BAS5N6J00	5.6	±5%	600mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAS6N0J00	6	±5%	600mA	0.03	2015	General	50 MHz - 20 GHz
LQW2BAS6N8J00	6.8	±5%	600mA	0.11	2015	General	50 MHz - 20 GHz
LQW2BAS7N5J00	7.5	±5%	600mA	0.14	2015	General	50 MHz - 20 GHz
LQW2BAS8N2G00	8.2	±2%	600mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAS8N2J00	8.2	±5%	600mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAS10NG00	10	±2%	600mA	0.1	2015	General	50 MHz - 20 GHz
LQW2BAS10NJ00	10	±5%	600mA	0.1	2015	General	50 MHz - 20 GHz
LQW2BAS12NG00	12	±2%	600mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAS12NJ00	12	±5%	600mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAS15NG00	15	±2%	600mA	0.17	2015	General	50 MHz - 20 GHz
LQW2BAS15NJ00	15	±5%	600mA	0.17	2015	General	50 MHz - 20 GHz
LQW2BAS18NG00	18	±2%	600mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAS18NJ00	18	±5%	600mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAS22NG00	22	±2%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS22NJ00	22	±5%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS24NG00	24	±2%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS24NJ00	24	±5%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS27NG00	27	±2%	500mA	0.25	2015	General	50 MHz - 20 GHz
LQW2BAS27NJ00	27	±5%	500mA	0.25	2015	General	50 MHz - 20 GHz
LQW2BAS33NG00	33	±2%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS33NJ00	33	±5%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS36NG00	36	±2%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS36NJ00	36	±5%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS39NG00	39	±2%	500mA	0.29	2015	General	50 MHz - 20 GHz
LQW2BAS39NJ00	39	±5%	500mA	0.29	2015	General	50 MHz - 20 GHz
LQW2BAS43NG00	43	±2%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS43NJ00	43	±5%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS47NG00	47	±2%	500mA	0.31	2015	General	50 MHz - 20 GHz
LQW2BAS47NJ00	47	±5%	500mA	0.31	2015	General	50 MHz - 20 GHz
LQW2BAS56NG00	56	±2%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS56NJ00	56	±5%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS68NG00	68	±2%	500mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BAS68NJ00	68	±5%	500mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BAS82NG00	82	±2%	400mA	0.42	2015	General	50 MHz - 20 GHz
LQW2BAS82NJ00	82	±5%	400mA	0.42	2015	General	50 MHz - 20 GHz
LQW2BAS91NG00	91	±2%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BAS91NJ00	91	±5%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR10G00	100	±2%	400mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BASR10J00	100	±5%	400mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BASR11G00	110	±2%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR11J00	110	±5%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR12G00	120	±2%	400mA	0.51	2015	General	50 MHz - 20 GHz
LQW2BASR12J00	120	±5%	400mA	0.51	2015	General	50 MHz - 20 GHz
LQW2BASR15G00	150	±2%	400mA	0.56	2015	General	50 MHz - 20 GHz
LQW2BASR15J00	150	±5%	400mA	0.56	2015	General	50 MHz - 20 GHz
LQW2BASR18G00	180	±2%	400mA	0.64	2015	General	50 MHz - 20 GHz
LQW2BASR18J00	180	±5%	400mA	0.64	2015	General	50 MHz - 20 GHz
LQW2BASR22G00	220	±2%	400mA	0.7	2015	General	50 MHz - 20 GHz
LQW2BASR22J00	220	±5%	400mA	0.7	2015	General	50 MHz - 20 GHz
LQW2BASR24G00	240	±2%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR24J00	240	±5%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR27G00	270	±2%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR27J00	270	±5%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR33G00	330	±2%	310mA	1.4	2015	General	50 MHz - 20 GHz
LQW2BASR33J00	330	±5%	310mA	1.4	2015	General	50 MHz - 20 GHz
LQW2BASR39J00	390	±5%	290mA	1.5	2015	General	50 MHz - 20 GHz
LQW2BASR47J00	470	±5%	250mA	1.76	2015	General	50 MHz - 20 GHz
LQW2BASR56J00	560	±5%	230mA	1.9	2015	General	50 MHz - 20 GHz
LQW2BASR68J00	680	±5%	190mA	2.2	2015	General	50 MHz - 20 GHz
LQW2BASR82J00	820	±5%	180mA	2.35	2015	General	50 MHz - 20 GHz
LQW2BAS1R0J00	1000	±5%	170mA	2.4	2015	General	50 MHz - 20 GHz
LQW2BAS2N7J0C	2.7	±5%	910mA	0.03	2015	General	50 MHz - 20 GHz
LQW2BAS2N8J0C	2.8	±5%	800mA	0.06	2015	General	50 MHz - 20 GHz
LQW2BAS3N0J0C	3	±5%	800mA	0.06	2015	General	50 MHz - 20 GHz
LQW2BAS5N6J0C	5.6	±5%	600mA	0.08	2015	General	50 MHz - 20 GHz
LQW2BAS6N0J0C	6	±5%	600mA	0.03	2015	General	50 MHz - 20 GHz
LQW2BAS6N8J0C	6.8	±5%	600mA	0.11	2015	General	50 MHz - 20 GHz
LQW2BAS7N5J0C	7.5	±5%	600mA	0.14	2015	General	50 MHz - 20 GHz
LQW2BAS8N2G0C	8.2	±2%	600mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAS8N2J0C	8.2	±5%	600mA	0.12	2015	General	50 MHz - 20 GHz
LQW2BAS10NG0C	10	±2%	600mA	0.1	2015	General	50 MHz - 20 GHz
LQW2BAS10NJ0C	10	±5%	600mA	0.1	2015	General	50 MHz - 20 GHz
LQW2BAS12NG0C	12	±2%	600mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAS12NJ0C	12	±5%	600mA	0.15	2015	General	50 MHz - 20 GHz
LQW2BAS15NG0C	15	±2%	600mA	0.17	2015	General	50 MHz - 20 GHz
LQW2BAS15NJ0C	15	±5%	600mA	0.17	2015	General	50 MHz - 20 GHz
LQW2BAS18NG0C	18	±2%	600mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAS18NJ0C	18	±5%	600mA	0.2	2015	General	50 MHz - 20 GHz
LQW2BAS22NG0C	22	±2%	500mA	0.22	2015	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW2BAS22NJOC	22	±5%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS24NGOC	24	±2%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS24NJOC	24	±5%	500mA	0.22	2015	General	50 MHz - 20 GHz
LQW2BAS27NGOC	27	±2%	500mA	0.25	2015	General	50 MHz - 20 GHz
LQW2BAS27NJOC	27	±5%	500mA	0.25	2015	General	50 MHz - 20 GHz
LQW2BAS33NGOC	33	±2%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS33NJOC	33	±5%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS36NGOC	36	±2%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS36NJOC	36	±5%	500mA	0.27	2015	General	50 MHz - 20 GHz
LQW2BAS39NGOC	39	±2%	500mA	0.29	2015	General	50 MHz - 20 GHz
LQW2BAS39NJOC	39	±5%	500mA	0.29	2015	General	50 MHz - 20 GHz
LQW2BAS43NGOC	43	±2%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS43NJOC	43	±5%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS47NGOC	47	±2%	500mA	0.31	2015	General	50 MHz - 20 GHz
LQW2BAS47NJOC	47	±5%	500mA	0.31	2015	General	50 MHz - 20 GHz
LQW2BAS56NGOC	56	±2%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS56NJOC	56	±5%	500mA	0.34	2015	General	50 MHz - 20 GHz
LQW2BAS68NGOC	68	±2%	500mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BAS68NJOC	68	±5%	500mA	0.38	2015	General	50 MHz - 20 GHz
LQW2BAS82NGOC	82	±2%	400mA	0.25	2015	General	50 MHz - 20 GHz
LQW2BAS82NJOC	82	±5%	400mA	0.42	2015	General	50 MHz - 20 GHz
LQW2BAS91NGOC	91	±2%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BAS91NJOC	91	±5%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR10GOC	100	±2%	400mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BASR10JOC	100	±5%	400mA	0.46	2015	General	50 MHz - 20 GHz
LQW2BASR11GOC	110	±2%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR11JOC	110	±5%	400mA	0.48	2015	General	50 MHz - 20 GHz
LQW2BASR12GOC	120	±2%	400mA	0.51	2015	General	50 MHz - 20 GHz
LQW2BASR12JOC	120	±5%	400mA	0.51	2015	General	50 MHz - 20 GHz
LQW2BASR15GOC	150	±2%	400mA	0.56	2015	General	50 MHz - 20 GHz
LQW2BASR15JOC	150	±5%	400mA	0.56	2015	General	50 MHz - 20 GHz
LQW2BASR18GOC	180	±2%	400mA	0.64	2015	General	50 MHz - 20 GHz
LQW2BASR18JOC	180	±5%	400mA	0.64	2015	General	50 MHz - 20 GHz
LQW2BASR22GOC	220	±2%	400mA	0.7	2015	General	50 MHz - 20 GHz
LQW2BASR22JOC	220	±5%	400mA	0.7	2015	General	50 MHz - 20 GHz
LQW2BASR24GOC	240	±2%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR24JOC	240	±5%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR27GOC	270	±2%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR27JOC	270	±5%	350mA	1	2015	General	50 MHz - 20 GHz
LQW2BASR33GOC	330	±2%	310mA	1.4	2015	General	50 MHz - 20 GHz
LQW2BASR33JOC	330	±5%	310mA	1.4	2015	General	50 MHz - 20 GHz
LQW2BASR39JOC	390	±5%	290mA	1.5	2015	General	50 MHz - 20 GHz
LQW2BASR47JOC	470	±5%	250mA	1.76	2015	General	50 MHz - 20 GHz
LQW2BASR50JOC	500	±5%	200mA	3.2	2015	General	50 MHz - 20 GHz
LQW2BASR56JOC	560	±5%	230mA	1.9	2015	General	50 MHz - 20 GHz
LQW2BASR68JOC	680	±5%	190mA	2.2	2015	General	50 MHz - 20 GHz
LQW2BASR82JOC	820	±5%	180mA	2.35	2015	General	50 MHz - 20 GHz
LQW2BAS1R0JOC	1000	±5%	170mA	2.4	2015	General	50 MHz - 20 GHz
LQW2UAS12NG00	12	±2%	1000mA	0.09	2520	General	50 MHz - 20 GHz
LQW2UAS12NJ00	12	±5%	1000mA	0.09	2520	General	50 MHz - 20 GHz
LQW2UAS18NG00	18	±2%	1000mA	0.11	2520	General	50 MHz - 20 GHz
LQW2UAS18NJ00	18	±5%	1000mA	0.11	2520	General	50 MHz - 20 GHz
LQW2UAS22NF00	22	±1%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS22NG00	22	±2%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS22NJ00	22	±5%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS27NG00	27	±2%	1000mA	0.13	2520	General	50 MHz - 20 GHz
LQW2UAS27NJ00	27	±5%	1000mA	0.13	2520	General	50 MHz - 20 GHz
LQW2UAS33NF00	33	±1%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS33NG00	33	±2%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS33NJ00	33	±5%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS39NF00	39	±1%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS39NG00	39	±2%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS39NJ00	39	±5%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS47NF00	47	±1%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS47NG00	47	±2%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS47NJ00	47	±5%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS56NF00	56	±1%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS56NG00	56	±2%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS56NJ00	56	±5%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS68NF00	68	±1%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS68NG00	68	±2%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS68NJ00	68	±5%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS82NF00	82	±1%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UAS82NG00	82	±2%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UAS82NJ00	82	±5%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UASR10F00	100	±1%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR10G00	100	±2%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR10J00	100	±5%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR12F00	120	±1%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR12G00	120	±2%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR12J00	120	±5%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR15F00	150	±1%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR15G00	150	±2%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR15J00	150	±5%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR18F00	180	±1%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR18G00	180	±2%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR18J00	180	±5%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR22F00	220	±1%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR22G00	220	±2%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR22J00	220	±5%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR27F00	270	±1%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR27G00	270	±2%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR27J00	270	±5%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR33F00	330	±1%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR33G00	330	±2%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR33J00	330	±5%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR39F00	390	±1%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR39G00	390	±2%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR39J00	390	±5%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR47F00	470	±1%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR47G00	470	±2%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR47J00	470	±5%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR56F00	560	±1%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR56G00	560	±2%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR56J00	560	±5%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR62F00	620	±1%	300mA	1.4	2520	General	50 MHz - 20 GHz
LQW2UASR62G00	620	±2%	300mA	1.4	2520	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW2UASR62J00	620	±5%	300mA	1.4	2520	General	50 MHz - 20 GHz
LQW2UASR68F00	680	±1%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR68G00	680	±2%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR68J00	680	±5%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR75F00	750	±1%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR75G00	750	±2%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR75J00	750	±5%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR82F00	820	±1%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR82G00	820	±2%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR82J00	820	±5%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR91F00	910	±1%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UASR91G00	910	±2%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UASR91J00	910	±5%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UAS1R0F00	1000	±1%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R0G00	1000	±2%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R0J00	1000	±5%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R2J00	1200	±5%	310mA	2	2520	General	50 MHz - 20 GHz
LQW2UAS1R5J00	1500	±5%	330mA	2.3	2520	General	50 MHz - 20 GHz
LQW2UAS1R8J00	1800	±5%	300mA	2.6	2520	General	50 MHz - 20 GHz
LQW2UAS2R2J00	2200	±5%	280mA	2.8	2520	General	50 MHz - 20 GHz
LQW2UAS2R7J00	2700	±5%	290mA	3.2	2520	General	50 MHz - 20 GHz
LQW2UAS3R3J00	3300	±5%	290mA	3.4	2520	General	50 MHz - 20 GHz
LQW2UAS3R9J00	3900	±5%	260mA	3.6	2520	General	50 MHz - 20 GHz
LQW2UAS4R7J00	4700	±5%	260mA	4	2520	General	50 MHz - 20 GHz
LQW2UAS12NG0C	12	±2%	1000mA	0.09	2520	General	50 MHz - 20 GHz
LQW2UAS12NJ0C	12	±5%	1000mA	0.09	2520	General	50 MHz - 20 GHz
LQW2UAS18NG0C	18	±2%	1000mA	0.11	2520	General	50 MHz - 20 GHz
LQW2UAS18NJ0C	18	±5%	1000mA	0.11	2520	General	50 MHz - 20 GHz
LQW2UAS22NF0C	22	±1%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS22NG0C	22	±2%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS22NJ0C	22	±5%	1000mA	0.12	2520	General	50 MHz - 20 GHz
LQW2UAS27NG0C	27	±2%	1000mA	0.13	2520	General	50 MHz - 20 GHz
LQW2UAS27NJ0C	27	±5%	1000mA	0.13	2520	General	50 MHz - 20 GHz
LQW2UAS33NF0C	33	±1%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS33NG0C	33	±2%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS33NJ0C	33	±5%	1000mA	0.14	2520	General	50 MHz - 20 GHz
LQW2UAS39NF0C	39	±1%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS39NG0C	39	±2%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS39NJ0C	39	±5%	1000mA	0.15	2520	General	50 MHz - 20 GHz
LQW2UAS47NF0C	47	±1%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS47NG0C	47	±2%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS47NJ0C	47	±5%	1000mA	0.16	2520	General	50 MHz - 20 GHz
LQW2UAS56NF0C	56	±1%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS56NG0C	56	±2%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS56NJ0C	56	±5%	1000mA	0.18	2520	General	50 MHz - 20 GHz
LQW2UAS68NF0C	68	±1%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS68NG0C	68	±2%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS68NJ0C	68	±5%	1000mA	0.2	2520	General	50 MHz - 20 GHz
LQW2UAS82NF0C	82	±1%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UAS82NG0C	82	±2%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UAS82NJ0C	82	±5%	1000mA	0.22	2520	General	50 MHz - 20 GHz
LQW2UASR10F0C	100	±1%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR10G0C	100	±2%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR10J0C	100	±5%	650mA	0.56	2520	General	50 MHz - 20 GHz
LQW2UASR12F0C	120	±1%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR12G0C	120	±2%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR12J0C	120	±5%	650mA	0.63	2520	General	50 MHz - 20 GHz
LQW2UASR15F0C	150	±1%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR15G0C	150	±2%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR15J0C	150	±5%	580mA	0.7	2520	General	50 MHz - 20 GHz
LQW2UASR18F0C	180	±1%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR18G0C	180	±2%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR18J0C	180	±5%	620mA	0.77	2520	General	50 MHz - 20 GHz
LQW2UASR22F0C	220	±1%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR22G0C	220	±2%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR22J0C	220	±5%	500mA	0.84	2520	General	50 MHz - 20 GHz
LQW2UASR27F0C	270	±1%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR27G0C	270	±2%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR27J0C	270	±5%	500mA	0.91	2520	General	50 MHz - 20 GHz
LQW2UASR33F0C	330	±1%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR33G0C	330	±2%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR33J0C	330	±5%	450mA	1.05	2520	General	50 MHz - 20 GHz
LQW2UASR39F0C	390	±1%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR39G0C	390	±2%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR39J0C	390	±5%	470mA	1.12	2520	General	50 MHz - 20 GHz
LQW2UASR47F0C	470	±1%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR47G0C	470	±2%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR47J0C	470	±5%	470mA	1.19	2520	General	50 MHz - 20 GHz
LQW2UASR56F0C	560	±1%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR56G0C	560	±2%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR56J0C	560	±5%	400mA	1.33	2520	General	50 MHz - 20 GHz
LQW2UASR62F0C	620	±1%	300mA	1.4	2520	General	50 MHz - 20 GHz
LQW2UASR62G0C	620	±2%	300mA	1.4	2520	General	50 MHz - 20 GHz
LQW2UASR62J0C	620	±5%	300mA	1.4	2520	General	50 MHz - 20 GHz
LQW2UASR68F0C	680	±1%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR68G0C	680	±2%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR68J0C	680	±5%	400mA	1.47	2520	General	50 MHz - 20 GHz
LQW2UASR75F0C	750	±1%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR75G0C	750	±2%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR75J0C	750	±5%	360mA	1.54	2520	General	50 MHz - 20 GHz
LQW2UASR82F0C	820	±1%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR82G0C	820	±2%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR82J0C	820	±5%	400mA	1.61	2520	General	50 MHz - 20 GHz
LQW2UASR91F0C	910	±1%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UASR91G0C	910	±2%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UASR91J0C	910	±5%	380mA	1.68	2520	General	50 MHz - 20 GHz
LQW2UAS1R0F0C	1000	±1%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R0G0C	1000	±2%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R0J0C	1000	±5%	370mA	1.75	2520	General	50 MHz - 20 GHz
LQW2UAS1R2F0C	1200	±1%	310mA	2	2520	General	50 MHz - 20 GHz
LQW2UAS1R2G0C	1200	±2%	310mA	2	2520	General	50 MHz - 20 GHz
LQW2UAS1R2J0C	1200	±5%	310mA	2	2520	General	50 MHz - 20 GHz
LQW2UAS1R5G0C	1500	±2%	330mA	2.3	2520	General	50 MHz - 20 GHz
LQW2UAS1R5J0C	1500	±5%	330mA	2.3	2520	General	50 MHz - 20 GHz
LQW2UAS1R8G0C	1800	±2%	300mA	2.6	2520	General	50 MHz - 20 GHz
LQW2UAS1R8J0C	1800	±5%	300mA	2.6	2520	General	50 MHz - 20 GHz
LQW2UAS2R2G0C	2200	±2%	280mA	2.8	2520	General	50 MHz - 20 GHz

品番	インダクタンス (nH)	インダクタンス 許容差	定格電流 (温度上昇に基づく場合)	直流抵抗(max) (ohm)	サイズコード (mm)	用途	周波数範囲 (simulation model)
LQW2UAS2R2J0C	2200	±5%	280mA	2.8	2520	General	50 MHz - 20 GHz
LQW2UAS2R7G0C	2700	±2%	290mA	3.2	2520	General	50 MHz - 20 GHz
LQW2UAS2R7J0C	2700	±5%	290mA	3.2	2520	General	50 MHz - 20 GHz
LQW2UAS3R3G0C	3300	±2%	290mA	3.4	2520	General	50 MHz - 20 GHz
LQW2UAS3R3J0C	3300	±5%	290mA	3.4	2520	General	50 MHz - 20 GHz
LQW2UAS3R9G0C	3900	±2%	260mA	3.6	2520	General	50 MHz - 20 GHz
LQW2UAS3R9J0C	3900	±5%	260mA	3.6	2520	General	50 MHz - 20 GHz
LQW2UAS4R7G0C	4700	±2%	260mA	4	2520	General	50 MHz - 20 GHz
LQW2UAS4R7J0C	4700	±5%	260mA	4	2520	General	50 MHz - 20 GHz
LQW2UAS5R6J0C	5600	±5%	240mA	4	2520	General	1 MHz - 20 GHz
LQW2UAS6R8J0C	6800	±5%	200mA	4.9	2520	General	1 MHz - 20 GHz
LQW2UAS8R2J0C	8200	±5%	170mA	6	2520	General	1 MHz - 20 GHz
LQW32FT2R2M0H	2200	±20%	1000mA	0.19	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT2R7M0H	2700	±20%	975mA	0.22	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT3R3M0H	3300	±20%	950mA	0.24	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT4R7M0H	4700	±20%	850mA	0.28	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT100M0H	10000	±20%	700mA	0.4	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT220M0H	22000	±20%	550mA	0.62	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT470M0H	47000	±20%	500mA	0.9	3225	Powertrain/Safety	1 MHz - 20 GHz
LQW32FT220M2H	22000	±20%	430mA	0.81	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT1R6M8H	1600	±20%	1400mA	0.06	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT2R2M8H	2200	±20%	1370mA	0.07	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT3R6M8H	3600	±20%	1000mA	0.12	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT4R7M8H	4700	±20%	900mA	0.14	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT6R8M8H	6800	±20%	850mA	0.16	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW32FT100M8H	10000	±20%	650mA	0.24	3225	Powertrain/Safety	50 kHz - 20 GHz
LQW43FT100M0H	10000	±20%	1000mA	0.13	4532	Powertrain/Safety	50 kHz - 20 GHz
LQW43FT180M0H	18000	±20%	845mA	0.16	4532	Powertrain/Safety	50 kHz - 20 GHz
LQW43FT220M0H	22000	±20%	700mA	0.18	4532	Powertrain/Safety	50 kHz - 20 GHz